

SGH-A867

P O R T A B L E Q u a d - B A N D
M O B I L E P H O N E

User Manual

**Please read this manual before operating your
phone, and keep it for future reference.**



Intellectual Property

All Intellectual Property, as defined below, owned by or which is otherwise the property of Samsung or its respective suppliers relating to the SAMSUNG Phone, including but not limited to, accessories, parts, or software relating there to (the "Phone System"), is proprietary to Samsung and protected under federal laws, state laws, and international treaty provisions. Intellectual Property includes, but is not limited to, inventions (patentable or unpatentable), patents, trade secrets, copyrights, software, computer programs, and related documentation and other works of authorship. You may not infringe or otherwise violate the rights secured by the Intellectual Property. Moreover, you agree that you will not (and will not attempt to) modify, prepare derivative works of, reverse engineer, decompile, disassemble, or otherwise attempt to create source code from the software. No title to or ownership in the Intellectual Property is transferred to you. All applicable rights of the Intellectual Property shall remain with SAMSUNG and its suppliers.

Samsung Telecommunications America (STA), LLC

Headquarters:	Customer Care Center:
1301 E. Lookout Drive	1000 Klein Rd.
Richardson, TX 75082	Plano, TX 75074
Toll Free Tel:	1.888.987.HELP (4357)

Internet Address: <http://www.samsungusa.com>

© 2008 Samsung Telecommunications America, LLC is a registered trademark of Samsung Electronics America, Inc. and its related entities.

Do you have questions about your Samsung Mobile Phone?

For 24 hour information and assistance, we offer a new FAQ/ARS System (Automated Response System) at:

www.samsungtelecom.com/support

Your phone is designed to make it easy for you to access a wide variety of content. For your protection, we want you to be aware that some applications that you enable may involve the location of your phone being shared. For applications available through AT&T, we offer privacy controls that let you decide how an application may use the location of your phone and other phones on your account. However, the AT&T privacy tools do not apply to applications available outside of AT&T. Please review the terms and conditions and the associated privacy policy for each location-based service to learn how location information will be used and protected. In addition, your AT&T phone may be used to access the Internet and to download, and/or purchase goods, applications, and services from AT&T or elsewhere from third parties. AT&T provides tools for you to control access to the Internet and certain Internet content. These controls may not be available for certain devices which bypass AT&T controls.

Licensed by Qualcomm Incorporated under one or more of the following patents: U.S.

Patent No. 4, 901, 307; 5, 056, 109; 5, 099, 204; 5, 101, 501; 5, 103, 459; 5, 107, 225; 5, 109, 390.

Openwave[®] is a registered Trademark of Openwave, Inc.

Disclaimer of Warranties; Exclusion of Liability

EXCEPT AS SET FORTH IN THE EXPRESS WARRANTY CONTAINED ON THE WARRANTY PAGE ENCLOSED WITH THE PRODUCT, THE PURCHASER TAKES THE PRODUCT "AS IS", AND SAMSUNG MAKES NO EXPRESS OR IMPLIED WARRANTY OF ANY KIND WHATSOEVER WITH RESPECT TO THE PRODUCT, INCLUDING BUT NOT LIMITED TO THE MERCHANTABILITY OF THE PRODUCT OR ITS FITNESS FOR ANY PARTICULAR PURPOSE OR USE; THE DESIGN, CONDITION OR QUALITY OF THE PRODUCT; THE PERFORMANCE OF THE PRODUCT; THE WORKMANSHIP OF THE PRODUCT OR THE COMPONENTS CONTAINED THEREIN; OR COMPLIANCE OF THE PRODUCT WITH THE REQUIREMENTS OF ANY LAW, RULE, SPECIFICATION OR CONTRACT PERTAINING THERETO. NOTHING CONTAINED IN THE INSTRUCTION MANUAL SHALL BE CONSTRUED TO CREATE AN EXPRESS OR IMPLIED WARRANTY OF ANY KIND WHATSOEVER WITH RESPECT TO THE PRODUCT. IN ADDITION, SAMSUNG SHALL NOT BE LIABLE FOR ANY DAMAGES OF ANY KIND RESULTING FROM THE PURCHASE OR USE OF THE PRODUCT OR ARISING FROM THE BREACH OF THE EXPRESS WARRANTY, INCLUDING INCIDENTAL, SPECIAL OR CONSEQUENTIAL DAMAGES, OR LOSS OF ANTICIPATED PROFITS OR BENEFITS.

Table of Contents

Section 1: Getting Started5

Setting Up Your Phone	5
Charging a Battery	7
Switching the Phone On or Off	9
Locking the Touch Screen	9
Setting Up Your Voice Mail	10

Section 2: Understanding Your Phone11

Features of Your Phone	11
Front View of Your Phone	11
Side Views of Your Phone	13
Rear View of Your Phone	14
Display Layout	14
Using the Multitasking Menu	17

Section 3: Menu Navigation19

Menu Navigation	19
Widgets	23
Widget Bar Navigation	26
Understanding the Event Widget	27

Section 4: Call Functions28

Displaying Your Phone Number	28
Making a Call	28
Making a Call from the Address Book	29
Answering a Call	30
Dialing Options	30

Video Share	30
Recent Calls	32
Call Time	35
Data Counter	35
Options During a Call	36

Section 5: Entering Text40

Text Input Options	40
Changing the Entry Method	40
Changing the Text Input Mode - Keypad	41
Using T9 Mode	41
Using Multitap Mode	42
Using Numeric	43
Using Symbols	43
Using the Handwriting Feature	44
Changing the Text Input Mode - Handwriting	45
Handwriting Mode-Entering Characters	46
Handwriting Mode-Entering Numbers	46
Handwriting Mode-Entering Symbols	47
Using the QWERTY Keyboard	48
Changing the Text Input Mode - Keyboard	48

Section 6: Changing Your Settings50

Sound Profiles	50
Normal Profile	50
Silent Profile	52

Driving Profile	53
Outdoor Profile	55
Display and Light Settings	57
Illumination	59
Time & Date	60
Phone Settings	61
Airplane Mode	65
Call Settings	66
Connectivity	67
Bluetooth Secure Mode	69
Configuring Your Phone's USB Settings	70
Network Profile Configuration	70
Applications Settings	72
Reset Settings	73
Memory Management	74
Software Update	75
Phone Information	75
Section 7: Video Features	76
Cellular Video	76
Music Videos	78
Section 8: AT&T Mobile TV	80
AT&T Mobile TV	80
Using the Mobile TV Player	82
Activating Full-Screen Mode	83
Using the Program Guide	83
Using the Options menu	84

Section 9: Understanding Your Address Book	87
Address Book Settings	87
Adding a New Contact	87
Using Contacts	91
Address Book Entry Options	92
Finding My Own Phone Number	93
FDN Mode	93
Group Settings	94
Managing Address Book Entries	95
Section 10: My Stuff	98
My Stuff Functions	98
Audio Files	99
Games & Apps	101
Pictures	102
Videos	104
Tools	104
Camera	104
Record Audio	104
Alarms	104
Calendar	105
Recent Calls	105
Tasks	105
Memo	105
Calculator	105
Converter	106
World Clock	106

Timer	106	Multimedia Store	128
Stopwatch	106	MEdia Mall Options	128
Other Files	106	Section 14: AT&T Music	129
Used Space	107	Music Player	129
Section 11: Camera	108	Shop Music	131
Using the Camera	108	Using Playlists	133
Camera and Camcorder Options	109	MusicID	136
Using the Camcorder	114	XM Radio	138
Section 12: Messaging	117	Music Videos	139
Types of Messages	117	Pandora	139
Creating and Sending Messages	117	Community	139
Additional Message Options	118	Music Applications	139
Viewing New Received Messages	119	Section 15: AT&T GPS	140
Using Message Options	120	Launching AT&T Navigator	140
Signing into Your Mobile Email	121	Using the Navigator	141
Using Instant Messaging (IM)	121	Obtaining Driving Directions	141
Deleting Messages	122	Shopping for GPS Applications	142
Messaging Settings	122	Where	142
Used Space	125	Section 16: Applications	144
Section 13: MEdia Mall	126	Tools	144
Downloading Multimedia Files	126	Camera	144
Ringtones	126	Record Audio	144
Games	127	Alarms	145
Cool Tools/Apps	127	Calendar	146
Color Graphics	127	Recent Calls	148
Answer Tones	127	Tasks	148

Memo	148	Responsible Listening	174
Calculator	148	Operating Environment	176
Converter	149	Using Your Phone Near Other Electronic Devices	176
World Clock	149	FCC Hearing-Aid Compatibility (HAC) Regulations for Wireless Devices	177
Timer	150	Potentially Explosive Environments	179
Stopwatch	150	Emergency Calls	179
Yellow Pages	150	FCC Notice and Cautions	180
Section 17: Web	151	Other Important Safety Information	180
Accessing the WAP Browser	151	Product Performance	181
Navigation Using the WAP Browser	151	Availability of Various Features/Ring Tones	182
Navigating via a URL Address	154	Battery Standby and Talk Time	182
Using Favorites	155	Battery Precautions	182
Browser Settings	157	Care and Maintenance	183
Using your History	158	Section 20: Warranty Information	185
Setting Browser Preferences	159	Standard Limited Warranty	185
About Browser	159	Index	189
Accessing the MEdia Net Homepage	160		
Accessing the MEdia Net Site	161		
Changing the WAP Profiles	161		
Section 18: Accessibility	164		
Section 19: Health and Safety Information	165		
Health and Safety Information	165		
Samsung Mobile Products and Recycling	166		
UL Certified Travel Adapter	167		
Consumer Information on Wireless Phones	167		
Road Safety	173		

Section 1: Getting Started

This section explains how to start using your phone by first configuring your hardware, activating your service, and then setting up your voice mail.

Setting Up Your Phone

Prior to use it is necessary to install both the battery and SIM into their corresponding internal compartments. The microSD card slot is also located in this same internal area.

1. Remove the battery cover by pressing down on the cover.
2. While applying pressure, slide the top portion up and away from the silver, lower portion of the phone.



Installing the SIM Card

When you subscribe to a cellular network, you are provided with a plug-in SIM card loaded with your subscription details, such as your PIN, available optional services, and many others features.

Important! The plug-in SIM card and its contacts information can be easily damaged by scratching or bending, so be careful when handling, inserting, or removing the card. Keep all SIM cards out of reach of small children.

- ▶ Carefully slide the SIM card into the SIM card socket (as shown) until the card locks into place.
 - Make sure that the card's gold contacts face into the phone and that the upper-left angled corner of the card is positioned as shown.



Note: If the card is not inserted correctly, the phone does not detect the SIM card. Re-orient the card back into the slot.

Installing the Memory Card

Your phone also supports the use of a memory card (microSD™) for data storage of such things as data, music, pictures, and video files. This type of memory card is designed for use with this mobile phone and other devices.

1. Place the microSD card into the slot (as shown).
 - Make sure the microSD's gold contact pins face downward and the card is securely inserted.



Note: The Samsung A867 has been tested to support up to an 8GB memory card.

Installing the Battery

1. Insert the battery into the opening on the back of the phone, making sure the connectors align (1).
2. Gently press down to secure the battery (2).



3. Replace the battery cover onto the back of the phone (3).
4. While applying pressure, slide the top portion towards the camera area (4) until you hear a light click.

Note: Make sure the battery is properly installed before switching on the phone.

Charging a Battery

Your phone is powered by a rechargeable Li-ion battery. The Travel Adapter is used to charge the battery, is included with your phone. Use only Samsung-approved batteries and chargers.

Note: Long backlight settings, searching for service, vibrate mode, browser use, and other variables may reduce the battery's talk and standby times.

Although you can use the phone while the battery is charging, doing so will require additional charging time.

Note: You must fully charge the battery before using your phone for the first time. A discharged battery recharges fully in approximately 4 hours.

Using the Travel Adapter

1. With the battery installed, temporarily remove the plastic cover (left side of phone) and plug in the wall charger's connector into the jack.


Important!: Verify that the handset battery is installed prior to connection. If the battery is not properly installed and the wall charger is connected, the handset may power off and on continuously, preventing proper operation.



2. Plug the flat end of the Travel Adapter into the Power/Accessory Interface connector and the other end into a standard AC wall outlet.
3. When charging is finished, first unplug the adapter's power plug from the AC wall outlet and then remove the flat end from the interface connector jack on the phone.

Note: Failure to unplug the wall charger before you remove the battery, can cause damage to the phone.

Low Battery Indicator

When the battery is weak and only a few minutes of talk time remain; the battery icon () blinks and the device sounds a warning tone at regular intervals. In this condition, your phone conserves its remaining battery power, not by turning off the backlight, but by entering the dimming mode. For a quick check of your battery level, glance at the battery charge indicator located in the upper-right corner of your device's display.

When the battery level becomes too low, the phone automatically turns off.

Note: Long backlight settings, searching for service, vibrate mode, browser use, and other variables may reduce the battery's talk and standby times.

Switching the Phone On or Off

1. Press and hold  or  until the phone switches on.



The phone launches the activation splash screen and then proceeds to search for the network. Once the network has been found, you can make or receive calls.

Note: The display language is preset to English at the factory. To change the language, use the Language menu. For more information, refer to “*Changing Your Settings*” on page 50.

2. Press and hold , until the phone switches off.

Locking the Touch Screen

1. Press  to lock the touch screen.



2. Press  again to unlock the touch screen.

Setting Up Your Voice Mail

1. In Idle mode, press , then touch and hold .



You may be prompted to enter a password.

Note: You can also access your voicemail from the onscreen keypad by touching  then pressing  or touch **Call**.


2. Follow the tutorial to create a password, record a greeting, and record your name.

Note: These steps may be different depending on your network.

Accessing Your Voice Mail

1. In Idle mode, press , then touch and hold .
2. When connected, follow the voice prompts from the voice mail center.

Accessing Your Voice Mail From Another Phone

1. Dial your wireless phone number.
2. When you hear your voicemail greeting, press .
3. Enter your passcode using the onscreen keypad.

Section 2: Understanding Your Phone

This section outlines some key features of your phone. It also displays the screen and the icons that appear when the phone is in use.





Features of Your Phone

Your phone is lightweight, easy-to-use and offers many significant features. The following list outlines a few of the features included in your phone.

- Touch screen provides quick response to a variety of in-phone menus and options
- Multitasking
- User friendly, menu driven access to features and options
- Ready access to the Internet
- Built-in Bluetooth technology
- Instant Messaging capability
- AT&T GPS Navigation functionality provides real-time navigation
- microSD card compatibility for use in data storage and access
- Games & Apps feature provides Files, Games, Organizer, Alarm, Calendar, Tasks, Calculator, World Clock, Unit Converter, Timer, and Stopwatch.


Front View of Your Phone




1. **External speaker** allows you to hear the caller and any ringtones or sounds offered by your phone.
2. **Display** shows the information needed to operate your phone, such as the received signal strength, phone battery level, time, etc..
3. **Contacts key** allows you to access your current Contacts, Groups and Favorites lists.
4. **Dial key** allows you to access the Phone Functions menu, such as Dialer, Contacts, and New Message screen.
5. **Talk/Send key** allows you to power on the phone, make or answer a call, access your History, Call Manager, and Call Block features. Press and hold to redial the last phone number.
6. **Back key** allows you to return to the previous menu. This key also allows you to return to the previous page within the Web browser.
 - While in an event, touch once to display the calendar in the Month view.
 - While on the Idle screen, pressing  also displays the calendar in the Month view.
7. **Power/End key** ends a call. Press and hold for three seconds to turn the phone on or off. While in a menu, pressing this key once cancels the current input and twice returns the phone to Idle mode.
8. **Menu key** allows you to access your phone's menu functions menu, such as Address Book, AT&T Music, AT&T GPS, MEdia Net, My Stuff, Tools, and Settings.
 - While in the Menu screen, this key is replaced with the Messaging key, whose function is to create new text messages.
9. **Light sensors** use the ambient light level to adjust both screen brightness/contrast and keypad access.
 - In a bright light condition (outdoors), the sensors cause the phone to increase the brightness and contrast for better viewing.
 - In a dark light condition (while talking on the phone) the sensors detect talk activity and lock the keypad to prevent accidental key presses.
10. **Hold key** () lets you lock or unlock the touch screen. If you receive an incoming call while the screen is locked, you can answer it by either:
 - Pressing  to receive the call without unlocking the screen.
 - Pressing  to unlock the screen and answer the call normally.


Side Views of Your Phone



- 1. Volume keys** allow you to adjust the ringer volume while in standby mode or adjust the voice volume during a call. When receiving an incoming call, briefly press down either volume key () to mute the ring tone.
 - Press and hold either volume key to reject the call and send it directly to voicemail.
- 2. Power/Accessory Interface connector** allows you to connect a Travel Charger or other optional accessories such as a USB/data cable or a hands-free headset for convenient, hands-free conversations.
- 3. Microphone** allows other callers to hear you clearly when you are speaking to them.
- 4. Illumination bar** glows using different user-defined colors depending on the event (call, alarm, text message).
 - For more information, refer to “*Illumination*” on page 59.
- 5. Camera key** allows you to both access the Picture camera menu and take pictures when you are in camera mode. Press to launch to activate the camera.

- Multitask key** () launches the multitask menu. This menu provides ready access to some of the most commonly used features such as: Call, Music Player, Main menu, MEdia Net, and Messaging.
- Earphone jack** allows you to plug in an optional headset for listening of music playback. Music can also be heard via a paired Bluetooth headset.

Rear View of Your Phone



- Camera lens** is used to take pictures and shoot videos.

Display Layout

Your display screen provides a wealth of information about the phone's status and options, as well as providing access to the new widget bar. The display has 4 main areas:



Widget bar

The Widget bar provides quick access to those functions you use most frequently (Analog Clock, Digital Clock, Dual Clock, TV, Today, Calendar, Photo, Birthday, Sound Profile, Alarm, Bluetooth, Calculator, Music player and Event). For more information about the Widget bar, see “*Widget Bar Navigation*” on page 26.

Function categories

Function categories are also shortcuts to Dial (for dialing a number), Contacts (accessing the Contacts list), and Menu (displays the icons for application access). While viewing the Main Menu, the Menu category changes to Messaging, that can be used to view and create messages.

Icons

This list identifies the symbols you'll see on your phone's display and Indicator area:



Displays your current signal strength. The greater the number of bars, the stronger the signal.



Indicates that the Airplane Mode is active. You cannot send or receive any calls or access online information.



Displays when you are out of your service area.



Displays when a call is in progress.



Displays within the lock screen when a call has been missed.



Displays within the Event Widget as a tab when a call has been missed.



Displays your battery's charge level. The more bars you see, the more power you have remaining.



Displays when your connection to an Edge network is active.



Displays when your phone is communicating with the Edge network.



Displays when your connection to a 3G network is active.



Displays when the phone is accessing services in a 3G+ (HSDPA) network. When data is being transferred, this icon animates.



Displays when your phone is communicating with the 3G network.



Displays when an internal microSD memory card is detected.



Displays when the phone is connected to a computer via a supported USB cable connection.



Displays within the Indicators area when a new text message is received.



Displays within the Event Widget as a tab when a new text message is received.



Displays within the Indicators area when a new Multimedia message is received.



Displays within the Event Widget as a tab when a new voicemail message is received.



Displays within the Event Widget as a tab when an event has been missed.



Displays within the Indicators area when a new voice mail is received.



Displays when you set an alarm to ring at a specified time. For more information, refer to “Alarms” on page 145.



Displays when Call forwarding is set to Forward always. For more information, refer to “Call Settings” on page 66.



Displays when the Sound profile is set to Normal (volume levels 1-7).



Displays when the Sound profile is set to silent or the volume has been manually lowered below level 1.



Displays when the Sound profile is set to Driving.



Displays when the Sound profile is set to Outdoor.




Displays when Bluetooth is active and a compatible device has been paired.



Displays when a Bluetooth stereo headset has been paired with the phone.

For more details on configuring your phone's settings, see “Changing Your Settings” on page 50.

Using the Multitasking Menu


This key () launches the Multitask menu that can be activated from within any active window or page on the phone. There is now no need to stop what you are doing, if you quickly want to jump out and activate another common feature.

The idea is to allow you to temporarily exit from your current location to access a group of common functions such as: Call, Music Player, Main menu, MEdia Net, and Messaging. This key keeps you from having to completely exit from your current task or window, whether that be a text message, a web page, or an active call, just to quickly do something else.


Here is an example:

You might be in the middle of typing up an email or text message, when you suddenly realize that you need to make a quick call. Typically, you would have to exit from your current message, navigate to the Idle screen, make your call (page 28), after which you would have to go back and re-create your message.


Using this same situation, all you would have to do is:

1. Press  until the you see the Multitask menu screen.
2. Touch Call, then enter your number and continue the call.
3. Once you are done, hang up the call normally and you are returned to the previous message screen.

Multitask Functions

Pressing the Multitasking key () on the right side of the handset, allows you to choose from one of the following functions:

- **Call:** allows you to make a voice call while using the handset for other tasks. If Music Player is active, it is muted during the call.
- **Music Player:** allows you to launch the Music Player while using the handset for other tasks. If an incoming call is received or you want to make a call, the Music Player is muted.
- **Main menu:** allows you to quickly access the Main menu.
- **MEdia Net:** allows you to launch the MEdia Net browser while using the handset for other tasks.
- **Messaging:** allows you to send a text or multimedia message while using the handset for other tasks.
- **Back:** exits the Multitask menu and returns you to your previously active menu or page.



Section 3: Menu Navigation

This section explains the menu navigation for your phone. The A867 has done away with the need for navigation wheels or keypads. The A867 is completely navigable by either an onscreen touch or scroll.

- Touching an onscreen option activates the feature.
- Long menu list can be easily viewed by either using your fingertip to scroll either up or down the onscreen list, or pressing the volume keys up or down.

Menu Navigation

You can tailor the phone's range of functions to fit your needs using both menus and widgets. Menus, sub-menus, and features can be accessed by scrolling through the available onscreen menus.

Locking and Unlocking the Phone




When the device is locked, press **HOLD** to unlock the A867 and display the Idle screen.

The Idle screen provides access to a wealth of phone features, including popup Widgets and Menu tabs (Dial, Contacts, and Menu).



Opening an Application


► Tap the associated onscreen icon.

- Press  to exit from the current menu and return to the previous screen.
- Press  to exit from the current location/function, cancel your input and return to the Main Menu.
- Press  twice to return to the Idle screen.

Navigating Through Menus

As you navigate through a menu, options display on the screen as scrollable lists. Menu tabs (located at the bottom of most screens, provide access to additional screen options).


To navigate a scrollable list:

1. From the Idle screen, touch .
2. Touch and gently press an onscreen option.
3. From the available list of options you can either:
 - Touch an onscreen entry to activate it.
 - Firmly press and slide your finger up or down the screen to scroll through lists of menu items.
 - Navigate through a long list by pressing either volume key up or down.

Note: Tapping or touching individual entries on the list opens the list entry.




Note: Scrolling requires that you press firmly on the screen then drag. When scrolling through a list (see below) make sure not to touch or press individual entries on the list as this will open the list entry.



Accessing the Phone's Main Menu

Once you display a menu list, tapping an item causes different functions, depending on its function. For example, you can open another list, add text to a message, send a message, play a song, or view a photo.


1. Touch  → Settings.



2. Scroll through the list to then touch/activate the desired phone function.


Using the Power Search Tab

Within the Contacts list (sorted alphabetically) the **Power Search** tab allows to quickly “thumb through” the alphabetical listing of entries by first letter (A → B → C, etc...). The **Power Search** tab is located along the left side of the screen and Contacts entries are then selected by pressing their name fields.



Scrolling Through Field Entries


Some screens will ask you to assign a value to an onscreen field by either touching the up/down selection arrows or by quickly sliding through these values by using your fingertip. An example of these actions can be found on the Alarm page.

1. Touch  → **Tools** → **Alarms** → **Create Alarm**.
2. Touch the **Alarm Time** field and then adjust the hour and minutes values by using either the up/down input arrows or by quickly sliding your fingertip over the numbers.



Widgets

The Widget bar provides quick access to mini-programs (widgets). This bar (located at the left of the Idle screen) gives you information at a glance and provides easy access to frequently used tools such as (Analog Clock, Digital Clock, Dual Clock, TV, Today, Calendar, Photo, Birthday, Sound Profile, Alarm, Bluetooth, Calculator, Music Player and Event). This bar makes great use of the available space on your A867. The Widget bar is a pane on the side of the display screen that houses user-selected mini-applications and keeps them organized and always accessible.



You can easily customize the Widget bar by allowing you to keep these mini-apps docked within the bar itself or they can also be undocked by dragging anywhere onto your Idle screen.

Adding and Deleting Widgets

To select which items are displayed or hidden within the Widget bar:

1. From Idle mode, touch  → **Settings → Display and Light → Widget**.
2. Touch the check box to place a check mark next to the Widget you want to display.

Note: By default all widgets are checked and will display on the Widget bar.

– or –

Touch the check box again to remove the check mark and hide the Widget.

The following table contains a description of each available Widget, its function, and how to navigate to that particular application. If the application is already described in another section of this user manual, only a cross reference is then provided.



Analog Clock: displays the current time on an analog clock.

- Touch, drag and drop the Analog clock onto the desktop to view the time in an analog format.



Digital Clock: displays the current time on a digital clock.

- Touch, drag and drop the Digital clock onto the desktop to view the time in a digital format.



Dual Clock/World Clock: displays current time in other user-defined international locations and find out what time it is another part of world.

- Touch, drag and drop the World clock onto the desktop to view the time in dual locations. For more information, refer to “*World Clock*” on page 149.



MobileTV: allows you to watch television shows on you device.

- For more information, refer to “*AT&T Mobile TV*” on page 80.



Calendar: allows you to access the Calendar feature.

With the Calendar feature, you can:

- Consult the calendar by month, week, or day.
- Set schedules and note anniversaries.
- Write memos to keep track of your schedule.
- Set an alarm to act as a reminder, if necessary.
- For more information, refer to “*Calendar*” on page 146.



Photo: allows you to view the list of photos downloaded from the web server, received in messages, or taken by the camera. You can then assign the image as the current wallpaper.

- For more information, refer to “*Using the Camera*” on page 108.



Birthday: displays an onscreen alert for a birthday occurring today on the calendar. These dates have been previously entered for an entry within the Address Book on the day assigned for that person's birthday.

- For more information, refer to *“Adding a New Contact”* on page 87.
- For more information, refer to *“Understanding the Event Widget”* on page 27.



Sound Profile: allows you to quickly modify your current sound Profile.

- For more information, refer to *“Sound Profiles”* on page 50.



Alarm: allows you to access alarm settings.

- For more information, refer to *“Alarms”* on page 145.



Bluetooth: From this application you can activate Bluetooth and configure it so other Bluetooth devices can see your device by name.

- Touch, drag and drop, then tap the Bluetooth icon to launch the Bluetooth application.
- For more information, refer to *“Bluetooth”* on page 67.



Calculator: allows you to use a built-in calculator.

- For more information, refer to *“Calculator”* on page 148.



Today: displays the current date (day/month/year).



Music Player allows you to play music files stored on the phone and control their playback.

- Touch, drag and drop, then Tap the Music Player icon to launch the Music player. For more information, refer to *“Music Player”* on page 129.
- Touch the arrows on the widget to control the playback of the currently active song.

Widget Bar Navigation

You can drag the widgets to the desktop to use the application or feature, then drag it back to the Widget Bar when you are finished.

Note: Many widgets can be used directly from the widget bar without dragging them onto the screen (ex: Bluetooth and Alarms).

Accessing the Widget Bar

1. Tap the Widget bar tab, located on the left side of the main display to open the widget (quick access) bar.
2. Tap the Widget bar tab again to close the widget bar.

Undocking Widgets

You can easily customize the Widget bar by either keeping these mini-apps docked within the bar itself or undocking them by dragging anywhere onto your Main display screen.

1. Touch and hold the widget (1).
2. While still holding the icon, in a single motion, drag it over to the new location and release your finger from the screen (2). The application is now located in another menu or in the case of this example, on the Main display screen.



Rearranging Widgets

You can also customize the Widget bar by arranging the location of your current widgets. This can help you place your frequently used (favorite) widgets at the top of the list.

1. Touch and hold the widget (1).
2. While still holding the icon, in a single motion, drag it away from the widget bar (2) then drag it back into its new location in the list.

Activating a Widget

1. Locate your widget (whether it is still docked in the Widget bar or in another location).
2. Touch the icon to activate the mini-application (widget).

Scrolling Through the Widget Bar

Although the Widget Bar contains a number of widgets, it can only display seven or eight widget icons at one time on the bar.

► Use your fingertip to scroll up and down along the Widget bar.

Tip: Flick the screen in an upward motion to quickly scroll through the list.

Understanding the Event Widget

The Event Widget is an area that displays on the screen to inform you of calendar events, missed calls, or when new messages have been sent to the phone. The following is a description of these onscreen notification tabs:



Displays within the Event Widget as a tab when a new text message is received.



Displays within the Event Widget as a tab when a call has been missed.




Displays within the Event Widget as a tab when a new voicemail message is received.



Displays within the Event Widget as a tab when a scheduled event has been missed.



Displays within the Birthday Widget (see below) when a birthday event (assigned within the Contact entry) is within 29 days of the current day.



Indicators Area

Event Widget (with tabs)

Birthday Widget

Section 4: Call Functions




This section describes how to make or answer a call. It also includes the features and functionality associated with making or answering a call.

For more information, refer to “*Call Settings*” on page 66.

Displaying Your Phone Number






- Touch  → **Settings** → **Phone Information**.

Making a Call

1. From the Idle screen, touch  and use the onscreen keypad to enter the number you wish to dial.
2. Touch  or press .




Note: When you activate the **Auto Redial** option in the Voice Call menu, the phone will automatically redial up to 10 times when the person does not answer the call or is already on the phone. For more information, refer to “*Call Settings*” on page 66.

Making an International Call

1. Touch , then touch and hold . The + character appears.
2. Use the onscreen keypad to enter the country code, area code, and phone number.
 - If you make a mistake, touch  until the desired numbers have been deleted.
3. Touch  or press .

Correcting an Entered Number

Use the following steps to correct a mis-typed entry when dialing.



1. After entering a number using the keypad.
 - If you make a mistake, touch  to erase a single character.
 - Press and hold  to erase the entire string of numbers.
2. Press  to return to the Idle screen.

Ending a Call


- Press  key.

Dialing a Recent Number

All incoming, outgoing and missed calls are recorded in the **Calls** menu. If the number or caller is listed in your Address Book, the associated name also displayed.

1. From the Idle Screen, briefly press .
2. Find the number by touching the drop down arrow to the right to view the call logs from the various options screens. Choose from: **All**, **Missed**, **Made**, or **Received**.
3. Touch  next to the desired phone number (or entry name if already in your Address Book).


– or –

From the entry's **Details** page, touch **Call** or press  to dial the number.

Note: Press and hold  to redial the last number.

To call the selected number

To save the number to the Address Book




Making a Call from the Address Book

You can store phone numbers that you use regularly on the SIM card or in the phone's memory. These entries are collectively called the **Address Book**.

For further details about the **Address Book** feature, see *"Finding an Address Book Entry"* on page 91.

Answering a Call

When a call is received the phone rings and displays the caller's phone number, or name if stored in the Address Book.

1. From the Incoming call screen, press .
 - If the Any Key option is activated (**Settings** → **Calls** → **General** → **Call Answer**), you can press any key to answer a call except




Note: To reject an incoming call, press and hold either Volume key on the left side of the phone. A quick press of a Volume key silences the ringer on an incoming call.

2. End the call by pressing .

Note: You can answer a call while using the Address Book or other menu feature. After ending the call, the phone returns to the previously active function screen.

Other Answering Options

When receiving an incoming call:

- ▶ Briefly press down either volume key () to mute the ring tone.
- ▶ Press and hold either volume key to reject the call and send it directly to voicemail.

Dialing Options

From the Idle screen and Main menu, you have the option to access the Dialer and initiate a call. When you manually enter numbers from the Dialer, you will see three dialing options displayed on the screen.





- **Call:** dials the current number entered using the onscreen keypad.
- **Send Message:** to create a new text message and address it to either a manually entered number or a current entry from your Address Book.
- **Create Contact:** to store the current phone number into your Address Book as either a new entry or an updated number.

Video Share

The Video Share features allows you to place a call and share live or recorded video while on the call. You can initiate or receive video by using the following steps.

Initiating and Receiving a Video Share Session

To initiate and receive a Video Share session:

1. From the Idle screen, touch  and use the onscreen keypad to enter the number you wish to dial.
2. Touch  or press .
3. Once the call is answered, if you're both capable of Video Sharing, the Video Share icon appears on the screen and turn from grey to black ( Video Share Ready).

4. Touch the **Video Share** onscreen button to invite the other party to see video shot from your phone. “**Establishing a Video Connection**” displays. A message is sent to the recipient “**###-###-#### Wants to Share Video With You.**”

Important! When establishing a Video Share session, only the sender of the video clip can save the file.

5. The recipient will receive a Video Share pop-up to either **Accept** or **Decline** the **Video Share** call. They should press the **Accept** soft key to continue or **Decline** soft key the invitation.
6. If the **Auto Record** option is **On**, a **Recording Started** popup displays showing the memory available for the video.

Note: The **Auto Record** option (page 72) must be enabled for this popup to be displayed.

7. During a Video Share session, the following functions are displayed as icons on the screen. Touch the corresponding icon to activate the feature. Once selected, the following options display above the right soft option key:



Stop: to stop the video share feature.



Brightness: to adjust the brightness for the video.



Landscape: to rotate the picture from Portrait to Landscape mode. Press any key to revert back to Portrait.



Rotate: to rotate from Portrait to Landscape, when Video Share is selected from the Camcorder options.



Mute: Select this icon to turn the audio off.

Tip: To stop the video share call press the **Options** soft key and press the **Select** the “**Video Share End**” soft key.

8. A pop-up message displays “**Video Sharing has been Stopped. Save the Recorded Video?**” If accepted, the recorded videos are stored in the **My Stuff → Video** folder.

Video Share (In-Call)

You can begin a **Video Share** call during an existing call by touching **Video Share** → **Live**.



Play a Video Share Recording

During a call (while not in a **Live Video Share** session) you can share a recorded video for the recipient.

1. Touch **Video Share** → **Recorded** and then select from the available files in your **Videos** folder.
2. To make the connection, the recipient should press **Accept** and the Video begins to play on both phones.

Recent Calls

The phone stores the numbers of the calls you've dialed, received, or missed in the **Calls** menu. You can access this menu by from the Idle screen by doing one of the following:

1. Briefly press .
– or –
Touch  → **Tools** → **Recent Calls**.
2. Touch the drop-down list located at the top right of the screen to select from **All**, **Missed**, **Made**, or **Received**.

If the number or caller is listed in your Address Book, the associated name is displayed.


Viewing All Calls

1. From the **Recent Calls** menu, touch the drop-down and select the **All** option. All calls made, received, and missed are listed.
2. Touch an entry from the list to view the following options:
 - **Details:** (located at the bottom of the page) allows you to see the number of the sender, the date and time of the call, the length of the call, and the contact's name, if listed in your Contact List.
 - **Call:** allows you to return the call automatically.
 - **Video Share:** allows you to set up a Video Share call with the caller, if their handset is Video Share enabled.
 - **Send Message:** allows you to send a text or Multimedia message to the caller.
 - **Save:** allows you to save the number to your Address Book on either the phone or SIM card.
 - **Block Caller:** allows you to add the sending number to your Reject List, where incoming calls are sent directly to voice mail.
 - **Delete:** allows you to delete the selected call or All calls.

Viewing Missed Calls

The number of calls you have missed is displayed on the Idle screen.

1. Touch the onscreen **Missed Calls** dialog. The most recently missed calls are displayed.



Note: If there is a voicemail sent by the same number, associated icons are displayed and can then be selected.

2. Scroll through the list of missed calls.
3. To move to another call type, touch the call drop-down list (upper right of Calls page) and make your selection.


Viewing the Details of a Missed Calls

To view the details of a selected missed call, use the following steps:

1. Touch the **Missed Calls** dialog. A list of the most recently missed calls is displayed.
2. Touch the desired missed call. Information for that caller is then displayed within a Missed Calls page. For more information regarding the available options, see “*Viewing All Calls*” on page 32.

Calling Back a Missed Call

To call back a missed call number:

1. Touch **Call** (if there was only a single missed call) or touch the **Missed Calls** dialog. A list of the most recently missed calls is displayed.
2. Touch the desired missed call.
3. Touch either **Call** or press .

Saving a Missed Call to your Address Book

1. Touch the **Missed Calls** dialog. A list of the most recently missed calls is displayed.
2. Touch the desired missed call.

Note: You may see different choices depending upon the settings for your “Save New Contacts to” option.

3. Touch **Save → New**.

For further details about the **Address Book** feature, see “*Adding a New Contact*” on page 87.

Sending a Message to a Missed Call

1. Touch the **Missed Calls** dialog. A list of the most recently missed calls is displayed.
2. Touch the desired missed call.
3. Touch **Send Message**.
4. At the “Create” screen, touch the empty text field and use the onscreen alphanumeric keys to type in a message.
5. When you are done with your message, touch **OK**.


6. To add additional recipients, touch the yellow recipients field. Insert new recipients by:
 - Pressing the yellow field and then entering the number manually.
 - Selecting from **Recent Contacts** to choose your recipient.
 - Select an entry from your **Contacts** list.
 - Selecting members of a **Group**.
7. Touch **Send** to initiate delivery.



Deleting a Missed Call

1. Touch the **Missed Calls** dialog. A list of the most recently missed calls is displayed.
2. Touch **Delete**.
3. Place a check mark adjacent to those entries you wish to select for deletion.
 - Touching **All** toggles the placement of a check mark next to every entry in the list.
4. Touch **Delete**.

Note: You can press  at any time to exit the **Missed Call** feature.


Call Time



1. Touch  → **Tools** → **Recent Calls** → **Call Manager** → **Call Time**.
2. Choose from one of the following options:
 - **Last Call Duration:** shows the length of time for the last call.
 - **Total Dialed:** shows the total length of time for the calls made.
 - **Dialed Voice Calls:** shows the total length of time for all voice calls made.
 - **Dialed Data Calls:** shows the total length of time for all data calls made.
 - **Total Received:** shows the total length of time for the calls received.
 - **Received Voice Calls:** shows the total length of time for all voice calls received.
 - **Received Data Calls:** shows the total length of time for all data calls received.
 - **Total Call Duration:** shows the total length of time for all calls made and received.
3. Reset these fields by touching **Reset All**.
4. Touch **Yes** to confirm the reset or **No** to cancel the operation.

5. Enter the user-defined password and touch **Confirm** to reset all counters. For more information, refer to “*Change Phone Password*” on page 64.
 - Press  or  to cancel this operation.

Data Counter

Data Counter refers to the amount of data (volume) to and from the phone.

1. Touch  → **Tools** → **Recent Calls** → **Call Manager** → **Data Counter**.
2. Choose from one of the following options:
 - **Last Sent:** shows the size of the last data packet (measured in KB - kilobytes) sent by the phone since the last time this counter was reset.
 - **Last Received:** shows the size of the last data packet (measured in KB - kilobytes) received by the phone since the last time this counter was reset.
 - **Total Sent:** shows the size of the total data packet (measured in KB - kilobytes) which have been sent by the phone since the last time this counter was reset.
 - **Total Received:** shows the size of the total data packet (measured in KB - kilobytes) which have been received by the phone since the last time this counter was reset.



- To set these counters back to zero, touch **Reset**.
 - Place a checkmark adjacent to those individual fields you would like reset.
 - Touch **All** to place a checkmark adjacent to all fields.
- Enter the password and touch **Confirm** to reset all counters. For more information, refer to “*Change Phone Password*” on page 64.
- Press  or  to cancel this operation.

Options During a Call

Your phone provides a number of control functions that you can use during a call.

Adjusting the Call Volume

During a call, to adjust the earpiece volume, use the **Volume** keys on the left side of the phone.

- ▶ Press  to increase the volume level and press  to decrease the volume level.

In Idle mode, you can also adjust the ringer volume using these same keys.

In-Call Options



During an active call there are several functions available by touching a corresponding onscreen button.

- **Spkr On/Off** routes the phone’s audio through either the speaker or through the earpiece.
 - Touch **Spkr On** to route the audio through the speaker. (You can adjust the speaker volume using the volume keys.)
 - Touch **Spkr Off** to use the phone’s earpiece.
- **Mute/Unmute** turn the onboard microphone either on or off.
 - Touch **Mute** during a call to mute the microphone.
 - Touch **Unmute** to unmute the microphone.
- **Video Share** lets you share video during an active call. For more information, refer to “*Video Share*” on page 30.
- **Dial** to display the onscreen keypad, where you can choose to Save the entered number to your Address Book, Send a new text message, or initiate a new call.
- **Hold** to place the current active call on hold.
- **More** to access additional in-call options such as:
 - **Address Book** to display your current Address Book entries.
 - **Save to Address Book** to store the current phone number into your Address Book.
 - **View Address Book Details** to view the detail information for the current Address Book entry. This function is only available when the number was previously entered into the Address Book.




- **Send Message** to send a new text message.
- **Memo** to create a new memo during the active call.


Placing a Call on Hold

You can place the current call on hold at any point during a conversation. You can also make another call while you have a call in progress if your network supports this service.

1. While on a call, touch . This action places the current caller on hold (which is displayed onscreen as a greyed-out box).
2. You can later reactivate this call by touching .



To making a new call while you have a call in progress:

1. While on a call, touch .
2. Touch  and enter the new phone number or look it up in the Address Book.
3. Press  to dial the second number.
- or -



Touch . Once connected, each call is displayed within either an **In call** or **On hold** tab.

Switching Between Calls

When you have an active call and a call on hold, you may switch between the two calls, changing the one on hold to active and placing the other on hold.

1. Touch .
 - The current call (caller #2) is placed on hold and the previous call on hold (caller #1) is then reactivated so that you can continue conversing with that person.
2. Press  to end the currently active call.

To end a specific call:


1. Press the associated tab (**In call** or **On hold**).
2. Touch  to end the specific call.
3. Press the  key to end the remaining call.

Note: The caller currently on hold appears within the **On Hold** tab.



Using the Speakerphone During an Active Call

While in an active call, it is possible to enable the speakerphone feature.

1. Dial the number and press .
2. Once the call is answered, touch **Spkr On** to activate the speakerphone.
3. Use the **Volume** keys (located on the left side of your phone) to adjust the volume.

Important! For more information, see “Responsible Listening” on page 174.

Switching off the Microphone (Mute)

You can temporarily switch your phone’s microphone off, so that the other person cannot hear you.

Example: You wish to say something to person in the room, but do not want the person on the phone to hear you.

Note: If you are already in Video Share or you have a call on hold, you need to select Mute/Unmute.

To switch the microphone off temporarily during a call:

1. Touch **Mute**. The option is then replaced with **Unmute**.
2. Touch **Unmute** to deactivate the Mute function and reactivate the microphone.

Searching for a Number in Address Book



1. During the active call, touch **More** → **Address Book**.
2. Touch the Address Book entry.

For further details about the **Address Book** feature, see “Finding an Address Book Entry” on page 91.



Call Waiting

The Call Waiting feature allows you to answer an incoming call while you have a call in progress, if this service is supported by the network, and you have set the **Settings → Calls → Voice Call → Call Waiting** Menu to **Activated**. You are notified of an incoming call by a call waiting tone.

To answer a call while you have a call in progress:

1. Press  to answer the next incoming call. The first call is automatically put on hold.
2. To switch between the two calls, touch .
 - **Swap**: Places the current call on hold and then activates the previous call.

To end a call on hold




1. Touch the On hold tab and touch  adjacent to the caller you wish to disconnect.
2. Press  to end the current active call.

3-Way Calling (Multi-Party Calling)

The 3-Way or Multi-Party feature allows you to answer a series of incoming calls and place them on hold. If this service is supported by the network, all calls can be joined together. You are notified of an incoming call by a call waiting tone.

Note: The **Join** option combines all of the calls you have established with your phone (both active and on hold).
Swap places the current call on hold and then activates the previous call.

This feature joins all of the calls you have established with your phone (both active and on hold) into a multi-party call.

1. Press  to answer the first incoming call.
2. Press  to answer the next incoming call. The first call is automatically put on hold.
3. Join the first two callers by pressing touching **Join**.
 - **Join**: combines your current set of callers into a single multi-party call (both active and on hold).
4. Press  to end the call.

Section 5: Entering Text

This section outlines how to select the desired text input mode when entering characters into your phone. This section also describes how to use the T9 predictive text entry system to reduce the number of key strokes associated with entering text.

The A867 comes equipped with an orientation detector that can tell if the phone is being held in an upright (Portrait) or sideways (Landscape) orientation. This is useful when entering text. If the phone is sideways, an onscreen keyboard is displayed. When upright, only the alphanumeric keypad is shown.

The A867 not only provides several on screen keypad/keypad text entry options, but also provides handwriting recognition to make the task of text entry that much easier.

Text Input Options

Your phone has the following text input modes:

- **T9** (T9Ab): this mode allows you to enter words with only one keystroke per letter. Each key on the keypad has more than one letter; for example, touching **5** can enter J, K, or L. However, the T9[®] mode automatically compares the series of keystrokes you make with an internal linguistic dictionary to determine the most likely word, thus requiring far fewer keystrokes than the traditional ABC mode.

- **Multitap** (Abc): this mode allows you to enter letters by touching the key labeled with the letter you want repeatedly, and then selecting the character from the available series of onscreen characters.
- **Numeric** (123): this mode allows you to enter numbers.
- **Symbols** (SYM): this mode allows you to enter symbols, such as punctuation marks.
- **Emoticons** (SYM): this mode allows you to scroll through pages of emoticons and then select one for insertion into your message.


When you are in a field that allows character entry, the text input mode indicator displays on the upper right portion of the screen.

Changing the Entry Method






The A867 can detect the orientation of the phone and adjust the text input screen accordingly. If the phone is detected in a Portrait (upright) orientation, only the alphanumeric keypad is shown. If the phone is turned on its side, the screen displays a full keyboard (page 48). The following will describe entering text in the portrait mode. For more information on entering text in Landscape mode, see *“Using the QWERTY Keyboard”* on page 48.

Changing the Text Input Mode - Keypad

When using your phone, you often need to enter text, such as when storing a name in your Contacts List, creating your personal greeting or scheduling events on your calendar. You can enter alphanumeric characters by using your phone's keypad.

1. From a screen where you can enter text, touch the text entry field.
2. From the onscreen keypad, touch  to change the Text Input mode.


Example: Writing a text message.

1. To change the text input mode, touch the **Text Input Mode** button (bottom center button) and select one of the following options:
 - T9 Predictive text ()
 - Multitap ()
 - Numeric ()
 - Symbols ()
 - Emoticons ()
2. Touch the text mode you desire. The text mode changes to the mode you touched.

Using T9 Mode

T9 is a predictive text input mode that allows you to key in any character using single keystrokes. This text input mode is based on a built-in dictionary.

To enter a word in T9 mode:


1. Touch the Text Input Mode button at the bottom of the screen and touch and select **T9 Predictive text** () .

When in T9 mode, start entering a word by touching the **2** to **9** keys. touch each key only once for each letter.

Example: To enter "Hello" in T9 mode, touch the 4, 3, 5, 5, and 6 keys.

The word that you are typing displays on the screen. It may change with each consecutive key that you touch.

2. Enter the whole word before editing or deleting the keystrokes.
3. When the word correctly displays, go to step 4.
 - If the word doesn't display correctly, you can then choose from possible word choices onscreen by touching the correct one.
 - If these choices do not include the word you want to use, touch the down arrow, then touch the Add Word field to then add the new word into the T9 dictionary.



Example: Both the words “Of” and “Me” have the 6 and 3 keys. The phone displays the most commonly used choice first.

4. Insert a space by touching **Space** and start entering the next word.

Note: [1 ∞] has some punctuation marks associated with it. This feature may not be available for some languages.

- To enter periods, hyphens, and other special characters, touch the Text Input button (bottom center), select **Symbols** (SYM) and then touch the corresponding key. If the symbol does not display on the initial screen, touch the left or right arrow key to display the next set of symbols.
- To shift case in T9 mode, touch **Shift** and then touch the desired letter on the keypad. There are 3 cases: Initial capital, Capital lock, and Lower case.
- You can move the cursor by touching where you want to place the cursor. To delete letters, touch [←], or touch and hold [←] key to clear the entire text string.

Using Multitap Mode

To use ABC mode, use the **2** to **9** keys to enter your text.

- ▶ Touch the Text Input Mode button at the bottom of the screen and select **Multitap** (Abc), then touch the key labeled with the letter you want:
 - Once for the first letter, twice for the second letter, and so on.
 - To shift case in ABC mode, touch **Shift**. There are 3 cases: Initial capital, Capital lock, and Lower case.

Multitap Keys

By default, the first letter of an entry is capitalized and all consecutive letters are kept in lowercase (unless you touch the Shift key). After entering a character, the cursor automatically advances to the next space after two seconds or when you enter a character on a different key.

Characters scroll in the following order (lowercase characters shown in parentheses):

1 ∞	., ' - ? ! @ : / 1
2 abc	A B C Ä Ç 2 a b c ä à ç
3 def	D E F É 3 d e f è é
4 ghi	G H I 4 g h i
5 jkl	J K L 5 j k l
6 mno	M N O Ñ Ö 6 m n o ñ ö
7 pqrs	P Q R S 7 p q r s ß
8 tuv	T U V Ü 8 t u v ü ù
9 wxyz	W X Y Z 9 w x y z

0 +

+ = < > € £ \$ % & ¥ □ 0

Space


Adds a space

Shift

Shift the case of the character.



Using Numeric


The Numeric mode enables you to enter numbers into a text message.

- Touch the **Text Input Mode** button at the bottom of the screen and select **Numeric** (), then touch the keys corresponding to the digits you want to enter.

Using Symbols

Symbol mode enables you to insert symbols and punctuation marks into text.

1. Touch the **Text Input Mode** button at the bottom of the screen and select **Symbols** (), then touch the desired symbol key.
2. To display more symbols, touch the left or right arrow key.
3. To clear the symbol(s), touch .


- Select the other letters in the same way.
 - To enter a period, @, or comma touch . ABC mode applies grammar rules to ensure correct punctuation.

You can move the cursor by touching **Space**. To delete letters, touch . Touch and hold  key to clear the display.

Tip: The cursor moves to the right when you touch a different key. When entering the same letter twice or a different letter on the same key, wait for a few seconds for the cursor to automatically move to the right, and then select the next letter.


Using the Handwriting Feature

- From a screen where you can enter text, touch the **Input Select** field (shown below) to change the screen to Hand Writing mode.
- From the drop-down list touch Handwriting to activate the handwriting recognition on the phone.



- Use your fingertip to write out each character.

Note: To properly recognize the written characters and to prevent scratching of the LCD do not use script and to prevent scratching of the LCD.



Changing the Text Input Mode - Handwriting

You can write your message using the Handwriting mode but if at any time you feel you can't remember how to input text, you can touch the **Input Select** field and select Keypad.

The available Text Input modes are: **abc**, **Abc**, **ABC**, **Numeric**, and **Symbols**. Each option causes the Handwriting mode to behave differently.

ABC

All uppercase: causes the phone to read everything being written as uppercase characters. Ex: **HI THERE**.

Abc

Initial uppercase: causes the phone to read words as having the initial character in uppercase and all consecutive characters of the same word as lower case. Ex: **Hi There**.

abc

All lowercase: causes the phone to read everything being written as uppercase characters. Ex: **hi there**.




123

Numeric: causes the phone to try and interpret all inputs as numbers. Ex: The letter **I** would be displayed as the number **1**. The word **HI** would appear as **551**.




SYM

Symbols: causes the phone to try and interpret all inputs as symbols. Ex: The letter **H** would be displayed as **+**). The word **Hi** would appear as **+)0**.

Handwriting Mode-Entering Characters

1. Touch the Text Input Mode button at the bottom of the screen and select **Abc**. The input mode indicator then changes to  which activates the Initial uppercase function.
2. Write the desired text using the stylus.
 - To change the case of the alphabetic characters touch the Text Input Mode button and select **ABC** or **abc**.
 - If you make a mistake, touch  to erase a single character.
 - Touch and hold  to erase an entire word or line.




As an example, to write “**Hi there.**” you would:

- Touch the **Text Input Mode** button and select **Abc**.  is then shown onscreen.
- Write **Hi** or **hi** (in either case the **Abc** mode causes the initial character to be uppercase while the rest are forced into lowercase.)
- Draw a line (___) across the screen to insert a space. Since there is no letter that matches this icon, the A867 inserts an empty space.
 - You could also touch the Input Select field and choose Keypad to then touch  and insert an empty space. After which return to the Handwriting mode.
- Touch the **Text Input Mode** button and select **abc**.  is then shown onscreen.



- Write **THERE** or **there** (in either case the **abc** mode causes characters to display as lowercase.)
- Touch the screen to insert a period.



Note: Draw a diagonal slash across the screen (/) to enter a paragraph return.

Handwriting Mode-Entering Numbers




1. Touch the Text Input Mode button at the bottom of the screen and select **Numeric**. The input mode indicator then changes to  which activates the number function. No alphabetic characters are recognized.
2. Write the desired numbers using the stylus.
 - If you make a mistake, touch  to erase a single character.
 - Touch and hold  to erase an entire word or line.

As an example, to write “**123 Anywhere**” you would:






- Touch the **Text Input Mode** button and select **Numeric**.  is then shown onscreen.
- Write **123**.
- Touch the **Text Input Mode** button and select **Abc**.  is then shown onscreen.
- Write **ANYWHERE** or **Anywhere** (in either case the **Abc** mode causes the initial character to be uppercase while the rest are forced into lowercase.)

- Draw a line () across the screen to insert a space. Since there is no letter that matches this icon, the A867 inserts an empty space.
- You could also touch the Input Select field and choose **Keypad** to then touch  and insert an empty space. After which return to the Handwriting mode.

Handwriting Mode-Entering Symbols


1. Touch the Text Input Mode button at the bottom of the screen and select **Symbols**. The input mode indicator then changes to  which activates the symbols function. No alphabetic or numeric characters are recognized.
2. Write the desired numbers using the stylus.
 - If you make a mistake, touch  to erase a single character.
 - Touch and hold  to erase an entire word or line.

As an example, to write “**pat@att.net**” you would:

- Touch the **Text Input Mode** button and select **abc**.  is then shown onscreen.
- Write **PAT** or **pat** (in either case the **abc** mode causes all characters to be lowercase.)
- Touch the **Text Input Mode** button and select **Symbols**.  is then shown onscreen.
- Draw @ or touch the Input Select field, choose **Keypad** to then choose from several pages of available symbols.
- Touch the **Text Input Mode** button and select **abc**.  is then shown onscreen.
- Write **ATT** or **att** (in either case the **abc** mode causes all characters to be lowercase.)
- Touch the screen to insert a period.
- Write **NET** or **net** (in either case the **abc** mode causes all characters to be lowercase.)
- Touch the Input Select field and choose **Keypad** to then touch  to insert an empty space. After which return to the Handwriting mode.
- Select  from the Symbols page to insert a new paragraph.

Using the QWERTY Keyboard

From a screen where you can enter text, rotate your phone to a Landscape orientation. Regardless of the current setting with the **Input Select** field (page 44), the onscreen QWERTY keyboard will display.



Changing the Text Input Mode - Keyboard

There are three main keyboard layout keys that will change the onscreen keys within the QWERTY keyboard.

The available Text Input modes are: **T9**, **1@**, **Emot**, **Abc**, and **EN/FR/ES**. Refer to the Text Input mode in the upper right hand corner to identify which mode you are currently in.

T9

T9: activates the T9 mode in either **abc** (all lower case) or **T9Eab** (where the keys default to lowercase until the Shift key is touched [activated]). This is achieved by repeatedly pressing the button to toggle the current state.

1@

Symbol-Numeric: activates the number and symbol keys.

Emot



Emoticons: activates the emoticon keys.

Abc

Abc: activates the default alphabet keys. This function works in conjunction with the T9 feature.

EN

Language: revamps the onscreen keyboard to conform to one of three available languages: English (**EN**), Spanish (**ES**), or French (**FR**).

1. Touch an onscreen Text Input mode button.
2. Touch a corresponding key to enter the associated character within the text field.
3. Touch either  or  to cycle through additional keys. This is only available within 123 and Emot options.
4. Touch **OK** to complete the message and return to the previous screen.


Section 6: Changing Your Settings

This section includes tips on how to use your phone's features, as well as how to change and customize the display settings, call handling, security settings, and other settings associated with your phone.

Sound Profiles

This menu allows you to specify how you are informed of incoming calls.


Selecting a Profile

1. Touch  → **Settings** → **Sound Profile**.
2. Touch the radio button next to the profile name. The selected profile activates. Choices include:
 - **Normal**
 - **Silent**
 - **Driving**
 - **Outdoor**

Normal Profile


The phone's profile defaults to Normal where the incoming Alert Type is set to melody.

Editing the Normal - Call Profile

1. Touch  → **Settings** → **Sound Profile** → **Normal**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Call**.
3. Select the **Call Alert Type** field and select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Increasing Melody**: the melody volume increases.
 - **Vibration then Melody**: the phone vibrates 3 times and then starts ringing.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Vibration & Increasing Melody**: the phone vibrates and the melody increases simultaneously.


4. Touch the **Voice Call Ringtone** field, touch to select a ringtone and touch **Save**.
5. Touch and drag the **Ringtone Volume** slider to the volume level you desire (range is 1-7).
6. Touch the **Vibration Pattern** field, then touch to select **Vibration 1 - 5**.
7. Touch **Save** to return to the Sound Profiles menu.

Editing the Normal - Message Profile

1. Touch  → **Settings** → **Sound Profile** → **Normal**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Message**.
3. Touch the **Message Alert Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates 3 times.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.

4. Touch the **Message Alert Tone** field, touch to select a ringtone and touch **Save**.
5. Touch the **Message Alert Repetition** pull-down and select one of the following options and touch **Save**:
 - **Once**: repeats the message alert once.
 - **Periodic**: repeats the message alert periodically.
6. Touch and drag the **Alert Tone Volume** slider to the volume level you desire (range is 1-7).
7. Touch the **Vibration Pattern** field, then touch to select **Vibration 1 - 3**.
8. Touch **Save** to return to the Sound Profiles menu.

Editing the Normal - Phone Profile

1. Touch  → **Settings** → **Sound Profile** → **Normal**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Phone**.
3. Touch the **Keypad Tone** pull-down and select one of the following tones and touch **Save**:
 - **Beep**

- **TouchWiz**
 - **Mute**
4. Touch the **Power On Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates but does not play a melody.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.
 5. Touch the **Power Off Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates but does not ring.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.
 6. Touch and drag the **Phone Sound Volume** slider to the volume level you desire (range is 0-7).
 7. Touch **Save** to return to the Sound Profiles menu.


Silent Profile

Silent mode is convenient when you wish to stop the phone from making noise, in a theater for example.


▶ Touch  → **Settings** → **Sound Profile** → **Silent**.

All sound tones are now changed to Silent.

Editing the Silent - Call Profile

1. Touch  → **Settings** → **Sound Profile** → **Silent**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Call**.
3. Select the **Call Alert Type** field and select one of the following and touch **Save**:
 - **Vibration**: the phone vibrates 3 times.
 - **Mute**: the phone is silent and does not play a melody or vibrate.
4. Touch the **Vibration Pattern** field, then touch to select **Vibration 1 - 5**.
5. Touch and drag the **Vibration Intensity** slider to the intensity level you desire (range is 1-7).
6. Touch **Save** to return to the Sound Profiles menu.


Editing the Silent - Message Profile

1. Touch  → **Settings** → **Sound Profile** → **Silent**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Message**.
3. Touch the **Message Alert Type** field, select one of the following and touch **Save**:
 - **Vibration**: the phone vibrates 3 times.
 - **Mute**: the phone is silent and does not play a melody or vibrate.
4. Touch the **Message Alert Repetition** pull-down and select one of the following options and touch **Save**:
 - **Once**: repeats the message alert once.
 - **Periodic**: repeats the message alert periodically.
5. Touch the **Vibration Pattern** field, then touch to select **Vibration 1 - 3** and touch **Save**.
6. Touch and drag the **Vibration Intensity** slider to the intensity level you desire (range is 0-7).
7. Touch **Save** to return to the Sound Profiles menu.

Driving Profile

In this case, the speaker is active and launches the currently selected Call alert type when the associated notification is activated.

Editing the Driving - Call Profile

1. Touch  → **Settings** → **Sound Profile** → **Driving**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Call**.
3. Select the **Call Alert Type** field and select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Increasing Melody**: the melody volume increases.
 - **Vibration then Melody**: the phone vibrates 3 times and then starts ringing.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Vibration & Increasing Melody**: the phone vibrates and the melody increases simultaneously.
4. Touch the **Voice Call Ringtone** field, touch to select a ringtone and touch **Save**.


5. Touch and drag the **Ringtone Volume** slider to the volume level you desire (range is 1-7).
6. Touch the **Vibration Pattern** field, then touch to select **Vibration 1 - 5** and touch **Save**.
7. Touch **Save** to return to the Sound Profiles menu.

Editing the Driving - Message Profile

1. Touch  → **Settings** → **Sound Profile** → **Driving**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Message**.
3. Touch the **Message Alert Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates but does not ring.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.
4. Touch the **Message Alert Tone** field, then touch to select **Message Tone 1 - 4** and touch **Save**.

5. Touch the **Message Alert Repetition** pull-down and select one of the following options and touch **Save**:
 - **Once**: repeats the message alert once.
 - **Periodic**: repeats the message alert periodically.
6. Touch and drag the **Alert Tone Volume** slider to the volume level you desire (range is 1-7).
7. Touch the **Vibration Pattern** field, then touch to select **Vibration 1 - 3** and touch **Save**.
8. Touch **Save** to return to the Sound Profiles menu.

Editing the Driving - Phone Profile

1. Touch  → **Settings** → **Sound Profile** → **Driving**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Phone**.
3. Touch the **Keypad Tone** pull-down and select one of the following tones and touch **Save**:
 - **Beep**
 - **TouchWiz**
 - **Mute**

4. Touch the **Power On Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates but does not play a melody.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.
5. Touch the **Power Off Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates but does not ring.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.
6. Touch and drag the **Phone Sound Volume** slider to the volume level you desire (range is 0-7).
7. Touch **Save** to return to the Sound Profiles menu.

Outdoor Profile


In this case, you are outdoors and might not be able to hear the phone, or need an increased volume in order to hear the phone. For example, you might be jogging and need the phone to vibrate and ring loudly.

Editing the Outdoor - Call Profile

1. Touch  → **Settings** → **Sound Profile** → **Outdoor**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Call**.
3. Select the **Call Alert Type** field and select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Increasing Melody**: the melody volume increases.
 - **Vibration then Melody**: the phone vibrates 3 times and then starts ringing.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Vibration & Increasing Melody**: the phone vibrates and the melody increases simultaneously.


4. Touch the **Voice Call Ringtone** field, touch to select a ringtone and touch **Save**.
5. Touch and drag the **Ringtone Volume** slider to the volume level you desire (range is 1-7).
6. Touch the **Vibration Pattern** field, then touch to select **Vibration 1 - 5** and touch **Save**.
7. Touch **Save** to return to the Sound Profiles menu.

Editing the Outdoor - Message Profile

1. Touch  → **Settings** → **Sound Profile** → **Outdoor**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Message**.
3. Touch the **Message Alert Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates but does not ring.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.

4. Touch the **Message Alert Tone** field, then touch to select **Message Tone 1 - 4** and touch **Save**.
5. Touch the **Message Alert Repetition** pull-down and select one of the following options and touch **Save**:
 - **Once**: repeats the message alert once.
 - **Periodic**: repeats the message alert periodically.
6. Touch and drag the **Alert Tone Volume** slider to the volume level you desire (range is 1-7).
7. Touch the **Vibration Pattern** field, then touch to select **Vibration 1 - 3** and touch **Save**.
8. Touch **Save** to return to the Sound Profiles menu.

Editing the Outdoor - Phone Profile


1. Touch  → **Settings** → **Sound Profile** → **Outdoor**.
 - Touch the name field and not the radio button to the right.
2. Touch drop-down menu (upper-right of the screen) and select **Phone**.

3. Touch the **Keypad Tone** pull-down and select one of the following tones and touch **Save**:
 - **Beep**
 - **TouchWiz**
 - **Mute**
4. Touch the **Power On Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates but does not play a melody.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.
5. Touch the **Power Off Type** field, select one of the following and touch **Save**:
 - **Melody**: the phone rings using the ring melody selected in the Ring tone menu.
 - **Vibration**: the phone vibrates but does not ring.
 - **Vibration & Melody**: the phone vibrates and plays a melody simultaneously.
 - **Mute**: the phone is silent and does not play a melody or vibrate.

6. Touch and drag the **Phone Sound Volume** slider to the volume level you desire (range is 0-7).
 - Touch **Save** to return to the Sound Profiles menu.


Display and Light Settings

In this menu, you can change various settings for the display or backlight.

1. From Idle mode, touch  → **Settings** → **Display and Light**.
2. Select one of the following options:
 - Wallpaper
 - Widget
 - Font Type
 - Greeting Message
 - Transition Effect
 - Brightness
 - Backlight Time
 - Illumination

Wallpaper

This menu allows you to change the background image displayed on the Main screen.

1. From Idle mode, touch  → **Settings** → **Display and Light** → **Wallpaper**.
2. Touch and drag an onscreen image to the left or right to view either the next or previously available images (located in your Pictures folder) for the wallpaper selection.
3. Touch one of the following options:
 - **Set**: assigns the current image as the new wallpaper image that appears when the Main screen.
 - **Pictures**: allows you to choose a photo from Pictures folder, that are displayed in a thumbnail view.


Widget

Allows you to select which widget applications will appear docked within the Widget bar on the Idle screen.

For more information, refer to “*Widgets*” on page 23.




Font Type

You can select the text style for the informational text displayed on the Main LCD.

1. From Idle mode, touch  → **Settings** → **Display and Light** → **Font Type**.
2. Select **Type1**, **Type2** or **Type3** and touch **Save**.


Greeting Message

In this menu you enter the text which displays on the main screen when the phone powers on.

1. From Idle mode, touch  → **Settings** → **Display and Light** → **Greeting Message**.
2. Touch and hold  to erase the current greeting message.
3. Use either the onscreen keypad/keyboard to enter a new greeting.
4. Touch .



Transition Effect

Allows you to activate/deactivate the default transition effect (wipe) during transitions between menu/options pages.

1. From Idle mode, touch  → **Settings** → **Display and Light** → **Transition Effect**.
2. Touch either **On** (activate) or **Off** (deactivate).

LCD Brightness



Allows you to adjust the display brightness for the LCD to see better within different lighting conditions.

1. From Idle mode, touch  → **Settings** → **Display and Light** → **Brightness**.
2. Touch and drag the **Level** slider to the brightness level you desire (range is 1-5).
– or –
Touch either **On** or **Off** (from within the **Automatic** field) to also allow the phone to use its light sensors to automatically adjust the LCD brightness.
3. Touch  .

Note: Modifying this setting will impact your battery life.

Backlight Time

The backlight turns the screen on using a preset brightness level. When the time (set in this feature) runs out, the touch screen locks. For more information, refer to “*Locking and Unlocking the Phone*” on page 19.

1. From Idle mode, touch  → **Settings** → **Display and Light** → **Backlight Time**.
2. Touch one of the backlight times to set the amount of time the phone’s touchscreen remains lit without activity. Options include: **8 Seconds**, **15 Seconds**, **30 Seconds**, **1 Minute**, **3 Minutes**, or **10 Minutes**.
3. Touch  .

Note: Modifying this setting will impact your battery life.

Illumination

This menu allows you to activate the lighting effect emitted by the phone when a certain event occurs. When active, this feature flashes a strip of color along the bottom of the phone once an event condition (such as incoming call, message, alarm, and turning the phone on/off) is met.


- From Idle mode, touch  → **Settings → Display and Light → Illumination.**



The illumination bar will activate during any of the following situations:

- When an incoming call is received
- When an incoming message is received
- When the alarm rings
- Power is turned On or Off.
- When the phone is charging (while powered off).

Time & Date

This menu allows you to change the current time and date displayed.

1. From Idle mode, touch  → **Settings → Time and Date.**
2. Touch the **Time Zone Updating** drop-down list and select one of the following:
 - **Automatic:** the phone automatically updates the time and date according to the current time zone using the network service.
 - **Manual Only:** you need to manually set the time and date according to the current time zone using the Set time menu.
 - **Prompt First:** you are prompted before a time change is applied.

3. Touch the **Time Zone** field and assign a new time zone by touching a corresponding area of the world map.
 - Touch  to save the new setting.
 - Major cities in each zone are displayed upon selection.
 - Current time zones are based upon Greenwich Mean Time.
4. Touch **12hr** (12 hour) or **24hr** (24 hour) from the **Time format** field.
5. Touch the **Time** field then adjust the hour and minutes values by using either the up/down input arrows or by quickly sliding your fingertip over the numbers to scroll through their available values.
 - Touch either **AM** or **PM**.
 - Touch  to complete the assignment.



6. Touch the **Date Format** pull-down list and select the format in which you want the date to display.
7. Touch the **Date** field then adjust the **Month**, **Day**, and **Year** values by using either the up/down input arrows or by quickly sliding your fingertip over the numbers to scroll through their available values.
 - Touch **Set** to complete the assignment.

8. Touch **Save** to store all the new Time and Date settings.

Phone Settings



You can customize various phone settings.

- ▶ From Idle mode, touch **Menu** → **Settings** → **Phone**.

Language


This menu allows you to select a display language for Text language and Text Input mode. Choose from Automatic, English, Français, and Español.

1. From Idle mode, touch **Menu** → **Settings** → **Phone** → **Language**.
2. Touch the **Screen Text** drop-down list, touch one of the following selections and touch **Save** :
 - **Automatic** (uses the language set on your SIM card).
 - **English**
 - **Français**
 - **Español**

3. Touch the **Input Language** drop-down list, touch one of the following selections and touch  :
 - English
 - Français
 - Español
4. Touch  to return to Phone settings page.

Vibration Feedback

You can set the level of intensity at which you want the vibration mode.

1. From Idle mode, touch  → **Settings** → **Phone** → **Vibration Feedback**.
2. Touch and drag the **Vibration Intensity** slider to the intensity level you desire (range is 0-4).
3. Touch **Save**.

Calibration

The Calibration feature allows you to re-align the screen's touch accuracy. Use this feature only when the device does not respond properly when you touch the screen.

1. From Idle mode, touch  → **Settings** → **Phone** → **Calibration**.

2. Touch the center of each target and repeat this step for all four targets displayed.
3. Touch **OK** from the **New settings saved...** display page.

Note: When touching the screen in Calibration mode, you must touch the center of the cross hair area.

Auto Keypad Lock

1. From Idle mode, touch  → **Settings** → **Phone**.
2. Touch **On** or **Off** from the **Auto Keypad Lock** field.

Phone Security

The Security feature enables you to restrict the use of your phone by others and to restrict the types of calls.

Various codes and passwords are used to protect the features of your phone.

- ▶ From Idle mode, touch  → **Settings** → **Phone** → **Security**.

Lock Phone

When the Phone Lock phone feature is enabled, the phone is locked and you must enter the 4 to 8 digit phone password each time the phone is switched on.

Note: You will be prompted to create a password the first time this feature is enabled.

To change the phone password, see *“Change Phone Password”* on page 64. Once you enter the correct password, you can use the phone until you switch it off.

► Touch **On** or **Off** from the **Lock Phone** field.

Lock SIM Card

When the Lock SIM Card feature is enabled, your phone only works with the current SIM. You must enter the lock code to unlock the SIM so you can use a different SIM card. Once you have entered the lock code, you are asked to confirm your password.

► Touch **On** or **Off** from the **Lock SIM Card** field.

Note: This lock code is typically the last four digits of the current phone number or can be obtained from an AT&T customer service representative.

Check PIN code

When the Check PIN code feature is enabled, you must enter your PIN each time you switch on the phone. Consequently, any person who does not have your PIN cannot use your phone without your approval.

► Touch **On** or **Off** from the **Check PIN Code** field.



Note: You can obtain your PIN from an AT&T customer service representative.

Lock Applications

Using this menu, you can lock your applications and media contents (apps, messages, images, and sounds) from being accidentally accessed, altered or deleted. Once you lock the contents, you must enter the phone's password to access the associated menus.

Note: The first time you access the password screen, you will be prompted to create a password.


1. Touch the **Lock Applications** field.
2. Touch the check box next to each application you wish to lock, or touch **All** to select all applications.
 - Applications include: Messaging, My Stuff, Recent Calls, Address Book, Calendar, Memo, IM, and Tasks.

- Touch **Save** to store your new selections.
3. Enter a new password (during the first use) using the onscreen keypad into the **New Password** field and touch .
 4. Enter the new password again and touch .

Note: To change this password, see “*Change Phone Password*” on page 64.

Fixed Dialing Mode

FDN (Fixed Dial Number) mode, if supported by your SIM card, restricts your outgoing calls to a limited set of phone numbers. When this feature is enabled, you can make calls only to phone numbers stored in the FDN list on the SIM card. For more information, refer to “*FDN Mode*” on page 93.

1. Touch **On** or **Off** from the **Fixed Dialing Mode** field.
 - **On:** you can only call phone numbers stored in the Address Book. You must enter your PIN2 to continue this configuration. You can obtain your PIN2 from AT&T’s customer service department.
 - **Off:** you can call any number.
2. Use the onscreen keypad to enter your PIN2 Code and touch .



Note: The PIN2 code is provided by AT&T. Entering an incorrect PIN2 code can cause the phone to lock, at which point, you will have to call AT&T customer service for assistance.

Change Phone Password

The Change password feature allows you to change your current phone password to a new one. You must enter the current password before you can specify a new one.

1. Touch the **Change Phone Password** field.
2. Enter the current phone password and touch .

Note: Initially, the phone will not have a password assigned, and step 2 will not be necessary. Once a password is assigned, all steps are necessary.

3. Enter the new password and touch .
4. Re-enter the same password and touch .

Note: If you change your password, be sure to write it down and keep it in a safe place. If you forget your password, your phone will require AT&T customer service to have it unlocked.

Change PIN code

This feature allows you to change your current PIN, provided that the PIN check feature is enabled. The Check Pin Code field must be active before you can access this function (page 63).

Note: This code is provided by AT&T. Entering an incorrect code can cause the phone to lock, at which point, you will have to call AT&T customer service for assistance.



1. Touch the **Change PIN Code** field.
2. Enter your PIN code and touch **Save**.

Change PIN2 code

The Change PIN2 code feature allows you to change your current PIN2 to a new one. You must first enter the current PIN2 (obtained from AT&T) before you can specify a new one. Once you have entered a new PIN2, you are asked to confirm it by entering it again.


Note: Not all SIM cards have a PIN2. If your SIM card does not, this menu does not display.

1. Touch the **Change PIN2 Code** field.
2. Use the onscreen keypad/keyboard to enter your PIN2 code and touch .


3. Enter the new PIN2 code and touch .
4. Re-enter (reconfirm) the same code and touch .

APN Control


Allows you to turn control of Access Point Names (APN) On or Off. APNs are a method by which you can access advanced communication using your handset. This advanced communication can include instant messaging, multimedia messaging, email, and Internet access. Turning On APN Control requires the PIN2 code.

1. Touch **On** or **Off** from the **APN Control** field.
2. Press  to return to the previous Phone settings page.

Airplane Mode

Airplane Mode allows you to use many of your phone's features, such as Games, Voice note, etc., when you are in an airplane or in any other area where making or receiving calls or data is prohibited. When your phone is in Airplane Mode, it cannot send or receive any calls or access online information. The () icon appears in place of the signal strength indicator when active.

1. From Idle mode, touch  → **Settings** → **Phone**.
2. Touch **On** or **Off** from the **Airplane Mode** field.

3. Press  to return to the previous Phone settings page.


Call Settings


- From Idle mode, touch  → **Settings** → **Calls**.

Adjusting the General Call Settings

1. Touch **General** and select from the following options:
 - **Show My Number:** allows you to select how your caller ID is handled when an outgoing call is initiated. This is what others see on their Caller ID screen. This value can be made blank if you do not wish your number displayed to other users.
 - **Auto Reject:** selects which numbers will be automatically sent to voicemail based on a user-created list from within the Reject List.
 - **Call Answer:** selects how your phone answers incoming calls. Selections are: Green Key, Any key, Automatic (Time - 1-5 seconds).
 - **Auto Reply:** sets up an automatic text message that is sent to the calling party when they call you.
 - Touch either **On** or **Off** to activate/deactivate the function.
 - If active (On), touch the **Reply to Send** field and use the onscreen keypad/keyboard to enter an auto reply message.

- **Call Status Tones:** allows you to activate an alert tone for one of two available status categories. Touch an option to make your selection and then touch  to store your new selection. Options include:

- **Call Connect Tone:** allows you to activate an alert tone when the a connection has been made.
- **Minute Minder:** allows you to activate an alert tone which sounds every minute the call is active.
- **Alerts on Call:** activates an alert tone for new messages being received during an active call. Touch  to store setting.

2. Press  twice return to the previous Phone settings page.

Adjusting the Voice Call Settings

1. Touch **Voice Call** and select from the following options:
 - **Call Forwarding:** incoming calls are re-routed to a secondary number that you specify. Select the condition for the call forward action:
 - **Forward Always** activates an automatic forward of all incoming calls regardless of condition.
 - **Busy** activates an forward function only when your number is currently in use and the caller receives a busy signal.
 - **No Reply** activates an automatic forward of all incoming calls after a preset amount of time (5 seconds - 30 seconds).

- **Unreachable** activates an automatic forward of all incoming calls only when you can not be reached and your phone status is set to unreachable.
 - **Cancel All** cancels all call forwarding functions.
 - **Call Waiting:** this network service informs you when someone is trying to reach you during another call. You can specify individual call waiting options for voice calls and/or data calls.
 - Touch of the available options: **Activate, Deactivate, Check Status** (checks the status of this service on your account).
 - **Auto Redial:** the phone automatically redials the last active number if the call was either cut off or you were unable to connect.
 - Touch either **On** or **Off** to activate/deactivate the function.
 - Touch  to store the new setting.
2. Press  twice return to the previous Phone settings page.



Connectivity


The phone has several communication/connection parameters which can be edited.

Bluetooth

Bluetooth is a short-range wireless communications technology capable of exchanging information over a distance of about 30 feet without requiring a physical connection. Unlike infrared, you don't need to line up the devices to beam information with Bluetooth. If the devices are within a range of one another, you can exchange information between them, even if they are located in different rooms. The following Bluetooth options are available:

Activation





1. From Idle mode, touch  → **Settings** → **Connectivity** → **Bluetooth**.
2. Touch the onscreen Bluetooth icon to activate or deactivate Bluetooth.
 - or –
 - Touch  → **Turn Bluetooth On/Off**.




Bluetooth
Inactive

Bluetooth
Active




Device Name

1. From Idle mode, touch  → **Settings** → **Connectivity** → **Bluetooth** → **My Info**.
2. Touch the **Name** field, touch and hold  to erase the current name.
3. Use the onscreen keypad/keyboard to enter the new name for this device and touch . For more information, refer to “Entering Text” on page 40.
4. Touch .

Phone's Visibility

1. From Idle mode, touch  → **Settings** → **Connectivity** → **Bluetooth** → **Visible**.
2. Touch **Yes** or **No** to enable or disable the visibility (discoverability) of your phone.
 - Your phone becomes visible to other devices when you transmit your device's name to others in your area. This allows other devices to detect your phone and request a connection. If your phone is not visible, you can still detect and connect to other devices, while still hiding yourself from others.

Connecting to Other Bluetooth Devices

1. From Idle mode, touch  → **Settings** → **Connectivity** → **Bluetooth** → **Search**.
 - Detected Bluetooth devices then appear as buttons on the Bluetooth page.
2. Touch the desired device to begin pairing.
3. Touch the **Passkey** field, enter the passkey used by the target device and touch .
4. Select a connection option and touch .
5. Once the target device accepts the pair your new device shows as connected (green) within the Bluetooth page.

Bluetooth Secure Mode

When the Bluetooth Visibility is turned on, your phone is wirelessly transmitting its phone name and status to every device within its range. This transmission can pose a security risk and incite unauthorized connection to your phone. It is recommended that you remain hidden unless necessary.

Remote SIM mode

This mode allows you to turn On or Off Remote SIM Mode. Remote SIM mode, when set to On, allows the Bluetooth phone car kit to access the contact information stored on the SIM card.

Note: There is a risk that another Bluetooth device (user) can access and modify your SIM card features and data.

1. From Idle mode, touch  → **Settings** → **Connectivity** → **Bluetooth** → **My Info**.
2. Touch **On** or **Off** from the **Remote SIM Control** field.
3. Touch **Save**.

Bluetooth Services

The Bluetooth specification is a protocol that describes how the short-range wireless technology works, whereas services describe the individual devices that are supported. These services reduce the chance that incompatible devices are allowed to connect to your phone.

- **Headset:** the Bluetooth headset enables both incoming and outgoing calls using the Bluetooth headsets.
- **Handsfree:** the Bluetooth car kit enables both incoming and outgoing calls.
- **Bluetooth Stereo Headset:** used to make calls and listen to music through the Bluetooth stereo headset.
- **Serial Port:** used to connect to other Bluetooth devices through a virtual serial port.
- **Dial up:** used to provide Internet access for Bluetooth devices through the phone's modem.
- **Basic Printing:** used to print images, text messages, personal data such as namecards and appointments, etc. through a remote Bluetooth printer.
- **File transfer:** used to transfer files to and from Bluetooth devices.
- **Object Push:** used to exchange personal data (namecards, Address Book contacts, etc.) with Bluetooth devices.
- **SIM Access:** provides access to the SIM card on the phone.

Configuring Your Phone's USB Settings

This menu selects the method of communication for the USB port.


Note: The Bluetooth feature **must first be disabled before initiating a USB connection** with the phone. Prior to connecting the USB cable to the phone, install the latest version of the PC Studio application. This application installs the necessary USB drivers onto your machine. For a free download of PC Studio, go to www.samsung.com/us/support.

1. From Idle mode, touch  → **Settings** → **Connectivity** → **Select USB Mode**.
2. Select one of the following USB modes:
 - **Ask on Connection:** causes the phone to present a "Select USB Mode" pop-up when you connect to the PC. You can then choose from either: **PC Studio**, **Media Player**, or **Mass Storage**.
 - **Samsung PC Studio:** sets PC Studio to launch as the default application when a USB connection is detected.
 - **Media Player:** sets the Media Player to launch as the default application when a USB connection is detected.
 - **Mass Storage:** allows you to utilize the onboard storage capacity of the phone to store and upload files. This option allows your computer to detect the phone as a removable storage drive.
3. Touch .

Network Profile Configuration

Your phone is wirelessly connecting to the Internet via a built in WAP browser. Connection can be made via either one of three available WAP browsers: MEdia Net, AT&T MMS (MultiMedia Server), and AT&T IMS. You need these settings to use the web browser or send MMS messages or Emails.

Use this menu to create and customize the profiles containing the settings for connecting your phone to the network. Although the active connection can be changed by the user, it is recommended that this choice be made with the assistance of either the retailer or customer service representative.

1. From Idle mode, touch  → **Settings** → **Connectivity** → **Network Profiles**.
2. Touch one of these options:
 - **MEdia Net**
 - **AT&T MMS**
 - **AT&T IMS**

Note: The MEdia Net WAP is pre-configured and cannot be altered on this screen. The AT&T MMS connection option can be edited, renamed, or deleted on this screen. Your phone is set up by default for connecting to the network. If you change the settings without first checking with your service provider, the web browser, MMS, and e-mail features may not work properly.

3. To create a new connection, touch .

– or –

To edit the existing AT&T MMS, touch this entry.

4. Select the parameter you want to edit:

- **Set Name:** enter a profile name.
- **Access Name:** edit the access point name.
- **Auth Type:** select the type of authentication used for this WAP connection: None, Normal, or Secure.
- **User ID:** enter the User ID required to connect to the network.
- **Password:** enter the user password required to connect to the network.
- **Protocol:** set the connection protocol used by the WAP browser: WAP, HTTP, or Other.
- **Home URL:** enter the URL address of the page to be used as your homepage.
- **Proxy Address:** MEdia Net set as the proxy server address and port.
- **Linger Time (sec.):** set a time period (in seconds) after which the network is disconnected if there has been no new data traffic in that time.

- **Advanced Settings:** allows you to configure some of the IP-specific information: Static IP, Static DNS, Server information, and Traffic Class.

- **Static IP:** specify if you want to manually enter an IP address. If you want the IP address to be automatically assigned by the server, remove the check mark.

- **Static DNS:** specify if you want to manually enter the Domain Name Server (DNS) address. If you want the address to be automatically assigned by the server, remove the check mark.

- **Traffic Class:** select the traffic class.

Note: The WAP settings may vary depending on the service provider.

5. Touch  to store these new settings.

IMS Settings


IMS is the method used to connect to the server in order set up the Video Share option.

1. From Idle mode, touch  → **Settings** → **Connectivity** →


IMS Settings.

2. Touch one of these options:

- **IMS Service** allows you to set the IMS service to **On** or **Off**.

Touch  to store the new setting.


Important! If you reset the IMS Service to **Off**, you will not be able to use the Video Share Option.

- **IMS Profiles** allows you to set the server that service is coming from. Select a profile, make your alterations, and touch  to store the new setting.

Important! If you change from the default **AT&T IMS**, you may not be able to use Video Sharing.

Applications Settings


The Applications Settings feature allows you to configure the functional parameters for most of the onboard applications. These applications are described in more detail within other sections of this manual.

1. From Idle mode, touch  → **Settings** → **Applications Settings**.
2. Select the type of application which you want to change:
 - **Messaging** (see page 117)
 - **Browser** (see page 157)
 - **Music Player** (see page 129)
 - **CV** (see page 76)
 - **Video Share** (see page 72)
 - **Record Audio** (see page 73)

- **Calendar** (see page 73)
- **Address Book** (see page 87).




Video Share Settings

To enable the Alerts, Auto Record, and Recording Location for Video Share, use the following steps.

1. From Idle mode, touch  → **Settings** → **Applications Settings** → **Video Share**.
2. Activate any of the following options by touching the onscreen button.
 - **Audio Alert:** allows you to turn **On** or **Off** the Video Share Alerts which displays a message and a tone.
 - **Auto Record:** allows you to turn **On** or **Off** the Auto Record which records the Video Share call.
 - **Recording Location:** allows you to set whether video recorded is stored on the **Phone** or on the microSD **Memory Card**.
3. Touch  .

Record Audio Settings

To configure the filename and maximum length for a recording.

1. From Idle mode, touch  → **Settings** → **Applications**
Settings → **Record Audio**.
2. Touch either of the following fields and edit the information:
 - **Default Name:** allows you to use the onscreen keyboard to enter a prefix name of all recorded audio files. Touch  to store the new name.
 - **Recording Time:** allows you to choose the maximum limit allowed for the recorded audio file (1 Minute, 2, Minutes, 3 Minutes, 4 Minutes, 5 Minutes, 60 Minutes, or Limit for MMS.)
3. Touch  .

Calendar Settings

To configure the starting day and view used when opening the Calendar application.

1. From Idle mode, touch  → **Settings** → **Applications**
Settings → **Calendar**.


2. Touch either of the following fields and edit the information:

- **Starting Day:** allows you choose which day mark the first day in your calendar week (Sunday or Monday).
- **View by:** allows you to choose the default view for appointments used by the Calendar application when launched (Month, Week, or Day).

3. Touch  .

Reset Settings


You can easily reset your phone to its default settings. To reset your phone:

1. From Idle mode, touch  → **Settings** → **Reset Settings**.
2. Place a checkmark next to those settings you wish reset:
 - **All:** selects all fields and places a checkmark alongside all entries.
 - **Sound Profiles**
 - **Display and Light**
 - **Phone**
 - **Alarms**
3. Touch **Reset**.
4. Enter your phone password, if prompted and touch **Confirm**.

At the “**Reset Settings?**” prompt, touch **Yes** to reset, or **No** to cancel. Once your phone has been reset to its default settings for those selected options, it will restart itself in order to incorporate the new settings.

Memory Management



You can easily check the amount of memory being used for storing data, such as messages, media, calendar data, or contacts entries. You can also delete any selected information from your phone:

1. From Idle mode, touch  → **Settings** → **Memory Management**.
2. Touch any of the following options:
 - **Clear Phone Memory**
 - **Memory Card Details**
 - **Use Space**

Clear Phone Memory

From this menu you can clear the memory for Files, Messages, Address Book entries, Calendar entries, Tasks, Memos, or All licenses. You can all select All to clear everything listed.

Note: To completely remove any personal information stored on your device, see “*Precautions for Transfer and Disposal*” on page 188.

1. From Idle mode, touch  → **Settings** → **Memory Management** → **Clear Phone Memory**.
2. Place a checkmark alongside those applications you wish to clear by touching individual applications
– or –
touch **All** to clear all the memory settings.
3. Touch .

Memory Card Details

Allows you to view specific information related to the current microSD card being used for storage.

- From Idle mode, touch  → **Settings** → **Memory Management** → **Memory Card Details**.


Note: Memory card is optional.

Check the Used Space

1. From Idle mode, touch  → **Settings** → **Memory Management** → **Used Space**.

2. Select one of the following storage categories to view the contents of a category's memory:

- **Shared Memory**
- **Messaging**
- **My Stuff**
- **Calendar**
- **Tasks**
- **Memo**
- **Address Book**

3. When you are finished, press  to return to Main menu.

Software Update

The Software Update feature enables you to use your phone to connect to the network and upload any new phone software directly to your phone.

1. From Idle mode, touch  → **Settings** → **Software Update**.
2. Follow the on screen instructions.

Phone Information

This option allows you to see the phone number on the SIM card (within the phone), the manufacturer, and the model number. This information may be necessary if talking to Customer Service in the event of a problem.

1. From Idle mode, touch  → **Settings** → **Phone Information**.
2. When you are finished, press  to return to Main menu.



Section 7: Video Features

There are a number of available video services on your A867:

- Cellular Video (CV) allows you to view pre-recorded video clips of news stories, weather forecasts, sports highlights, movie trailers, music videos and more from popular content providers.
- The AT&T MobiVJ™ provides music channels playing the latest music videos.
- AT&T Mobile TV™ provides you with real-time scheduled programming in full-length broadcast quality and sound (page 80).

Cellular Video



Your phone is equipped with a WAP (Wireless Application Protocol) browser which allows you to access the Internet and download media files directly to your phone. These media files are displayed using the built-in Media Player. Cellular Video (CV) is a media service which allows you to stream media content (Weather, News, Sports highlights, etc.) directly to your phone.

1. In Idle mode, touch  →  to launch the default CV homepage. This homepage provides you with access to content categories & settings:
 - **My Favorites:** allows you to choose from some recently uploaded video clips from among the following media providers: CNN, ESPN, HBO Mobile Preview, or Access Hollywood.

- **Video Categories:** provides some general content categories from which to begin searching for media: Entertainment, Sports, News & Weather, Music, Kids & Cartoons & HBO Mobile.
- **Customize CV:** allows you to access the CV Settings menu where you can configure most of the settings associated with CV.
- **Parental Controls:** provides you with settings which can be configured to restrict certain media content from being displayed on the phone.
- **MEdia Net:** exits from the CV application and launches the MEdia Net homepage.
- **Help:** provides basic on-line assistance which answers most of the common issues users come across while using this feature.

2. Select from one of the available categories by touching an option.

Viewing a Video Clip

1. In Idle mode, touch  →  .
2. Select the video clip by touching the entry from within the Favorites section.
3. After the stream has been buffered into memory, you can choose to either pause or play the content.
 - Touch the Pause/Play button to toggle between the two functions.

- Touch the Return button to be taken back to the CV homepage.



Using the Video Categories

This grouping of media categories provides access to an additional listing of streaming media. Where the previous Favorites list of media stream can be user edited and updated, this list of categories is defined by CV's homepage and can not be changed.

Customizing CV



Updating the Favorites List

The list of media providers which appear in the Favorites section of the CV homepage can be edited and changed by the user.

1. In Idle mode, touch  →  → **Customize CV** → **Edit Favorites**.
2. Touch the **Add to Favorites** section of the page.
3. Touch the radio box next to any of the available streaming media channels (not currently in your Favorites list [ex: Cartoon Network].) The **Manage My Favorites** section of the page then reflects these new additions.



Adding a Video Alert

When new media is available for upload to your phone (such as breaking news), you can set your phone to notify you of the new available content.

1. In Idle mode, touch  →  → **Customize CV** → **My Video Alerts** → **Add to My Alerts**.
2. Touch the radio box next to any of the available alert services listed within the Add to My Alerts section of the page (ex: Breaking News).

My Purchases

The CV homepage can be used to shop for streaming multimedia content. The **My Purchases** section can help keep track of your purchase history and view any new resale products.



1. In Idle mode, touch  →  → **Customize CV** → **My Purchases** → **Purchase History**. This provides you with an on screen listing of your “to date” purchase history for media content.
2. Touch **My Account**. This provides you with an onscreen description of your account details.

Parental Controls



Your phone can be configured to block both purchased and streamed media content. Before filtering, you must first establish a pin/password and a contact e-mail address. Once those have been established, you can the two available filter options:

- **Content Filters:** let you restrict access to inappropriate content both on and outside of MEdia Net.
- **Purchase Blocker:** lets you restrict the ability to buy ringtones, downloads, games, etc., from MEdia Net on this phone.

Setting up Parental Controls


1. In Idle mode, touch  →  → **Customize CV** → **Parental Controls** to access the MEdia Net parental setup fields.
2. Touch each of the following fields and use the onscreen keypad/keyboard to enter the information: **PIN**, **Re-enter**, **contact email address**.
3. Touch **Save** and allow a few minutes for your information to be received and accepted by MEdia Net. You can then use this information to activate the parental filters.

Configuring the Filters

1. In Idle mode, touch  →  → **Customize CV** → **Content Filters** → **On** button to toggle the On/Off state.
2. Touch **Purchase Blocker** → **On** button to toggle the On/Off state.
3. Touch **OK** to activate the filter.

Music Videos

Music Videos provides links to music video channels that are organized by music genres.

1. Touch  → **AT&T Music** → **Music Videos**.
You are then taken to the MobiVJ Music Videos application.
2. During the initial setup, touch **OK** to acknowledge the data service usage information and verify your subscription.
3. Touch **Accept** to agree to the terms of the MobiVJ service and follow the on screen prompts. A welcome video is then displayed.
4. Touch a desired video station to view music videos.

Music Video Options

While playing a music video channel, touch **Guide** to view the channel guide listing.

Note: This service requires a subscription. You will have a trial period, after which a fee will be applied.

1. Touch  → **AT&T Music** → **Music Videos** → **Guide**.
2. From the main Music Video homepage, touch **Options**.

To view Help content and access video player options, select from the following:

- **Full Screen** - enlarges the picture to fill the entire screen.
- **Get Ringtones** - allows you to purchase ringtone content associated with the video content that is currently playing.
- **Buy** - allows you to purchase a monthly subscription.
- **Mute** - silences the audio in the application.
- **Help/Settings** - provides information on how to use the application & information about subscriptions.

Viewing a Video Clip

- ▶ Touch the video clip to begin the streaming playback.

After the stream has been buffered into memory, you can choose to either Pause or play the content.

Section 8: AT&T Mobile TV



AT&T Mobile TV


The AT&T Mobile TV service allows you to watch an exciting lineup of live full-length episodes of entertainment, news, sports and kids' programming from some of the most popular networks, including CBS Mobile, CNBC, CNN Mobile Live, Comedy Central, ESPN Mobile TV, FOX Mobile, FOX News, MSNBC, MTV, NBC 2Go, Nickelodeon and PIX.

Subscribe and start watching your favorite programs immediately. The Program Guide is simple to use and navigate, allowing you to change from one channel to the next quickly and easily without progress bars and download delays.


Important! Programming and available networks are subject to change. AT&T Mobile TV services may require separate subscription and activation fees. Contact AT&T for details.

Getting Started

1. In Idle mode, touch  →  .
– or –

From the Widget bar, scroll through and touch  . Allow a few minutes for the system to launch when you start AT&T Mobile TV for the first time.

2. Follow the onscreen instructions to navigate through the onscreen guide.



3. Touch any of the following buttons to activate a function.



Move up through the available options.



Move down through the available options.





Return to the previous page.



Accept the current onscreen selection.

Subscribing to AT&T Mobile TV

You need to be in an AT&T Mobile TV coverage area to subscribe.

1. In Idle mode, touch  →  .
2. Touch **Subscribe now**. The Review Base Package screen then appears.
– or –

If you decide to **Subscribe later**, you can access the **Subscribe now** option each time you launch Mobile TV.

3. Review the basic package information and touch **Continue**.
 - If premium content is available, the **Select Premium Package** screen appears allowing you to select from additional packages.

4. Select the premium package(s) you want to add to your base package and touch **Continue**. You can choose more than one premium package at a time. The Terms of Service screen then appears.
5. Read the Terms of Service and if you agree, touch **Agree**.
– or –
Touch **Disagree** if you do not agree to the terms and you will be prompted to exit the subscription process.
6. Confirm your package subscription and touch **Submit**. Package costs are automatically added to your monthly bill.
7. Touch **Close** to return to the Player.

Note: The costs of the package(s) are automatically added to your monthly bill.

8. Edit or cancel your subscription options by accessing **Subscription Manager** from within the **Program Guide Options** menu.

Using the Mobile TV Player

While in the Mobile TV application, you will receive visual notification for incoming calls and calendar/alarm events. For all other incoming alerts, you will receive only an audible tone.



Touch any of the following onscreen buttons to navigate within the Player.



Access and display the Program Guide.



Exit the AT&T Mobile TV application.



Move up through the channels.



Move down through the channels.



View the current program in full-screen mode.




Return to the previous page.




Accept the current selection.

Activating Full-Screen Mode

You may view Mobile TV programming using the entire video screen by touching  after selecting a program.

Note: The default resolution for program viewing is 320 x 240.

- ▶ From a current onscreen program, touch . This resizes the onscreen video window to full-screen mode (400 x 240).

After selecting full-screen mode, the Player displays video at this resolution only when Player controls are not visible. If you touch the screen again, the Player controls and program title information become visible and the video resizes back to its default viewing size of 320 x 240.

Using the Program Guide

The Program Guide lists all scheduled programs, along with their respective channel names, program titles, descriptions, program ratings and show times.

Touch a program entry (onscreen buttons) from within the Program Guide to then launch that program in the Mobile TV Player. If you select a channel that is not included in your subscription package, you can add that programming package immediately by touching the onscreen **Press here for subscription info** button and following the prompts.



- ▶ Touch any of the following buttons to move through the Program Guide:



Returns to the Player with the selected program still in progress.



Launches a current highlighted program.

- You can also touch the program title to launch the program.
- This page also displays information about any future program you have highlighted



Launch the Options menu.



Move up/down through different channels in the guide and display program titles across the same time block.




Move left/right across different time blocks to see upcoming programming for a particular channel.



Display information about the current or any future programs.


Using the Options menu

You can change your subscription, set parental controls, check for updates, and refresh your subscription by accessing the Options menu.


1. From the **Program Guide** screen, touch .
2. Follow the onscreen options and make your selection by touching the corresponding onscreen button. Options include: **Subscription manager**, **Mobile TV Parental Controls**, **Check for Updates**, **Refresh Subscription**, and **About**.

Subscription manager

The Subscription manager allows you to edit or cancel your subscription, as well as view your memory usage and terms of agreement.


1. From the **Program Guide** screen, touch  to launch the **Options** menu.
2. Touch **Subscription manager** to manage your subscription and configure available options.



3. Touch  to display available options.
4. Touch **OK** after selecting your updated settings.

Mobile TV parental controls

Limits access to certain rated programs, by setting parental controls.

1. From the **Program Guide** screen, touch  to launch the **Options** menu.
2. Touch **Mobile TV Parental Controls**.
3. Touch the **Parental control on/off** field and touch **On**.
4. Use the onscreen keypad/keyboard to create a 4-digit PIN. This PIN will be required to delete, modify, or add programming packages to your subscription.
5. Touch **OK** to store the new PIN.
6. Touch **Parental control ratings** and select the rating levels for TV, movies and audio.




After settings are confirmed, the service assesses a program's rating before allowing it to be viewed. When a selected program exceeds the rating you've set, you will be prompted to enter the assigned PIN.

- Enter the incorrect or no PIN and the program cannot be viewed.
- Enter the correct PIN and the program can be viewed.

Keep your PIN in a safe place, and do not share it with unauthorized third parties.


If you forget your PIN, call AT&T customer service for assistance.

Checking for updates


1. From the **Program Guide** screen, touch  to launch the **Options** menu.
2. Touch **Check for updates**. The system searches for updates to your AT&T Mobile TV service and automatically downloads any new software versions.

Refreshing a subscription

Refresh your subscription if you have more than one AT&T Mobile TV enabled phone and you switch your SIM card between phones.

1. From the **Program Guide** screen, touch  to launch the **Options** menu.
2. Touch **Refresh Subscription**. The AT&T Mobile TV service then checks your records to verify you are receiving the correct package.

About


1. From the **Program Guide** screen, touch  to launch the **Options** menu.
2. Touch **About** to display the current version of AT&T Mobile TV operating on your phone.

Section 9: Understanding Your Address Book

This section allows you to manage your daily contacts by storing their name and number in your Address Book. Address Book entries can be sorted by name, entry, or group.

Note: When storing an Address Book entry into your SIM card, note that only the name, phone number, group, and slot location are initially offered as fields (some SIM cards may allow an address as well). Although you may add additional fields to a SIM entry; if you move that same SIM card to another model phone, it is possible that only the basic information will be transferred.

Address Book Settings



1. Touch  → **Address Book** → **Address Book Settings**.
2. Touch any of the following options to activate a function:
 - **My Business Card:** attaches a user created virtual business card as an attachment to outgoing messages.
 - **Save New Contacts to:** defines the destination for new contact entries (Phone or SIM Card) (page 95).
 - **View Contacts from:** to filter the display of current Address Book entries. Options include: All, Phone, or SIM Card (page 91).
 - **Own Number:** to display your current phone number (page 93).
 - **Fixed Dial Contacts:** assigns phone numbers as FDN entries (page 93).

- **Used Space:** displays the memory storage allocation (total available and remaining) within both your Phone, SIM card, and FDN list (page 97).

Adding a New Contact

Use the following procedure to store a new contact to your Address Book.

Saving a Number from the Idle screen


1. Touch  →  (**Create Contact**). This opens the **Add New Contact** screen.
2. Touch the image icon and assign a picture to the new entry by choosing one of three options:
 - **Remove** although not an option with a new entry, deletes any previously assigned image.
 - **Take Photo** to use the camera to take a new picture and assign it to this entry.
 - **Caller Image** to retrieve a previously stored image from your Pictures folder and assign it to this entry. Select an image and touch **Add** to assign the image and return to the previous **Add New Contact** screen.

3. Touch the **First Name**, **Last Name**, and **Display Name** fields and use the onscreen keyboard to enter names for the new entry, and touch **OK**. (For more information, refer to “*Entering Text*” on page 40.)

- **First Name:** allows you enter a first name for this entry.
- **Last Name:** allows you enter a Last name for this entry.
- **Display Name:** allows you enter a display name for this entry which then appears when you receive a call from this contact.

4. Touch the **Phone Number** field and use the onscreen keypad to enter the phone number for the entry, and touch **OK**.

- **Phone Number:** allows you keep or alter the currently entered phone number.

5. Touch  to change the category type of the entry. Choose from among: **Phone Number (Cell)**, **Home**, **Work**, **Fax**, or **Others**.

6. Use your fingertip to scroll down the screen and touch any of the remaining fields to update their information. Touch **OK** to save your updates. Available fields consist of:

- **Email:** adds a contact email address for this entry.


- **Group:** assigns this contact to group. Touch an group type to complete the assignment. For more information, refer to “*Creating New Group*” on page 94.
- **Ringtone:** assigns a ringtone for this contact information. Choose from **Tones**, **Music**, or **Recorded Audio** categories. Touch a music file to play a short sample and then touch **Add** to complete the assignment.
- **Vibration:** assigns a vibration type for this contact information. Touch a setting (**Vibration 1 - 5**) to be provided with a sample. Touch **Save** to complete the assignment.
- **Birthday:** assigns a calendar date for the contacts birthday. Touch **Save** to store the new date. For more information, refer to “*Scrolling Through Field Entries*” on page 22.
- **Note:** allows you enter notes associated with this contact. For more information, refer to “*Entering Text*” on page 40.

7. Touch **Save** to store the new entry into the Address Book.

Note: By default, Contacts are saved on the phone. To copy them to a SIM card, see “*Copying an Entry to the SIM Card*” on page 95.

Adding More Fields to a Number

While in the process of creating a new entry or editing an existing contact, you can add additional fields to the entry's list of information.


1. Within the open Contact Screen, touch  (**Add More Fields**).
2. Place a checkmark adjacent to an individual field by touching each entry.

– or –


Place a checkmark alongside all entries by touching **All**.
Additional fields include:

- **Phone Number**: adds an additional number field for the entry.
- **Email**: adds an additional contact email address field for this entry.
- **URL**: adds a Web site's URL to the entry.
- **DTMF**: adds a DTMF tone string for use with this entry.
- **Group**: creates an additional group field for group assignment.
- **Message Tone**: adds a field used to assign a message tone that will sound when messages are received from this contact.
- **NickName**: adds a field that can be used to enter a nickname for the entry that is displayed when calls are either made to or received from the contact.
- **Company**: adds a company field for this entry.




- **Job Title**: adds a a Job Title field for this entry.
- **Address**: adds a field used to assign a physical address for this entry.

3. Touch  to store the new fields to the entry and return to the previous screen.





– or –

To add even more fields, touch  and repeat the previous step.



Deleting Fields From a Number

1. Within the open Contact Screen, touch  (**Delete Fields**).
2. Touch  to confirm deletion of an individual field. After each deletion, you are returned to the Contacts screen.
3. Repeat the above step for each field you wish to delete.
4. Once you have made your modifications, touch  to store the new entry and its fields.

Saving a Number During a Call


1. Make your call, touch , use the onscreen keypad to enter your number.
2. Press  or touch  to initiate the call.
3. Touch  → **Save to Address Book** → **New**.
 - Select **Update** if this was a previously created entry and you are adding the current number to the previous entry.
4. Enter the desired information, see “Saving a Number from the Idle screen” on page 87.


Saving a Number After a Call Has Ended

1. Press  to bring up the recent calls screen.
– or –
Touch  → **Tools** → **Recent Calls**.
2. Touch a phone number from the list to reveal the **Details** page (shown below) for the phone entry.

To call the selected number

To save the number to the Address Book



3. Touch  → **New**.
 - Select **Update** if this was a previously created entry and you are adding the current number to the previous entry.
4. Enter the desired information, see “Saving a Number from the Idle screen” on page 87.

Using Contacts

Dialing a Number from Address Book


Once you have stored phone numbers in the Address Book, you can dial them easily and quickly by either using their SIM card location number or by using the Search field to locate the entry.

Note: The default Address Book entries are: *Now - *669, Check Bill Balance - *225#, Directory Assistance - 411, Pay My Bill - *729, View Data Usage - *3282#, View My Minutes - *646#, Voice Dial - *08, and Music ID - #43.


Finding an Address Book Entry

You can store phone numbers and their corresponding names onto your SIM card and phone's onboard memory. The two locations are physically separate but are used as a single entity, called the Address Book.

Depending on your particular SIM card, the maximum number of phone numbers the SIM card can store and how they are stored may differ.

1. In Idle mode, touch  → **Address Book** → **Contacts**.
2. Touch the **Contacts Filter** field (upper-right) and select Contacts. Additional entry categories include Groups and Favorites.


3. Within the Contacts list (sorted alphabetically), touch and drag the **Power Search** tab to quickly “thumb through” the alphabetical listing by first name.










4. When found, touch  adjacent to the entry to make the call.

Address Book Entry Options

While in the details page for a specific entry (seen below) you have two sets of options, each accessible from two of the onscreen buttons.

1. Touch  and touch a phone number from the list to reveal the **Entry Options** page (shown below) for the phone entry.



2. Touch  to reveal the first set of options:
 - **Call**: allows you to call a currently selected entry.
 - **Video Share**: allows you to share either a live video recording or recorded video with a phone that is similarly equipped, and if both SIMs have the feature enabled.
 - **Send Message**: allows you to send a text message or a multimedia message to the selected entry.
3. Press  to return to the previous Entry Options page.
4. Touch  to alter the properties of the current entry such as: Name, Category, Group, or location. Touch  to store your changes.
5. Touch  to delete the current address book entry from a target location such as the Phone and/or SIM card.
6. Touch  to reveal the second set of entry options:
 - **Print via Bluetooth**: allows you send the selected contact entry information to a Bluetooth compatible printer.
 - **Send Business Card via**: allows you to send a message to the selected entry which contains the information from an Address Book Business Card entry which you have on file. This can be sent as either a message or via Bluetooth.
 - **Add to Favorites**: allows you add the current contact entry to your favorite list of callers (Favorites list).

Finding My Own Phone Number

This function is a memory aid, which you can use to check your own phone number if you need to do so.


- ▶ In Idle mode, touch  → **Address Book** → **Address Book Settings** → **Own Number** → <voice line #>.

FDN Mode

FDN (Fixed Dialing Number) mode, if supported by your SIM card, restricts your outgoing calls to a limited set of phone numbers. When this feature is enabled, you can make calls only to phone numbers stored in the FDN list on the SIM card.

Note: FDN Mode must be set to **On** in the **Menu** → **Settings** → **Phone** → **Security** → **Fixed Dialing Mode** option before you can add, change, or delete contacts on the FDN List.

Changing the FDN mode Status

1. In Idle mode, touch  → **Settings** → **Phone** → **Security**.
2. Scroll down to the **Fixed Dialing Mode** field and touch **On** (to enable fixed dialing) or **Off** to disable the option.






Important! With Fixed Dial Mode enabled, you will NOT be able to dial any number other than those created Fixed Dial Numbers.

Creating New FDN Numbers

With the Fixed Dial mode On, follow these procedures:



1. In Idle mode, touch  → **Address Book** → **Fixed Dial Contacts** → **Create FDN**.


Note: If FDN is Off: touch **Menu** → **Address Book** → **Address Book Settings** → **Fixed Dial Contacts** → **Create FDN**. Then follow steps 2-7.

2. Enter your PIN2 password and touch **Confirm**. This number is provided to you by your Service Provider.
3. Touch **Name** and use the onscreen alphanumeric keypad to enter a name for this FDN contact. Touch .
4. Touch **Phone Number** and use the onscreen numeric keypad to enter a contact phone number for this FDN contact. Touch .
5. Touch the SIM card location field to then use the onscreen numeric keypad to enter a location value for the entry on the SIM card. Touch .
6. Touch  to store the new FDN entry.
7. Press  to return to the Main menu.





Group Settings

Creating New Group




1. In Idle mode, touch  → **Address Book** → **Group** → **Create Group**.
2. Touch the **Group Name** field and use the onscreen keypad/keyboard to enter a new group name. For more information, refer to “*Entering Text*” on page 40.
 - Touch  to store the new group name.
3. Touch the **Group Picture** field and choose a location for the new image:
 - **Reset**, although not an option with a new group, deletes any previously assigned image.
 - **Take Photo** to use the camera to take a new picture and assign it to this entry.
 - **Group Picture** to retrieve a previously stored image from your Pictures folder and assign it to this group entry.
4. Touch **Group Ringtone** to choose an audio file for assignment to this new group. Choose from **Tones**, **Music**, or **Recorded Audio** categories.
 - Touch a music file to play a short sample and then touch **Add** to complete the assignment.


5. Touch **Group Vibration** to choose a vibration type for assignment to this new group. Choose from five vibration options (**Vibration 1-5**).
 - Touch a vibration option to activate a short sample and then touch **Save** to complete the assignment.
6. Touch  to store the new Group category.

Adding an Entry to a Group

1. Touch , then touch an Address Book entry from the list to reveal the **Entry Options** page (page 92) for the phone entry.
2. Touch  → **Group**.
3. Touch a current Group category → .
– or –
 1. In Idle mode, touch  → **Address Book** → **Group**.
 2. Touch a group entry.
 3. Touch **Add Member** and place a checkmark alongside those entries you wish to add to the current Group.
 4. Touch **Add**.

Removing an Entry From a Group



1. Touch , then touch an Address Book entry from the list to reveal the **Entry Options** page (page 92) for the phone entry.
2. Touch  → **Group**.
3. Touch a remaining Group category to then assign the entry to this new group.
4. Touch  to store the new assignment.
– or –

1. In Idle mode, touch  → **Address Book** → **Group**.
2. Touch a group entry.
3. Touch **Remove Member** and place a checkmark alongside those entries you wish to add to the current Group.
4. Touch **Remove**.

Editing a Caller Group

To edit a Group entry, there must be at least one member as part of the selected group.

1. In Idle mode, touch  → **Address Book** → **Group**.
2. Touch a current Group entry.

3. Touch  → **Edit Group**.
4. Make modifications to the **Group Name**, **Group Picture**, **Group Ringtone**, **Group Vibration** fields. For more information, refer to “*Creating New Group*” on page 94.
5. Touch  to store your changes.


Managing Address Book Entries

You can copy, delete, and view the memory status for the Phone and SIM entries on your phone.


Copying an Entry to the SIM Card


Note: When storing an Address Book entry into the SIM card, note that only the name, phone number, group, and slot location are initially offered as fields (some SIM cards may allow an address as well). To save additional information for a particular contact, such as other phone numbers, or e-mail, it is important to add new fields to that Contact information. It is also important to note that if you move the SIM card to another phone that does not support additional fields on the SIM card, this additional information may not be available.

1. In Idle mode, touch  → **Address Book** → **SIM Management** → **Copy Contacts to SIM**. The phone then displays a list of your current contacts.

2. Place a checkmark adjacent to those entries you wish to have copied to the SIM card.
 - Repeat this step for all individual entries you wish copied to the SIM or touch **All** to place a checkmark alongside all entries.
3. Touch **Copy**. You are prompted to confirm that you want to copy these entries to the SIM card.
 - To copy the checked entries to the SIM card, touch **Yes**.
 - To cancel the copy process, touch **No**.
4. When you are finished, press  to return to the Main menu.

Copying an Entry to the Phone



1. In Idle mode, touch  → **Address Book** → **SIM Management** → **Copy Contacts from SIM**. The phone then displays a list of your current contacts held on the SIM card.
 - If the entry's associated Group graphic has a SIM location icon on it, then the entry exists on the SIM card. This is the type you can duplicate.
 - If the entry's associated Group image does not have a SIM location icon, then this entry currently exists on the phone.

2. Place a checkmark adjacent to those entries you wish to have copied from the SIM card to the Phone.
 - Repeat this step for all individual entries you wish copied to the Phone or touch **All** to place a checkmark alongside all entries.
3. Touch **Copy**.
4. When you are finished, press  to return to the Main menu.



Deleting All of the Address Book Entries

You can delete all Phone or SIM entries from your phone's memory.

Deleting all entries from the Phone

1. In Idle mode, touch  → **Address Book** → **Contacts** → **Delete**.
2. Touch the **All** field to place checkmarks alongside all the current Address Book entries.
3. Touch **Delete**.
4. When you are finished, press  to return to the Main menu.


Deleting all entries from the SIM

1. In Idle mode, touch  → **Address Book** → **SIM Management** → **Delete Contacts from SIM**.
Touch the **All** field to place checkmarks alongside all the current Address Book entries.
2. Touch **Delete**.
3. When you are finished, press  to return to the Main menu.

Note: Entries on the FDN Address Book must be deleted from within the FDN Address Book

Using the Service Dialing Numbers


You can view the list of Service Dialing Numbers (SDN) assigned by your service provider. These numbers may include emergency numbers, customer service numbers, and directory inquiries.

1. In Idle mode, touch  → **Address Book** → **Service Number**.
2. Scroll through the available numbers.
3. To dial the number displayed, press .

Note: This menu is available only when your SIM card supports Service Dialing Numbers.

Checking the Address Book's Used Space

You can check how many names and numbers are stored in the Address book, in both SIM card and the phone memory. You can also see the capacity of both memories.


1. In Idle mode, touch  → **Address Book** → **Address Book Settings** → **Used Space**.
 - **Phone:** tells you how many Address Book entries (out of a possible 2000) are in use.
 - **SIM Card:** tells you how many entries are in use on your SIM card.
 - **Additional No. 1:** if you have added additional numbers to contacts saved on the SIM card, this is a counter of the number of SIM contacts with a second number saved on your SIM card.
 - **Additional No. 2:** if you have added additional numbers to contacts saved on the SIM card, this is a counter of the number of SIM contacts with a third number saved on your SIM card.
 - **Email:** tells you how many entries are in use.
 - **FDN:** tells you how many entries are in use (out of a possible 40).

Note: Depending on the SIM card, the number of entries may differ.

2. Once finished, press  to return to the Main menu.

Section 10: My Stuff

The topics covered in this section are games, apps, pictures, videos, calendar, schedule events, setting an alarm, and performing simple math calculations.

1. Touch  → **My Stuff**.
2. Select from one of the following functions: **Audio, Games & Apps, Pictures, Videos, Tools, Other Files**, or **Used Space**.
3. Touch the filter drop down (upper-right of My Stuff page) to filter the entries based on their current location (**All, Phone**, or **Memory Card**).



My Stuff Functions

This page provides you with several functions that can be activated from virtually any page within the My Stuff directories. Most editing features are only applicable to those files/folders that are not locked, and therefore editable.


1. Touch  → **My Stuff**.
2. Select from the following:
 - **Create Folder**: create a new My Stuff folder on either the Phone or Memory Card.
 - **Manage**: allows you to move or copy an existing unlocked folder or file.

- **More**: provides you with the ability to Delete, Rename, Sort by, Send via Bluetooth, Bluetooth Visibility, and Lock/Unlock certain files or folders.

Creating a New Folder

1. Touch  → **My Stuff** → **Create Folder**.
2. Select a destination for the new folder by touching either **Phone** or **Memory Card**.
3. Use the onscreen alphanumeric keypad to create a new name for the folder and touch  once you are done.

Managing Files and Folders

1. Touch  → **My Stuff** → **Manage**.
2. Select a migration option by touching either **Move** or **Copy**.
 - **Move**: takes an unlocked file/folder and moves it to a new location.
 - **Copy**: takes the selected file/folder and duplicates it in the new location.
3. Select an unlocked entry by touching it to then place a checkmark next to the entry.
 - Touch **All** to place a checkmark alongside all available/unlocked items.


4. Once complete, touch **Move/Copy** to complete the process.

More Functionality

1. Touch  → **My Stuff** → **More**.
2. Select an onscreen option:
 - **Delete**: erases selected files/folders.
 - **Rename**: renames the selected files/folders.
 - **Sort by**: sorts the current available files and folders using either: Date, Type, Name, or Size.
 - **Send via Bluetooth**: sends a selected file via Bluetooth to another compatible device.
 - **Bluetooth Visibility**: allows you to make specific files or folders visible to other Bluetooth devices.
 - **Lock**: locks available files and folders.


Audio Files

The **Audio** menu option allows you to shop tones, answer tones, and music using the WAP browser. You can also access previously stored (pre-recorded) audio files from your internal microSD card.

1. Touch  → **My Stuff** → **Audio**.
2. Touch an onscreen option (**Tones**, **Answer Tones**, **Music**, and **Recorded Audio**).


Tones

You can shop, download, and save to your Downloaded Ringtones folder.

1. Touch  → **My Stuff** → **Audio** → **Tones**. A menu then displays to give you the option of either shopping for tones or selecting from files previously stored to your phone.
2. Touch **Shop Tones** → select a file to download, and follow the on-screen options. (These files are downloaded and stored in the **Tones** folder.)
– or –
Touch an available entry.
3. From the playback page, touch **Set as** and select from the following options:
 - **Call Ringtone**: allows you to assign the selected ringtone for use with general incoming calls when no other caller ringtone has been assigned.
 - **Caller Ringtone**: allows you to assign a ringtone to someone in your Contacts list (**Search Contact**) or **Create Contact**.
 - **Alarm Tone**: allows you to assign the tone to an alarm.


Answer Tones

You can shop and download Answer Tones, manage your Answer Tones, and access Help files. To access the **Answer Tones** menu option, use the following steps:

1. Touch  → **My Stuff** → **Audio** → **Answer Tones**.
2. Touch one of the following options and follow the onscreen instructions.
 - **Shop Answer Tones:** launches the WAP browser from which you can touch Shop Answer Tones, then follow the onscreen instructions to purchase a file.
 - **Manage Answer Tones:** launches the WAP browser from which you can assign Answer Tones to Callers and Groups, turn your greeting on or off, and shop for more Answer Tones.
 - **About Answer Tones:** launches the WAP browser from which you can navigate through the frequently asked questions regarding Answer Tones.



Music

This menu allows you to shop for music using the WAP browser.



1. Touch  → **My Stuff** → **Audio** → **Music** → **Shop Music** to launch the WAP browser.
2. Follow the on-screen options.

Recorded Audio

This menu shows a list of saved voice memos. When a voice memo is recorded and saved, it is stored in the Recorded Audio folder. To access this menu use the following steps:

1. Touch  → **My Stuff** → **Audio** → **Recorded Audio**.
2. Touch a pre-recorded memo to begin playback.
3. To exit, press .


Creating a new audio recording

1. Touch  → **Tools** → **Record Audio**.
2. To start recording, touch .


For more information, refer to “*Record Audio*” on page 144.

Games & Apps

The **Games & Apps** menu option allows you to shop games and applications using the WAP browser. You can download new games and applications, then save them to the **Games & Apps** folder.

1. Touch  → **My Stuff** → **Games & Apps**.
2. Select one of the following options:
 - **Shop Games**
 - **Shop Applications**
 - **Tumbling Dice**
 - **AT&T Navigator**
 - **MEdia Mall 2.0**
 - **Mobile Banking**
 - **Mobile Email**
 - **MobiVJ**
 - **MusicID**
 - **My-Cast Weather**
 - and others..
3. Follow the onscreen options.

Shop Games


1. Touch  → **My Stuff** → **Games & Apps** → **Shop Games** to launch the WAP browser.
2. Follow the onscreen options. The file is downloaded and stored in the **Games & Apps** folder.

Note: Service charges and subscription purchase may be required.

3. To access a pre-installed game, touch a game from the available list.

For more information, refer to “*MEdia Mall*” on page 126.

Shop Applications

1. Touch  → **My Stuff** → **Games & Apps** → **Shop Applications** to launch the WAP browser.
2. Follow the onscreen options to purchase the new application. The file is downloaded and stored in the **Games & Apps** folder.
3. To access a new application, touch the entry from the available list.

Mobile Banking Access

You can access your banking information on your device. Mobile Banking allows you to view balances, perform transfers, view account history and pay bills directly from your mobile phone.

Partner banks include: **Wachovia**, **SunTrust**, **Synovus**, and **BancorpSouth**.

1. Touch  → **My Stuff** → **Games & Apps** → **Mobile Banking**.
2. Follow the onscreen instructions.

Note: This service is dependent upon your banking institution's rules and regulations. Standard data charges apply.

Pictures

The **Pictures** menu option allows you to shop for and download new graphics (using the WAP browser), then save them to your **Pictures** folder. To access the Graphics menu option, use the following steps:

- ▶ Touch  → **My Stuff** → **Pictures**.

From the Pictures page you can access the following menu options (see “*My Stuff Functions*” on page 98.):

- **Create Folder:** create a new My Stuff folder on either the Phone or Memory Card.

- **Manage:** allows you to move or copy an existing unlocked folder or file.
- **More:** provides you with the ability to Delete, Rename, Sort by, Send via Bluetooth, Bluetooth Visibility, and Lock/Unlock certain files or folders.

Shop Graphics



1. Touch  → **My Stuff** → **Pictures** → **Shop Graphics**. The WAP browser is launched.
2. Follow the onscreen options to purchase the new image. The file is downloaded and stored in the **Pictures** folder.
3. To access a new application, touch the entry from the available list.

Image Features

Touch a graphic from the Pictures page to display the image. From the image viewer page, you have access to both macro functions (Zoom, Edit, and Info) and menu options.

- **Zoom:** allows you to magnify the current image.
- **Edit:** allows you to edit the current image by applying various image effects. For more information, refer to “*Editing Images*” on page 103.

Note: Editing is only available for unlocked images or non DRM images.

- **Information:** displays an onscreen listing of the image's properties such as: name, format, size, etc..
- **Send:** lets you send the currently active image as part of a new multimedia message, to an external device via Bluetooth, or to HP's online Snapfish® service.
- **Set as:** allows you to assign the current image as either your current Wallpaper, or as a display image used by a specific entry within your Address Book.
- **More:** allows you to choose from the following image options:
 - **Delete:** allows you to delete the current graphic.
 - **Rename:** allows you to rename the current graphic.
 - **Slide Show:** allows you play a slideshow using the graphics currently available from within the Pictures folder. Press  to stop the slideshow.
 - **Bluetooth Visibility:** allows you to toggle your current Bluetooth visibility status between Visible or Hidden.
 - **Print via:** allows you to make a selected graphic printable by either USB or Bluetooth printer.
 - **Lock/Unlock:** allows you to secure a selected graphic by protecting it from accidental alterations.
 - **Properties:** allows you to view the properties of a photo.

Editing Images


1. Touch  → **My Stuff** → **Pictures** → <image>.
2. Touch **Edit** () → **Files** → **Open** or **Save as** (to save a renamed copy of this image).

– OR –

 Touch **Edit** () → **Edit** and select from any of the following:
 - **Effects:** allows you to choose from among several effects such as: **Filter**, **Style**, **Warp**, or **Partial Blur**.
 - **Adjust:** allows you to adjust **Auto Level**, **Brightness**, **Contrast**, and **Color**.
 - **Transform:** allows you to **Resize**, **Rotate**, and **Flip** the image.
 - **Crop:** allows you to crop the image. Touch one corner of the image and, in a single motion, drag to another location to create the crop area, then touch **Crop**.
 - **Insert:** allows you to add **Frames**, **Picture**, **Clip arts**, **Emoticon**, and **Text** to the image.
 - **Memo on screen:** allows you to select a color, then handwrite a message onto the current image. Touch **Done** to store the new changes.

Videos

This menu allows you shop for videos and to set up folders to save your videos using the WAP browser.

1. Touch  → **My Stuff** → **Videos** → **Shop Videos**. The WAP browser is launched.
2. Follow the onscreen options to purchase the new video. The file is downloaded and stored in the **Videos** folder.

Tools

The Tools folder provides access to and allows you to use the Camera, Record Audio files, set Alarms, use the Calendar features, view Recent Calls, create Tasks, create Memos, use the Calculator, use the Converter (for currency, length, weight, volume, area, and temperature), view World Clock, set the Timer, and use the Stopwatch.

For more information, refer to “Tools” on page 144.

Camera

Taking Photos

Note: When taking a photo in direct sunlight or in bright conditions, shadows may appear on the photo.

1. Press the Camera key to activate the camera mode.
– or –

In Idle mode, touch  → **Tools** → **Camera**.

2. If desired, before taking the photo, press the onscreen **Settings** button to access camera options.
3. Press the Camera key to take the photo.

Note: Your camera produces photos in JPEG format.

For more information, refer to “Using the Camera” on page 108.

Record Audio

Record Audio allows you to record voice memos. It also allows you to send your audio clip to other people as an attachment of an MMS message. Recording time is limited to free memory space available.

For more information, refer to “Record Audio” on page 144.

Alarms

This feature allows you to:

- set the alarm to ring at a specific time.
- set the phone to switch on automatically and ring the alarm even if the phone is switched off.

- ▶ Access the Alarms menu by selecting **My Stuff → Tools → Alarms**.

For more information, refer to “*Alarms*” on page 145.

Calendar

The calendar feature allows you to view the Month, Week, and Day layout views. Events such as an appointment, anniversary, or private entries are merged into a single scheduled event. It also shows any Missed Alarm Events that have occurred.

Note: Birthdays which take place on the current day are displayed within the onscreen Birthday widget (page 23).

- ▶ Access the Calendar menu by selecting **My Stuff → Tools → Calendar**.

For more information, refer to “*Calendar*” on page 146.

Recent Calls

The phone stores the numbers of the calls you’ve dialed, received, or missed in the **Recent Calls** menu. If the number or caller is listed in your Address Book, the associated name is displayed.

- ▶ Access the Recent Calls menu by selecting **My Stuff → Tools → Recent Calls**.

For more information, refer to “*Recent Calls*” on page 148.

Tasks

This menu option allows you to create a “to do” entry of tasks which are created in a similar fashion to previously described Calendar entries.

- ▶ Access the Tasks menu by selecting **My Stuff → Tools → Tasks**.

For more information, refer to “*Tasks*” on page 148.

Memo

This option allows you to create memos and add them to your events.

- ▶ Access the Memo menu by selecting **My Stuff → Tools → Memo**.

For more information, refer to “*Memo*” on page 148.

Calculator

This option allows you to use your phone as a calculator. The calculator provides the basic arithmetic functions; addition, subtraction, multiplication, and division.

- ▶ Access the Calculator menu by selecting **My Stuff → Tools → Calculator**.

For more information, refer to “*Calculator*” on page 148.

Converter

The Converter menu provides the following conversion categories:

- Currency
- Length
- Weight
- Volume
- Area
- Temperature

- ▶ Access the Converter menu by selecting **My Stuff → Tools → Converter**.

For more information, refer to “*Converter*” on page 149.

World Clock

The World Clock allows you to view the time of day or night in another parts of the world. World displays time in the 30 different time zones around the world.

- ▶ Access the World Clock menu by selecting **My Stuff → Tools → World Clock**.

For more information, refer to “*World Clock*” on page 149.

Timer

The Timer allows you to set an amount on time and then activate the built-in counter to begin a countdown (Hour/Minute/Second) to that preset time frame.

- ▶ Access the Timer menu by selecting **My Stuff → Tools → Timer**.

For more information, refer to “*Timer*” on page 150.

Stopwatch

This feature allows you can to measure intervals of time for four separate times. To enable the Stopwatch, do the following:

- ▶ Access the Stopwatch menu by selecting **My Stuff → Tools → Stopwatch**.

For more information, refer to “*Stopwatch*” on page 150.



Other Files

This feature provide additional storage of other miscellaneous file types that may not fit into any of the previous categories.

- ▶ Access the Other Files menu by selecting **My Stuff → Other Files**.

Used Space

The Used Space menu option allows you to view the usage and available memory for Audio, Games & Apps, Pictures, Videos, and Other Files. To access the **Used Space** option, use the following steps:

1. Touch  → **My Stuff** → **Used Space**.
2. Choose from **Audio, Games & Apps, Pictures, Videos,** or **Other Files**.
3. Press  to return to the **Used Space** menu.

Section 11: Camera

This section explains how to use the camera on your phone. You can take photographs and shoot video by using the built-in camera functionality. Your 3.0 megapixel camera produces photos in JPEG format.

Important! Do not take photos of people without their permission.
Do not take photos in places where cameras are not allowed.
Do not take photos in places where you may interfere with another person's privacy.

Using the Camera

Taking Photos

Taking pictures with your device's built-in camera is as simple as choosing a subject, pointing the camera, then pressing the camera key.


Note: When taking a photo in direct sunlight or in bright conditions, shadows may appear on the photo.

1. Press the Camera key to activate the camera mode.


– or –

In Idle mode, touch  → **Tools** → **Camera**.

2. Using the phone's main display screen as a viewfinder, adjust the image by aiming the camera at the subject.
3. Press the Camera key until the shutter sounds. (The picture will automatically be stored within your designated storage location. If no microSD is installed, all pictures will be stored on the Phone.) For more information, refer to *"Camera and Camcorder Options"* on page 109.



Note: The number of JPEG pictures remaining on the selected media appears in the upper-right of the screen. This is an approximate number of total pictures which can be taken at the current image size.

4. If desired, before taking the photo, you can touch onscreen icons to access various camera options.
5. Press  to return to the picture viewer.

Camera and Camcorder Options

Options are represented by icons across both sides of the screen.



Camera/Camcorder/Video Share Mode: allows you to take a photo in various modes. Once you change the mode, the corresponding indicator appears at the top left of the display. Choose from Camera, Camcorder, or Video Share.



Recording Mode: allows you to set the recording mode to either: Normal (limited only by available space on destination location), Limit for MMS (limited by MMS size restrictions), Video Share (only available in Camcorder mode.)



Shooting mode: allows you to set the shooting mode. Options are:

- **Single:** takes a single photo and view it before returning to the shooting mode.
- **Continuous:** takes a succession of consecutive photos by pressing and holding the Camera key.
- **Panorama:** takes a landscape photo by taking an initial photo and then adding additional images to itself. The guide box lets you view the area where the second part of the panoramic picture should fall within.
- **Smile Shot:** the camera focuses on the face of your subject. Once the camera detects the person's smile, it will take the picture.
- **Mosaic:** takes up to nine photos and then groups them together into a single final photo.
- **Frame:** allows you to choose a custom frame border for your image. Choose from one of the 20 available frames. Touch **OK** to assign the frame.



Camera Resolution: allows you to set the image size to either: 3M(2048x1536), 2M(1600x1200), 1M(1280x960), 0.3M(640x480), w3M (2048X1232) or 400x240.



Camcorder Resolution: allows you to set the video size to either: 320x240 or 176x144.



Settings: allows you to customize your camera settings. Choose the following options and touch **OK**:

Camera tab:

- **Effects:** allows you to change the color tone or apply special effects to the photo. Options include: None, Black and White, Sepia, Negative, or Water Color.
- **Exposure Meter:** allows you to set how the camera measures or meters the light source: Normal, Center-Weighted, or Spot.
- **Scene:** allows you to set the camera options to capture scenes such as None, Portrait, Landscape, Night, Sports, Sunset, or Text.
- **Image Quality:** allows you to set the image quality to: Superfine, Fine, Normal, or Economy.



Camcorder tab:

- **Effects:** allows you to change the color tone or apply special effects to the video. Options include: None, Black and White, Sepia, Negative, or Water Color.
- **Video Quality:** allows you to set the video quality to: Fine, Normal, or Economy.



Settings tab:

- **Guidelines:** allows you to turn the guidelines On or Off.
- **Review:** allows you to activate the instant review feature where images are displayed immediately after review (On or Off).
- **Shutter Sound:** allows you to select a tone to play when the camera's shutter opens and closes. Sound selections are Shutter 1, Shutter 2, Shutter 3, or Off.
- **Audio Recording:** allows you to record audio while recording video. Selecting Off, temporarily mutes the microphone and records only video.
- **Storage:** allows you to configure the default storage location for images/videos as either Phone or Memory Card (if inserted).



White Balance: allows you to set this option from the following choices: Auto, Daylight, Incandescent, Fluorescent, or Cloudy.



Timer: allows you to set a time delay before the camera takes the photo or the camcorder begins recording video. Options include: Off, 2 seconds, 5 seconds, or 10 seconds.




Brightness: allows you to adjust the brightness level by moving the slider across the page.




Access Pictures/Video Folder Options: allows you to access the options page for a selected image/video. Options include: Play slideshow, Edit, Information, Send, Set as, Delete, and Return to previous page.


Pictures/Videos Folder Options

After you have taken a photo or shot a video, you can access various options from the Pictures/Video Folder page.








► Touch one of the available options:

- **Play Slideshow** (): to play the available images (from the Pictures folder) within a slideshow. Touch the Up/Down arrows to set the duration of each onscreen image.


- **Edit** (): allows you to edit the current image using any of the following:
 - **Effects:** allows you to choose from among several effects.
 - **Adjust:** allows you to adjust **Auto Levels**, **Brightness**, **Contrast**, and **Color**.
 - **Transform:** allows you to **Resize**, **Rotate**, and **Flip** the image.
 - **Crop:** allows you to crop the image. Touch one corner of the image and, in a single motion, drag to another location to create the crop area, then touch **Crop**.
 - **Insert:** allows you to add **Frames**, **Picture**, **Clip arts**, **Emoticon**, and **Text** to the image.
 - **Memo on screen:** allows you to select a color, then handwrite a message onto the current image. Touch **Done** to store the new changes.

Note: Edit and Set as are not a features available when the camcorder mode is active.

- **Information** (): displays file information such as name, format, size, resolution, etc..
- **Send** (): lets you send the currently active image as part of a new multimedia message, to an external device via Bluetooth, or to HP's online Snapfish® service.
- **Set as** (): allows you to assign the current image as either your current Wallpaper, or as a display image used by a specific entry within your Address Book.

- **Delete** (): erases the currently selected image/video.
- **Return** (): takes you back to the previously active camera or camcorder page where you can take another photo or shoot a new video.

Accessing the Pictures Folder

1. Touch  → **My Stuff** → **Pictures**.
2. Touch a photo to open it in the viewer.


Selecting and Using the Pictures Folder

Touch a picture from the Pictures page to display the image. From the image viewer page, you have access to both macro functions (Zoom, Edit, and Info) and menu options.



- **Zoom:** allows you to magnify the current image.
- **Edit:** allows you to edit the current image by applying various image effects.
- **Information:** displays an onscreen listing of the image's properties such as: name, format, size, etc..
- **Send:** lets you send the currently active image as part of a new multimedia message, to an external device via Bluetooth, or to HP's online Snapfish® service.
- **Set as:** allows you to assign the current image as either your current Wallpaper, or as a display image used by a specific entry within your Address Book.

- **More:** allows you to choose from the following image options:
 - **Delete:** allows you to delete the current graphic.
 - **Rename:** allows you to rename the current graphic.
 - **Slide Show:** allows you play a slideshow using the pictures currently available from within the Pictures page. Touch the screen to stop the slideshow.
 - **Bluetooth Visibility:** allows you to toggle your current Bluetooth visibility status between Visible or Hidden.
 - **Print via:** allows you to make a selected graphic printable by either USB or Bluetooth printer.
 - **Lock/Unlock:** allows you to secure a selected graphic by making it protected from accidental alterations.
 - **Properties:** allows you to view the properties of a photo.

Editing a Photo

1. Touch  → **My Stuff** → **Pictures** → <image>.
2. Use the following options onscreen buttons and icons for editing and photo management.
3. Touch **Edit** () → **Edit** and select from any of the following:
 - **Effects:** allows you to choose from among several effects such as: **Filter**, **Style**, **Warp**, or **Partial Blur**.
 - **Adjust:** allows you to adjust **Auto Levels**, **Brightness**, **Contrast**, and **Color**.
 - **Transform:** allows you to **Resize**, **Rotate**, and **Flip** the image.
 - **Crop:** allows you to crop the image. Touch one corner of the image and, in a single motion, drag to another location to create the crop area, then touch **Crop**.
 - **Insert:** allows you to add **Frames**, **Picture**, **Clip arts**, **Emoticon**, and **Text** to the image.
 - **Memo on screen:** allows you to select a color, then handwrite a message onto the current image. Touch **Done** to store the new changes.



Assigning an Image to an Address Book Entry

1. Touch  → **My Stuff** → **Pictures** → <image>.
2. Touch **Set as** → **Caller Image** → **Search Contact**, touch an onscreen entry and touch .

– or –

Touch **Set as** → **Caller Image** → **Create Contact**, and follow the create a new Address Book entry with the image already assigned. For more information, refer to “*Understanding Your Address Book*” on page 87.

Assigning an Image as a Wallpaper






1. Touch  → **My Stuff** → **Pictures** → <image>.
2. Touch **Set as** → **Wallpaper**.
3. Touch the screen to reveal the adjustment tools:
 - Zoom slider: touch the magnifying icons at either the top or bottom of the slider to adjust the magnification of the current image.
 - Rotate: orients the current image in either a landscape or portrait orientation. The bottom left of the page indicates how much of the image will be displayed as the wallpaper.
4. Touch  to store the new settings and assign the wallpaper image.


Using the Camcorder



In addition to taking photos, the camera also doubles as a camcorder allowing you to also record, view, and send videos.

Shooting Video

Tip: When shooting video in direct sunlight or in bright conditions, it is recommended that you provide your subject with sufficient light by having the light source behind you.

1. In Idle mode, touch  → **Tools** → **Camera**.
– or –
Press the Camera key to activate the camera mode.
2. Touch  then touch Camcorder ().
3. Using the phone's main display screen as a viewfinder, adjust the image by aiming the camera at the subject.
4. Press the Camera key again to begin shooting video.
5. Touch  to stop the recording and save the video file to your Videos folder.
– or –
Before shooting, touch  and select **Video Share**.

- Video Share allows you to make a Video Share call by displaying a screen where you can input the number of a recipient that also has Video Share. (This option will only display if you have the Video Share service.) If the recipient accepts the Video Share call, you continue using the camcorder as usual.
- Touch  to end the Video Share session. You will get a message "Video Sharing has been Stopped. Save the Recorded Video?" You can select either **Yes** or **No**. You can then continue the call or terminate it.

6. Once the file has been saved, touch  to play back your video for review.
7. Press  to return to the viewer.

Camcorder Options


Camcorder options are represented by icons across both sides of the screen.

For more information, refer to "Camera and Camcorder Options" on page 109.





Camcorder Options after a Video is Taken

After you have shot a video, you can use various options that appear as icons on the screen. Touch an icon to activate the function.

► Touch one of the available options:

- **Play Slideshow** (): to play the available images (from the Pictures folder) within a slideshow. Touch the Up/Down arrows to set the duration of each onscreen image.

Note: Edit and Set as are not a features available when the camcorder mode is active.

- **Information** (): displays file information such as name, format, size, resolution, etc..
- **Send** (): lets you send the currently active image as part of a new multimedia message or to an external device via Bluetooth.
- **Delete** (): erases the currently selected image/video.
- **Return** (): takes you back to the previously active camera or camcorder page where you can take another photo or shoot a new video.

Accessing the Video Folder


1. Touch  → **My Stuff** → **Videos**.
2. Touch a video to open it in the viewer and initiate playback.
3. To play the video, touch .

Options available from the main Videos page, and before you select it to play:

- **Create Folder:** create a new My Stuff folder on either the Phone or Memory Card.
- **Manage:** allows you to move or copy an existing unlocked folder or file.
 - **Move:** allows you to choose the Selected or Multiple videos to move.
 - **Copy:** allows you to copy a selected or multiple videos.
- **More:** provides you with the ability to Delete, Rename, Sort by, Send via Bluetooth, Bluetooth Visibility, and Lock/Unlock certain files or folders.
 - **Delete:** allows you to delete the Selected video or Multiple videos.
 - **Rename:** allows you to rename the video file.
 - **Sort by:** allows you to sort video clips by Name, Date, Size or Type.
 - **Send via Bluetooth:** allows you to send the video to a Bluetooth device.
 - **Bluetooth Visibility:** allows you to make the Selected or Multiple videos visible to Bluetooth devices.

- **Lock/Unlock:** allows you to lock/unlock the video file to prevent deletion. Lock prevents the video clip from being deleted; Unlock allows the video clip to be deleted.

Once you have selected the video to play, your options are:

- **Options** (

Camera 116

Section 12: Messaging

This section describes how to send or receive different types of messages. It also includes the features and functionality associated with messaging.

► Touch  to store each new settings.

Types of Messages

Your phone provides the following message types:

- Text Messages
- Multimedia (Picture and Video) Messages
- IM Messages

The Short Message Service (SMS) lets you send and receive text messages to and from other mobile phones or email addresses. To use this feature, you must subscribe to your service provider's message service.

The Multimedia Messaging Service (MMS) lets you send and receive multimedia messages (such as picture messages and video messages) to and from other mobile phones or email addresses. To use this feature, you must subscribe to your service provider's multimedia message service.

Important! When creating a message, adding an image, a sound file, or a video clip to a text message changes the message from a text message to a multimedia message.

Messaging icons are displayed at the top of the screen and indicate when messages are received and their type. For more information, refer to “*Icons*” on page 15.

Creating and Sending Messages

1. Touch  → **Messaging** → **Create Message**.

– or –

Touch **Messaging** from the bottom of the Main menu.

2. Select a recipient by selecting an entry method by touch **Tap to Add Recipient** and then selecting an associated option:
 - **Recent Contacts:** to select a recipient from a list of recently sent messages.
 - **Contacts:** to select a recipient from your Contacts list (valid entries must have a wireless phone number).
 - **Group:** to select a recipient from the Group list.


Note: If the number of recipients are less than 10, all members in the group will be added. You will need to delete any unnecessary members in the list by selecting the trash can icon and deleting unwanted entries.

- **Enter Manually:** to manually enter a destination using a valid cellular phone number.
-

Note: Enter additional recipients by separating each entry with a semicolon (;) then using the previous procedure.

3. Touch the empty onscreen text field and use the onscreen keyboard to enter a message. Rotate the phone on its side to reveal the keyboard. For more information, refer to “*Entering Text*” on page 40.
4. Touch **OK** to save your text and return to the message screen.
5. Add more recipients by touching the yellow recipient field and repeating step 2.
6. Review your message and touch **Send**.

Additional Message Options

1. Touch **Insert** to reveal additional insert options.
 - **Picture:** allows you to choose an existing image from the Pictures list, then add it to your message by touching **Add**.
 - **Video:** allows you to choose an existing video from the Videos list, touch , then select **Add**.
 - **Audio:** allows you to choose an existing audio file from the Audio list, then add it to your message by touching **Add**.
 - **Take Picture:** allows you to temporarily exit the message, take a photo with phone's camera, and then add it to your message by touching **OK**.
 - **Record Video:** allows you to temporarily exit the message, record a video clip using the phone's camera, and then add it to your message by touching **OK**.
 - **Record Audio:** allows you to temporarily exit the message, record an audio clip using the phone's microphone, and then add it to your message by touching **Add**.
 - **Favorites URL:** allows you to temporarily exit the message, access your Favorites list then select those URLs you would like to add to the current message by touching **Add**.
 - **Contact Info:** allows you to choose an existing Address Book entry, then add it to your message by touching **Insert**.

2. Touch **More** to reveal additional options.

- **Preview:** allows you to preview your current message before delivery.
- **Slide Options:** allows you to add more images to the current message but then have those configured to display as a slideshow on the recipients phone. Options include: Add Slide, Delete Slide, or Edit Style).
- **Attach Files:** allows you to add either a file, card, or other information such as a calendar entry, task, or note.
 - **File:** allows you to insert an audio, graphic, or video clip to your message as an attached file.
 - **Business Card:** allows you to insert the contact information for an entry from Address Book directly to your message as an attached file.
 - **Event:** allows you to insert an Event entry from your calendar directly to your message as an attached file.
 - **Tasks:** allows you to insert an entry from your calendar tagged as a Task directly to your message as an attached file.
 - **Memo:** allows you to insert a presaved Memo (text) directly to your message as an attached file.
 - **Favorites:** allows you to add a web address from your Favorites list of Internet sites as an attachment to the message.
- **Add Subject/Remove Subject:** allows you to either add or delete a subject field to the new message.

- **Save to Drafts:** saves the current message to the Drafts folder.
- **Delivery Options:** allows you to configure the options associated with sending the message.




3. When you have finished composing your message, touch **Send to** and confirm the recipient(s). For more information, refer to *“Creating and Sending Messages”* on page 117.
4. Touch **Send** to deliver the message to the selected recipients.

Viewing New Received Messages

1. In Idle mode, new messages are indicated by icons and a **New Messages** pop-up. For more information, refer to *“Understanding the Event Widget”* on page 27.
2. Touch the tab corresponding to the message type (Text or Multimedia).

Note: If you accidentally exit from this notification screen, you will need to go to **Menu → Messaging → Inbox**, or you will need to dial your voicemail to access your messages.

3. Touch a message you wish to view. The selected message appears in the display.

- To play a multimedia message, touch .
 - To pause playback of the multimedia message, touch .
 - To stop playback of the multimedia message, touch **Stop**.
- To scroll through the message (if additional text pages have been added), touch the screen and in a single motion, scroll up or down the onscreen page.
- When you have finished, press .

Note: Messages can also be accessed by navigating to your Inbox (**Menu** → **Messaging** → **Inbox**).

Using Message Options

Message options at the Inbox level differ according to the message type, what you have done with the message, and whether you are viewing the message. Some of the main message category types include:


- Inbox:** stores any incoming message (text or multimedia).
- Sent:** stores a copy of the messages you sent.
- Outbox:** contains messages until they are sent and then the message no longer displays in this box but instead displays in the Sent box.
- Drafts:** stores unsent messages that you want to edit or send later.

- ▶ With the list of current message displayed onscreen, use any of the following menu options:
 - **List by:** sort the current list based on one of the following criteria:
 - Sender, Read/Unread, Type, Subject, Size, or Protection status.
 - **Delete:** deletes either a single or multiple set of messages. Touch an entry from the list to place a checkmark alongside the entry and mark it for deletion. Touch  to complete the process.
- ▶ With a message open for reading, use any of the following menu options:
 - **Reply (to):** allows you to compose and send a reply to the message. This option reads Reply (when replying to an SMS [Text] message), and Reply to (when replying to an MMS [Multimedia] message).
 - **Delete:** deletes the current message.
 - **More:** provides these additional message functions:
 - **Forward:** allows you to forward the message.
 - **Save to Address Book:** allows you to save the recipient or sender's information from the message to your Address Book as either a New or Updated entry. For more information, refer to “*Understanding Your Address Book*” on page 87.
 - **Move to Phone/Move to SIM:** If a message is stored in the SIM card, it is saved to the phone's memory. If a message is stored in the phone's memory, it is then saved to the SIM card.
 - **Print via Bluetooth:** allows you to print the contents of the message on a Bluetooth compatible printer.

- **Save Attachment:** allows you save any selected attachments. If the file is currently available, you are prompted to rename the filename.
- **Properties:** displays the properties of any attached files.
- **Lock/Unlock:** allows you to secure a selected message by protecting it from accidental alterations.

Signing into Your Mobile Email

Take your email with you! With Mobile Email you can check your Yahoo!® Mail, AOL® , AIM, Windows Live Hotmail, AT&T Yahoo!®, BellSouth, and other providers quickly and easily.


1. Touch  → **Messaging** → **Mobile Email**.
2. Touch an Email carrier of your choice.
3. Touch **I Agree** to accept the conditions of service.
4. Touch both the ID and password fields, then use your onscreen keyboard/keypad to enter the account information (for example, “silverfox2”), and touch **Sign In**. You will be connected to your account's Inbox and contacts, where you can send and receive emails.
5. Follow any remaining onscreen instructions to complete the process.

Using Instant Messaging (IM)

The Instant Messaging allows you to send and receive instant messages using AIM, Windows Live, and Yahoo!® communities.

Signing into Your IM Account


Although each account type differs, the initial sign in procedure is common to all supported types. Before beginning the sign in procedure, you must complete the previous procedures for selecting your default IM Community.

1. Touch  → **Messaging** → **IM**.
2. Touch an IM client of your choice (AIM, Windows Live, or Yahoo!).
3. Touch **New Account** and then touch the available fields to enter your information such as Email Address and Password. Select any additional fields.
4. Touch **Sign In** to continue.

Deleting Messages


When your phone's memory is full, an error message displays notifying you that you cannot receive any new messages. Use the **Delete** option to erase obsolete messages, freeing memory for new messages. You can delete the messages in each message folder(s) either individually or all at one time. Another option is to delete messages from all categories at once.

Deleting Messages within a Folder

1. Touch  → **Messaging**.
2. Select a message folder (**Inbox**, **Sent**, **Outbox**, or **Drafts**). A list of messages in the folder appears in the display.
3. Touch **Delete** and touch an entry to mark it for selection with a checkmark.
4. Touch either an individual message or **Select All** to place a checkmark alongside all entries in the list.
5. Touch **Delete**.

Delete All Messages

1. Touch  → **Messaging** → **Delete by Folder**.


2. Touch either a single category (**Inbox**, **Sent**, **Outbox**, or **Drafts**) or touch **All** to place a checkmark alongside all entries.
3. Touch .
4. At the "**Locked Messages**" pop-up, touch **Yes** or **Cancel** to discontinue the process. This message indicates the presence of protected/locked messages in one of the selected folders.

Messaging Settings

To configure the settings for text messages, multimedia messages, Voice mails, and Push messages.

- ▶ Touch  → **Settings** → **Applications Settings** → **Messaging**.

Configuring Text Message Settings

1. From Messaging Settings page, touch **Text Message** → **Delivery Options**.
2. Touch **Keep a Copy** and touch  to store a local copy of all outgoing text messages.

Configuring the Text Message Center

1. From Messaging Settings page, touch **Text Message** → **Text Message Center**. These settings allow you to set the default method of text message transmission used by the Text Message Center.
2. Touch one of the available setting fields and make the necessary updates.
 - **SMS Settings:** allows you to configure the Text message delivery parameters when sending Text messages.
 - **Email Settings:** allows you to configure the Email parameters when sending this type of message.
 - **Empty:** allows you to configure a new Text Message Center profile for use when sending this type of message.


Note: It is recommended that you do not alter these fields without assistance from a customer service representative.

3. Touch  to store your settings.

Configuring Multimedia Message Settings

1. From Messaging Settings page, touch **Multimedia Message**.
2. Touch an available field and make the necessary updates.


- **Delivery Options:** to configure the parameters associated with the delivery of the multimedia message such as:
 - **Priority:** you can select the priority level of your messages.
 - **Expiration:** select the length of time you wish the message you sent to remain on the Multimedia message server.
 - **Delivery Time:** you can set a time delay before the phone sends your messages.
 - **Message Size:** you can set the maximum allowed size (30/100/300/600 KB) for a multimedia message.
 - **Get Delivery Report:** when this option is enabled, the network informs you whether or not your message has been delivered.
 - **Get Read Report:** when this option is enabled, your phone requests a reply along with your message to the recipient.
 - **Keep a Copy:** you specify whether you want to keep a copy of the sent messages on your phone.
 - **Add My Business Card:** you send your content information along with your sent messages.
- **Receiving Options:** to configure the parameters associated received multimedia messages such as:
 - **Download Type:** allows you to set the message receipt options. Choose from Auto Download, Manual, or Reject.
 - **Send Delivery Report:** when this option is enabled, the phone allow the network report to the sender whether or not the message has been received.

- **Send Read Report:** when this option is enabled, your phone sends a notification back to the recipient indicating that your message has been received.
 - **Reject Anonymous:** allows you to automatically reject messages with a category of anonymous.
 - **Reject Advertisement:** allows you to automatically reject messages with a category of advertisement.
 - **MMS Profiles:** to configure your Network parameters (For more information, refer to “*Changing the WAP Profiles*” on page 161.)
 - **Auto Resize Image:** to configure the limits you'll accept for incoming images. Images larger than your setting, will be resized to meet this value. Options include: No Resize, 100 KB, 300 KB, or 600 KB.
 - **Creation Mode:** provide you with editing and formatting tools. Choose from: Free, Warning, or Restricted.
 - **Default Style:** assigns the “look and feel” for the multimedia message screen with parameters such as: Background Color, Font Color (for text), Font Style, and Slide Duration (during playback).
3. Touch  to store each new settings.

Configuring Voice Mail Settings

There may be times when the voice mail access number might need to be changed. If this is necessary, please obtain the information from the customer service center.

Note: It is recommended that you do not alter these fields without assistance from a customer service representative.

1. From Messaging Settings page, touch **Voice Mail**.
2. Touch the **Voice Mail** field and use your onscreen keypad/keyboard to enter the new Name and Center Address (voicemail phone number).
 - **Name:** allows you to create a new descriptive name for this access number.
 - **Center Address:** allows you edit the existing number and create a new number for use when accessing the remote voicemail.
3. Touch  to store this new information.

Configuring Push Message Settings



A Push Message is a method for your service provider to deliver content (e.g. images, ringtones, software upgrades, information, etc.) to mobile phones that are WAP enabled. You cannot initiate or reply to WAP Push Messages. This message may direct you to go to a URL that is included in the message for further information and/or updates, or it may be information only.

Examples may be firmware updates or emergency notifications.

1. From Messaging Settings page, touch **Push Message**.
2. From the **Receiving Options** field touch **On** (activate) or **Off** (deactivate) to toggle the state of this feature.
3. Touch the **Service Loading** field and choose how applications will be loaded onto your phone: **Always**, **Prompt**, or **Never**.

Used Space

You can check the amount of the memory being used and the memory remaining for Multimedia, Text, Push, and Configuration Messages. The display shows the total space including the used and free space. You can also view how much space is currently occupied by each message box.

1. Touch  → **Messaging** → **Used Space**.
2. Touch a particular folder for review or both size and contents within the selected folder.
3. When you have finished, press .


Section 13: MEdia Mall

The MEdia Mall allows you to shop for Ringtones, Games, Cool Tools/Apps, Videos, Color Graphics, Answer Tones, and Multimedia using the built-in browser. You can also access the MEdia Home site.

- ▶ Touch  → **MEdia Mall**. This then launches the WAP browser to the Media Mall home page.

Downloading Multimedia Files

You can buy a variety of multimedia files, such as ringtones, graphics, applications, Multimedia content, and so on from the WAP browser. Your phone has embedded links to the web sites providing you with download services, preset by your service provider.

1. Touch  → **MEdia Mall**.
2. Touch an onscreen entry such as: **Games, Cool Tools/Apps, Videos, Color Graphics, Answer Tones, or Multimedia Store**.
 - To access the homepage for the online shopping mall, touch **MEdia Net Home**.
3. Touch the onscreen Options button to also access the following options. For more information, refer to “*MEdia Mall Options*” on page 128.


- MEdia Mall Home
- My MEdia Club
- MEdia Mall Account
- Recently View
- Exit

4. Find the item you want to download and follow the onscreen instructions to purchase it.

Note: You can retrieve the messages from the server and then save the items in your phone’s memory. You cannot forward these messages to other people or add the saved items to a Multimedia message.


Ringtones

This option allows you to shop for ringtones using the built-in browser.

1. Touch  → **MEdia Mall** → **Ringtones**. You may have to touch an onscreen entry twice, once to select it and a second time to navigate to that page.
2. Follow the on-screen options. Purchase options include: Full Track Music, Movie Tones, Voice Tones, and Sound Effects.


Games

This option allows you to shop for games using the built-in browser.


1. Touch  → **MEdia Mall** → **Games**. You may have to touch an onscreen entry twice, once to select it and a second time to navigate to that page.
2. Follow the on-screen options to purchase a game.

Cool Tools/Apps

This menu allows you to shop for tools and applications using the built-in browser.


1. Touch  → **MEdia Mall** → **Cool Tools/Apps**. You may have to touch an onscreen entry twice, once to select it and a second time to navigate to that page.
2. If prompted to accept a redirection, touch **Ok**.
3. Follow the on-screen options to purchase an application or tool.

Shopping for GPS Applications

1. Touch  → **AT&T GPS** → **Shop GPS Apps**.
2. Follow the onscreen prompts to purchase additional GPS Applications.


Color Graphics

This menu option allows you to shop for graphic images using the built-in browser. You can download new images to your **Pictures** folder.

1. Touch  → **MEdia Mall** → **Color Graphics**. You may have to touch an onscreen entry twice, once to select it and a second time to navigate to that page.
2. Follow the on-screen options to purchase a color graphic.


Answer Tones

This menu option allows you to shop for answer tones using the built-in browser.

1. Touch  → **MEdia Mall** → **Answer Tones**. You may have to touch an onscreen entry twice, once to select it and a second time to navigate to that page.
2. If prompted to accept a redirection, touch **Ok**.
3. Follow the on-screen options to purchase an answer tone.

Multimedia Store

This menu option allows you to shop for multimedia files (videos) using the built-in browser.

1. Touch  → **MEdia Mall** → **Multimedia Store**. You may have to touch an onscreen entry twice, once to select it and a second time to navigate to that page.
2. When prompted to confirm that you want to “**Open Link in Browser? This link will take you out of MEdia Mall. Continue?**” touch **Ok**.
3. Follow the on-screen options to purchase multimedia content.

MEdia Mall Options

The onscreen **Options** button (visible from the main MEdia Mall homepage). The following options appear:

- **MEdia Mall Home**: takes you back to the MEdia Mall home screen.
- **MyMEdia Club**: enables you to join the MyMEdia Club, where you can earn credits to be used for tones, graphics, and games in the AT&T MEdia Mall.

Note: A monthly charge is applied for MyMEdia membership.

- **MEdia Mall Account**: shows a history of your MEdia Mall account.
- **Recently Viewed**: shows the most recently viewed ringtones, games, videos, graphics, and answer tones.
- **Exit**: takes you back to the Main menu.

Section 14: AT&T Music


AT&T Music provides you access to Streaming Music, Music Videos, Music communities, Music applications, and allows you to both identify and purchase music directly from your handset.

Music Player

The Music Player is an application that can play music files. The music player supports files with extensions AAC, AAC+, eAAC+, MP3, WMA, 3GP, MPEG, MP4, and M4A. Launching the Music Player allows you to navigate through your music library, play songs, and create playlists.

Important! You must create and organize your playlist before you get started. The following characters cannot be used in the filename: < > " ? / \ : * |.

Using the Music Player

1. Touch  → AT&T Music → Music Player.
2. Touch a library category (all music, artist, album, or playlist) to view the available music files.
3. Scroll through the list of songs and touch an entry to begin playback.

Music Player Functions

- Touch any of the following onscreen buttons during playback to activate their features:

Shuffle mode button:



- Shuffle On: the current list of songs are randomly shuffled for playback.



- Shuffle Off: songs play in order and are not shuffled.

Equalizer button:



Equalizer presets include: NORMAL, ROCK, POP, DANCE, CLASSICAL, JAZZ, WIDE, DYNAMIC, and SURROUND.

Repeat button:



- Repeat one: repeats the currently playing song.



- Repeat all: replays the current list when the list ends.



- Play All: plays the current song list once.



- Plays the previous song.



- Touch once to play the current song.



- Touch twice to pause the current song.



- Advances to the next song.

► Touch the player menu options at the bottom of the screen to reveal additional menu functions:

- **Library:** displays the Music Player library view (Now Playing, All Music, Artist, Album, Playlists, and Shop Music).
- **Minimize:** reduces the player and leaves it running in the background so that you can navigate to other programs or activities.
- **More:** provides access to options such as:
 - **Add to Playlist:** allows you to add the current audio file to a selected playlist.
 - **Send via:** allows you to send the current file via a message attachment or as a data file delivered to a Bluetooth-capable device.
 - **Settings:** allows you to access the Background Playing Settings menu.

- **Properties:** allows you to view details for the current song such as Name, Format, Size, Date Created, and Location.

Adding Music to your Handset

Music files (ringtones and full tracks) can be added to your handset by using one or more of the following methods:

- Purchase and download music and ringtones directly to your handset over your wireless carrier's network by using the AT&T Music – Shop Music feature (also accessible from My Stuff).

Note: Audio files smaller than 300 KB are treated as ringtones, whereas audio files larger than 300 KB are stored in the Music Folder. You can not assign an MP3 file larger than 300 KB as a ringtone.




- Transfer music files from a personal computer using a media player application and an optional USB Data Cable and an optional microSD™ Memory Card.

Note: When the Bluetooth feature is active on your handset, USB communication is not be available. To transfer files to your handset, turn off the Bluetooth functionality (**Settings** → **Connectivity** → **Bluetooth**). (For more information, refer to “Bluetooth” on page 67.)

Note: The maximum number of songs you can synchronize between your phone and your PC is 1500.

Shop Music

AT&T Music can be used to shop for ringtones, Answer Tones™ and songs from some of your favorite music stores.


1. Touch  → **AT&T Music** → **Music Player** → **Shop Music**.
This launches the built-in browser.
2. Select your music store of choice (or select **Ringtones**).
3. From the **Categories** listing, select the desired entry. Touch  to return to the previous page.
4. Exit the browser at any time by pressing .

Transferring Music from the Digital Music Stores


In order to download music from the computer to your handset, a microSD card and USB data cable are required. These items are sold separately; go to www.wireless.att.com/cell-phone-service/accessories/.

1. Using your computer, open your preferred Windows Media Digital Rights Management (WMDRM) PC music management client.
2. Download the selected song to your library.

Note: If the music file is protected, Media Player will block the playing or syncing of that file.

3. Verify the pre-insertion of the microSD card into the handset. For more information, refer to *“Installing the Memory Card”* on page 6.
4. Use the USB adapter cable to connect the handset to the target PC. When an active connection has been established, a USB icon () appears on the phone.

Note: If the target computer does not detect the newly connected handset or provide an MTP Player dialog window on the PC screen, please follow steps 6 - 9.


5. Touch  → **Settings** → **Connectivity** → **Select USB Mode** → **Mass Storage**. For more information, refer to *“Configuring Your Phone’s USB Settings”* on page 70.
6. Once the USB connection has been established, the handset displays **“Connected”** and the computer screen then shows your device. If the detection occurs, skip to step 8.
7. Locate the song on your computer and using your right mouse button, click **Copy**.
8. Open the Removable Disk drive corresponding to the microSD card location on the phone.

9. Open the **Music** folder (ex:\Audio\Music) you wish to upload from the handset.
10. Using your right mouse button, click **Paste**. This step begins the download process.

Note: The Music Player does not necessarily support all features of a particular file format nor all the variations of those formats. The Music Player includes support for Windows Media Digital rights Management (WMDRM) which allows you to play some purchased or subscription content. Copyright protections may prevent some images, music (including ringtones) and other content from being copied, modified, transferred or forwarded.

Playing Music through a Stereo Bluetooth Device

Your device supports the Stereo Bluetooth profile (A2DP), and when connected to a stereo Bluetooth headset, will play back music in stereo from the phone through the headset.

1. Pair and connect your handset to a stereo Bluetooth device. For more information, refer to “*Connecting to Other Bluetooth Devices*” on page 68.
2. From the list of compatible devices, select the previously paired Bluetooth headset to begin listening to your song through the headset.
3. Touch  → **AT&T Music** → **Music Player** → **All Music**.


4. Select a song to play within the Music Player.

Playing Music while Using the Phone



The Music Player allows you to play music in the background while performing other tasks on your phone. The music will pause when an incoming call is accepted, and the music will resume when the call is ended. Music will continue to play when you receive a Text Message, Multimedia Message, or an Instant Message.

The other functions you can use are:

- **Call:** make or receive a call (music player is paused)
- **Messaging:** send or receive a text or multimedia message. Music continues to play unless an audio clip is received as a part of a multimedia message.
- **MEdia Net:** browse the web (music continues to play).
- **Music Player:** turns on Music Player, or allows you to use full-screen controls of the music player.
- **Games & Apps:** lets you play games or access applications while listening to music.

Important! When you are finished using the **Music Player** function, you must press  to stop the function to prevent the battery from losing its charge. **Pausing** the player will continue to use the battery.




Music Player Settings

1. Touch  → **AT&T Music** → **Music Player** → **Settings**.
2. Touch **On** or **Off** to either activate or deactivate the Background Playing option. This determines whether you want the music to play in the background while outside of the player.
3. Touch .


Using Playlists

Playlists are used to assign songs to a list of preferred media which can then be grouped into a list for later playback. These Playlists can be created via either the handset's Music Player options menu or from within a 3rd party music application (such as Windows Media Player) and then downloaded to the handset.


Creating a Playlist

1. Touch  → **AT&T Music** → **Music Player** → **Playlists** → **Tap to Create**.
2. Touch the ivory playlist name field and use the onscreen keyboard to enter a descriptive name for the new playlist.
3. Touch  →  to complete the creation process.

Adding Songs to a Playlist

1. Touch  → **AT&T Music** → **Music Player** → **Playlists**.
2. Touch a previously created playlist from the list and touch **Add**.
3. Touch any available music files to place a checkmark alongside their entry (indicating their selection).
– or –
Touch **Select All** to select all available songs from the list.
4. Touch **Add** and wait for the songs to be added to the current playlist.

Remove songs from a Playlist

1. Touch  → **AT&T Music** → **Music Player** → **Playlists**.
1. Touch a previously created playlist from the list and touch **Remove**.
2. Touch any available music files to place a checkmark alongside their entry (indicating their selection).
– or –
Touch **Select All** to select all available songs from the list for removal.



3. Touch **Remove** and wait for the songs to be deleted from the current playlist.

Transferring Music using a Media Application

A USB cable, microSD card, and a current version of a media application (such as Napster® or Windows Media Player®) are required for this procedure.

1. Open the media player on your personal computer (if you are using Windows Media Player, use version 10.0 or higher).


Note: The Napster application can be downloaded at www.napster.com. Subscription fees may apply.

2. Touch  → **Settings** → **Connectivity** → **Select USB Mode** → **Media Player**. For more information, refer to “*Configuring Your Phone’s USB Settings*” on page 70.
3. Use the USB adapter cable to connect the handset to the target PC. When an active connection has been established, a USB icon () appears on the phone.
4. Once the USB connection has been established, the handset displays “**Connected**” and the computer screen then shows your phone.

Note: If the target computer does not detect the newly connected handset or provide an MTP Player dialog window on the PC screen, see “*Transferring Music from the Digital Music Stores*” on page 131.


Note: The following steps reflect the procedure used with Windows Media Player. If you are using either Napster, or some other form of media player, you should refer to that application’s Help files for specific directions.

5. If this is your first time connecting the A867 to Windows Media Player you will need to enter a unique name for this phone connection (ex: A867 Card). This assigns a name to both the phone (when recognized) and to the internal microSD card.



- Click **Finish** to continue onto the application. You will then notice the Sync tab active and displaying a connection with the phone and displaying the name you created.
- From within the Windows Media Player application, click on the **Sync** tab. Available songs are then listed on the left side of the application.


Note: This upper-right area also indicates the amount of free storage space left on the internal microSD.



- If not already active, click the **Sync** tab.
- Choose the destination location for the media files. The **A867 Card** entry (you named) appears in a drop-down list on the left side of the screen.

10. Click on the **Library** entry (from the left column) and select a category to reveal available songs.
11. Click a song from the center column and drag it into the Sync List section of the current page. This then places the current song on a “wait list” for update to the target location within the phone.
12. Click the **Start Sync** button (at the bottom of the Sync List) to begin uploading the selected songs to your handset. A “**synchronization in progress**” message appears on the application. Do not unplug the handset during this process. Once complete, a **Sync Results** folder then appears below the device entry to indicate sync status.
13. It is now safe to unplug the USB connector from the handset.

Importing a Playlist from Windows Media Player

1. Open Windows Media Player on your computer (version 10.0 or higher).
2. Use the USB adapter cable to connect the handset to the target PC. When an active connection has been established, a USB icon () appears on the phone.

3. Once the USB connection has been established, the handset displays “**Connected**” and the computer screen then shows your phone.

Note: If the target computer does not detect the newly connected handset or provide an MTP Player dialog window on the PC screen, see “*Transferring Music from the Digital Music Stores*” on page 131.

4. If not already active, click the **Sync** tab.
5. Locate the Playlist section (upper-left).
6. Right-click a playlist entry and select **Add to ‘Sync List’**.
7. Click the **Start Sync** button (at the bottom of the Sync List) to begin uploading the selected playlist to your handset.
8. It is now safe to unplug the USB connector from the handset.

MusicID


MusicID is an application which uses the onboard microphone to analyze a music sample and then identify the song. Once the application completes the analysis of the song sample, it then provides you with the name of the song, artist and album art as well as opportunities to buy related content.

1. Touch  → **AT&T Music** → **Music ID**.


2. Select any of the following options by touching an entry:
 - **ID song!:** begins the analysis of the song being sampled through the handset's microphone.
 - **manage IDs:** provides a list of recently identified song and allows you to obtain information about the song, delete the song, or send the Music ID as a link to another phone number.
 - **help me out:** provides you with on screen descriptions of several key MusicID features.
 - **exit:** allows you to exit the application and return to the main AT&T Music menu.

To exit the application at any time, simply press .


Using ID song!

1. Touch  → **AT&T Music** → **Music ID** → **ID song!**.
2. Place the handset's microphone up to the source of the song, which can be from either a radio, stereo, or headset. The handset then begins to analyze the audio signal and displays "**Listening**" then "**Analyzing**". If a song match is found, the screen displays the Artist Name, Track Title, and Album cover art.
3. To purchase the song (with ringtone and wallpaper if available), touch **get**.
4. To share the song ID with another user, touch **Share ID**.


5. Touch the **123** button from the bottom of the screen to display an alphanumeric keypad. Use these keys to enter the recipients phone number. Touch **OK** once complete.
6. Touch **ShareID!**. Within a short time they will receive a message containing a Music ID link to the song.
7. If the song can not be found, the handset displays a "Sorry, No Match Try Again!" message. Touch **newID!** and try analyzing the song again.

To exit the application at any time, simply press .


Using Manage IDs

1. Touch  → **AT&T Music** → **Music ID** → **manage IDs**. The screen displays a list of the most recent successful song IDs which were made.
2. Touch a song to highlight it then touch the onscreen **Options** button.
3. Select one of the following options:
 - **ID Info:** displays the Artist Name, Track Title, and Album cover art of the identified song.
 - **Delete ID:** deletes the selected song from the list of identified songs.

- **New ID!**: begins the song analysis process again. Hold the microphone to the song source and wait for analysis.

To exit the application at any time, simply press .

Getting Help with Music ID

1. Touch  → **AT&T Music** → **Music ID** → **help me out**. The screen displays a list of helpful topics related to the musicID application. These topics cover:

- **IDing a Song**: provides information about the analysis process.
- **ID Picks and More!**: describes the process following the successful identification of a song. You can choose to purchase the song and wallpaper (if available) or send the musicID as a link to another phone number.
- **Subscription**: provides details about the general usability and monthly term information.
- **About MusicID**: provides information about the MusicID software version.

Exiting from the Music ID Application


- ▶ Exit the application by simply pressing  → **Yes**.

XM Radio

This service allows you to stream over 20 channels of commercial free music through your handset.

Note: Since this product uses a large amount of data in its stream process, you should note that you are responsible for all data charges incurred. It is recommended that you subscribe to a MEdia Max data bundle so that you are not charged for data overages.

Note: XM Radio does not work with Bluetooth. Periodically, the application will ask the customer to confirm they are still listening to the stream.

1. Touch  → **AT&T Music** → **XM Radio**.
2. During the initial setup, touch **OK** to acknowledge the data service usage information and verify your subscription.

Note: This is a paid service, initially you will only be allowed a 10 minute trial period before you have to register for the paid service.

3. Touch **Accept** to agree to the terms of the XM Radio service and follow the on screen prompts.
4. Select a radio station category from the guide list.
5. Select a specific radio channel to start the music streaming to your phone.

6. Touch **Buy** to purchase the music content associated to the selected channel.

Music Videos


For more information, refer to “*Music Videos*” on page 78.

Pandora

This service allows you to enjoy all the stations you've created on the web - and create new ones right from your mobile phone.

You can enter the name of your favorite artist or song, and the system will generate a radio station featuring not only the selected song, but also similar songs you might enjoy.

You can also rate songs using thumbs up and thumbs down, which allows the application to better personalize the songs offered on your stations. You can also allows bookmark your favorite artists and songs. The Pandora™ application on your phone is fully integrated with its web counterpart, so that everything you create, rate, or bookmark on your mobile phone then appears the next time you're back on the web.

1. Touch  → **AT&T Music** → **Pandora**.
2. If you agree to the high data use by this application, touch **OK** (right onscreen key). Read and answer the remaining prompts.

3. Register for the service by entering a unique email address (username) and password, the touch **OK**.

Note: It is not recommended that you use the same password as is currently active for your email account.

4. Follow the onscreen prompts.

Exit the application by simply pressing .

Community

The Community is a place where you can find a listing of various fan sites that provide sound clips, wallpapers, bios, discographies, and other information about an artist.

1. Touch  → **AT&T Music** → **Community**.
2. Select a fan site and follow the onscreen instructions.

Exit the application by simply pressing .

Music Applications

The Music Applications option accesses the internet to provide Music tools for your handset. Services provided on this site may include, Music ID, MobiRadio, Billboard Mobile Channel, MobiTV: Live TV, and MobiTV en Español.

1. Touch  → **AT&T Music** → **Music Applications**.
2. Select a music site and follow the onscreen instructions.

Section 15: AT&T GPS

AT&T GPS provides you with access to real-time GPS-driven applications. These programs not only allow you to achieve real-time GPS enabled turn-by-turn navigation, but also access local searches based on a variety of category parameters. The system is also future upgradeable via the purchase of additional GPS applications.


Global GPS turn-by-turn navigation—mapping and Point of Interest content for three continents, including North America (u.s., Canada, and Mexico), Western Europe, and China where wireless coverage is available from AT&T or its roaming providers

AT&T GPS is an audible and visual, JAVA-based driving aid that uses a GPS signal to provide turn-by-turn directions.

The application is a separately licensed product that requires you to download the feature to your handset, and accept the license agreement before using. A trial period is provided for you to test it for your own use.

Important!: You must have a data plan to use this feature.


Launching AT&T Navigator


1. Touch  → **AT&T GPS** → **AT&T Navigator**.
2. Touch the onscreen **Free Trial** button to activate the 30-day trial and create a temporary account. A 30-day free trial period is provided with a notice that if you do not cancel within 30 days then you are charged for the GPS service.

Important!: After the trial period, a monthly recurring charge for AT&T Navigator will apply. Contact your AT&T service provider for details.


3. Read the warning disclaimer and touch **Agree** to acknowledge the terms of use.
4. Touch **Yes** to take a brief tour of the AT&T Navigation features and functionality, or **No, Skip Tour** to continue to the main navigation screen.

Using the Navigator

Although your phone does not come with left and right softkeys, these are available as onscreen buttons so you can activate their corresponding features. Touch  below an onscreen option to activate the function.

1. Touch  → **AT&T GPS** → **AT&T Navigator**.
2. Select an option and follow the onscreen instructions to activate a Navigator features.
 - **Drive To:** lets you get driving directions from wherever you are to wherever you're going. Choices include:
 - **My Favorites:** displays your favorite (marked) GPS navigation sites.
 - **Recent Places:** displays your recently entered locations.
 - **Address:** displays manually entered locations.
 - **Intersection:** used to locate a specific address by using two separate street addresses to identify an intersection. These can be entered either manually (Type It) or by speaking into the phone (Speak It).
 - **City:** allows you to enter a city, State and/or Province for navigation.
 - **Businesses:** allows you to enter a business type or name, category, or location.
 - **Airports:** allows you to use either local airports based on current a GPS location or manually enter the 3-letter airport code or name.
 - **Search:** allows you to search for the address by either speaking it or by entering the information manually. This function lets you search for locations from options such as: Food/Coffee, Gas

Stations, Gas By Price, Banks/ATMs, WiFi Spots, Parking Lots
Hotels & Motels, and Movie Theaters.

- **Maps and Traffic:** provides access to 2D and 3D maps for both your current location and for several categories of locations such as Airports and Contacts.
 - **Tools & Extras:** provides additional features such as sharing your location with contacts, recording your current location, creating and storing My Favorites locations, accessing the product tour, enabling a real-time compass, and setting detailed application preferences.
3. Press  to return to the Main menu.




Note: These services require the purchase of a subscription.

Obtaining Driving Directions


The A867's built-in GPS hardware allows you to get real-time driving directions to selected locations or establishments based on your current location.

Using a Physical Address

1. Touch  → **AT&T GPS** → **AT&T Navigator** → **Drive To** → **Address** → **OK**.


2. Touch either **Type It** or **Speak It**.
 - **Type It:** requires that you enter the physical address using either the keypad or onscreen keyboard.
 - **Speak It:** allows you to place a call to the TeleNav™ operator where you will speak the desired address. This is similar to calling 411 for directory assistance.
3. If typing in the address, touch the following fields and use the onscreen alphanumeric keypad to enter the necessary information:
 - **Street:** used to enter a street address. Touch  to complete.
 - **City:** to enter the city for the address. Touch  to complete.
 - **State/Province** or **ZIP/Postalcode:** additional information that can provide a more detailed search. Touch  to complete.
4. Touch **Done** to begin the search process and receive driving directions from the GPS network.
5. Follow both the onscreen and audio directions.

Shopping for GPS Applications

1. Touch  → **AT&T GPS** → **Shop GPS Apps**.
2. Follow the onscreen prompts to purchase additional GPS Applications.

Where

WHERE™ is a downloadable mobile application that uses your current location (obtained via the built-in GPS) to help you find places of interest, things to do, and local information while you're on the go.

1. Touch  → **AT&T GPS** → **Where**. A seven-day free trial period is provided with a notice that if you do not cancel within seven days then you are charged for the GPS service.

Important! After the trial period, charges for Where service apply. Contact your service provider for details.

2. Read through the onscreen and touch **Agree** to accept the Terms of Service.
3. Touch either **Buy Now** (to purchase the service) or **Continue Trial** (to continue the trial period). The following menu options then appear in the display:
 - **add free widgets:** allows you to download and manage your widgets.
 - **Starbucks:** allows you to locate the nearest Starbucks.

- **Yelp:** allows you to search for the address, phone numbers, and reviews of restaurants, shopping, arts and entertainment, and hotels and travel.
- **Eventful Events:** allows you to search for in Music, Performing Arts, Sports, Single, Social, Food, Cuisine, Wine, and Family Fun categories.
- **GasBuddy:** allows you research gas pricing in your area.
- **AccuWeather:** allows you to check the local weather.
- **Insider Alerts:** allows you to insider alert information for your current area.

4. Touch an option and follow the onscreen prompts.

These services require the purchase of a subscription.

Section 16: Applications

The on-board applications (such as camera, camcorder, calendar, and alarms) can be supplemented with additional applications which can be purchased through the AT&T Mall.

Tools

Tools are feature options that allow you to use your handset for a variety of non-phone related activities. To access any of the tools, perform the following:

- ▶ Touch  → **Tools**.





Camera

For more information, refer to “*Camera*” on page 108.

Record Audio




Record Audio allows you to record voice memos. It also allows you to send your audio clip to other people as an attachment of an MMS message. Recording time will vary based on the available memory within the phone.

1. Touch  → **Tools** → **Record Audio**. For more information, refer to “*Record Audio Settings*” on page 73.
2. To start recording, touch . Record a memo by speaking into the microphone.

3. During the recording process you can either touch Stop () to stop the recording or Pause () to temporarily halt the recording. Once the audio recording has stopped, the message is automatically saved.
4. Once stopped, choose from one of the following options:
 - **Play**: allows you to play the memo.
 - **Record**: allows you to save the current memo and begin another session.
 - **Delete**: allows you to delete the current memo.
 - **More**: provides these additional functions.
 - **Send via**: allows you to send your voice clip to other people using either a message or to a Bluetooth device.
 - **Set as**: allows you to set the music file as a Call Ringtone, a Caller Ringtone for a specific entry or an Alarm Tone.
 - **Properties**: displays the Name, Format, Size, etc.. of the current voice memo.
5. To exit, press  or press .


Recorded Audio Folder

This folder shows a list of audio clips that have been recorded and saved. To access this folder, use the following steps:

1. Touch  → **My Stuff** → **Audio** → **Recorded Audio**.
2. Touch a pre-recorded memo from the list to begin playback.
3. To exit, press  or press .

Alarms

This feature allows you to both set the alarm to ring at a specific time.

1. Touch  → **Tools** → **Alarms** → **Tap to Create**. The following options display:
 - **Alarm Name:** allows you to use a specific name for the alarm. The name will appear on the display when the alarm activates.
 - **Alarm Time:** use either the Up/Down input arrows or scroll through the available fields to set the new time for the event, at which time an alarm will sound. Touch **Set** to save the new values.

Note: To change the time format, see “Time & Date” on page 60.


- **Alarm Repeat:** use this option to set the repeating status for the alarm by placing a checkmark alongside those days you would like to use for the current alarm. **Everyday** places a checkmark alongside all days.
 - **Set Details:** allows you modify some additional features:
 - **Alarm Type** sets the way in which the alarm sounds when activated (Melody, Increasing Melody, Vibration, Vibration then Melody, Vibration & Melody, and Vibe & Increasing Melody).
 - **Alarm Tone** sets the sound file which is played when the alarm is activated.
 - **Alarm Volume** adjusts the alarm's volume (1 - 7).
2. Touch **Save** to store the alarm details and **Save** again store this new event.
 3. Touch **On** from the **Auto Power-up** field to keep the alarm event active even if the phone is turned off. Activating this feature turns the phone on and sounds the alarm even if the phone was previously is a powered-off state.

Note: To stop the alarm when it rings, locate the **Stop** slider on the screen and slide it across to the right until the alarms stops, or you can also press any key, such as: volume, , , etc..

Calendar

The calendar feature allows you to view the Month, Week, and Day layout views. It also shows any Missed Alarm Events that have occurred.

Creating a New Event

1. Touch  → **Tools** → **Calendar** → **Create Event**.
2. Touch the **Title** field and use the onscreen keyboard to enter a name for this specific event. Touch **OK** to save the new name.
3. Touch the **Start Date** field and use either the Up/Down arrows or scroll through the available fields to set the new date. Touch **Set** to complete the process.
4. Touch the **Start Time** field and use either the Up/Down arrows or scroll through the available fields to set the new time. Touch **Set** to complete the process.

Note: Touching and holding down the arrows (up or down) increases the speed at which the numbers scroll through each reel.

5. Touch the **Alarm** field and select a time for the alarm to begin alerting you of the upcoming event. Touch **Save** to store the new alert time.




- Choices include: Off, On Time, 30 Minutes Before, 1 Hour Before, 1 Day before, 1 Week Before, Customize (your own defined schedule).

6. Touch **Set Details** to configure additional parameters for the new event:




- **End Date:** enter final date for this event to occur. This is useful if the alarm is for a repeating event. Touch **Set** to store the date.
- **End Time:** enter final time for this repeating event. Touch **Set** to store the time.
- **Details:** enter a description for this event. Touch **OK** to store the name.
- **Location:** enter a location for this event. Touch **OK** to store the name.
- **Alarm Tone:** allows you to choose an alarm tone. Once highlighted, navigate to the Audio folder and select an audio file. Touch **Add** to assign the file as your new alert tone.
- **Repeat:** allows you to set the number of repetitions allowed for this appointment (Off, Everyday, Every Week, Every Month, or Every Year). Once selected, all remaining alarm settings are enabled. Touch **Save** to store the option.
 - **Every:** allows you to set the number of times the entry is to repeat in the selected time frame.
- **Repeat Until:** allows you to set as duration for this appointment by assigning an expiration date.

7. Touch  →  to store the new event.




Other Event Options

1. Touch  → **Tools** → **Calendar** → **More**.
2. Touch any of the following options:
 - **Go to**: allows you to manually select a target date for review by using the Go To dialer page. Touch **Go** to be taken to the dialed-in date.
 - **View by Day**: allows you to change the Calendar view to display a daily event listing.
 - **View by Week**: allows you to change the Calendar view to display a weekly event listing.
 - **Delete**: allows you to remove an event from your Calendar.
 - **Calendar Settings**: allows you to configure the Calendar's Starting Day (select either Sunday or Monday) and Default View Mode (select Month, Week, or Day view).
 - **Missed Alarm Events**: displays any missed events.
 - **Used Space**: displays a list of the different Calendar event categories along with the memory allocation for each.
3. To exit, press  or press .

Viewing an Event

1. Touch  → **Tools** → **Calendar** → **Event List**. A listing of all upcoming events is then displayed.
2. Touch an event from the Events page to then open that instance.
3. To exit, press  or press .

Deleting an Event

1. Touch  → **Tools** → **Calendar** → **Event List** → **Delete**.
2. Touch an individual event from the list or touch **Select All** to place a checkmark adjacent to all events.
3. Touch **Delete**.
4. To exit, press  or press .


Recent Calls

The phone stores the numbers of the calls you've dialed, received, or missed in the **Recent Calls** menu. If the number or caller is listed in your Address Book, the associated name displays.

For more information, refer to “Recent Calls” on page 32.



Tasks

This menu option allows you to create a “to do” entry of tasks which are created in a similar fashion to previously described Calendar entries.

1. Touch  → **Tools** → **Tasks** → **Tap to Create**.
2. Select any of the following options:
 - **Title**: enter a title for this task (up to 15 characters).
 - **Priority**: allows you assign the task a priority (High, Medium, or Low).
 - **Start Date**: enter a date for this task to begin.
 - **Due Date**: enter a date for this task to end.
 - **Status**: allows you assign a current project status (Completed or Ongoing).



3. Touch **Set Details** to access additional options:

- **Details**: enter a detailed description for this task (up to 100 characters).
- **Alarm**: allows you to set a time prior to the event where the event alerts will begin.
- **Alarm Time**: enter a time for this alarm to sound. Touch **Set** to assign the new time.
- **Alarm Tone**: allows you to choose an alarm tone. Once selected, navigate to the Audio folder, select a file, and touch **Add** to assign the audio file as the current alarm tone.

4. Touch  →  to store the new task.


Memo

This option allows you to create memos to add to your events.

1. Touch  → **Tools** → **Memo** → **Create Memo**.
2. Use the onscreen keyboard to enter a new memo and touch .

Calculator


With this feature, you can use the phone as a calculator. The calculator provides the basic arithmetic functions; addition, subtraction, multiplication, and division.




1. Touch  → **Tools** → **Calculator**.
2. Enter the first number using the onscreen numeric keys.

3. Enter the operation for your calculation by touching the corresponding onscreen arithmetic function key.
4. Enter the second number.
5. To view the result, touch equals (=).

Converter


Your phone comes with a built-in conversion application. This conversion menu provides the following conversion categories:


- Currency
 - Length
 - Weight
 - Volume
 - Area
 - Temperature
1. Touch  → **Tools** → **Converter**.
 2. Select the specific converter function by touching one of the above onscreen conversion functions.
 - Each converter function has a field for the type of unit to be converted, and the type of unit to convert to. An additional field allows you to input the unit amount to convert.

3. Enter the main value by touching the first onscreen value field (top left of the page).
4. Use the keypad to enter the necessary value and touch .
5. Touch the drop-down list (upper-right) to then select the desired source unit. This is the value you are converting “from”.
 - The resulting converted values (“to”) are the automatically displayed in a list.
6. Touch **Reset** to erase the current values and begin again.
7. To exit, press  or press .

World Clock

World Clock allows you to view the time of day or night in another parts of the world. World displays time in the 100 different cities, within all 24 time zones around the world.

1. Touch  → **Tools** → **World Clock** → **Add**.
2. Touch and drag the onscreen map to find the desired global region.

3. Touch a representative city from a desired area. If the city area is then correctly highlighted in blue, your selection was accurately read and you can touch .

– or –


If not read correctly, repeat the previous two steps until your selection is correct.

Deleting a World Clock Entry

1. Touch  → **Tools** → **World Clock** → **Delete**.
2. Touch the Trash Can () next to the entry you wish to delete.

Timer

You can use this menu to set a countdown timer. Use a timer to count down to an event based on a preset time length (hours, minutes, and seconds).

1. Touch  → **Tools** → **Timer**.
2. Select a countdown time length for the alert by setting the Hours, Minutes, and Seconds value.

Note: Touching and holding down the arrows (up or down) increases the speed at which the numbers scroll through each reel.

3. Touch **Start** to begin the timer and touch **Stop** to pause the timer.


Stopwatch

You can use this menu to measure intervals of time.

1. Touch  → **Tools** → **Stopwatch** → **Start**.
2. Touch **Stop** to stop the stopwatch and touch **Lap** to mark a unit of time per lap.
3. Touch **Reset** to erase all times recorded.

Yellow Pages


The Yellowpages.com application provides quick and ready access to businesses, map locations, and storage of your favorite searches (My Place). A leader in local search, this application allows you to tap into local businesses, locations, and events, connecting you to your search in real-time.

1. Touch  → **Yellowpages**.
2. Follow the onscreen prompts to enter the desired business name, location or search by category types.

Section 17: Web

Your phone is equipped with a WAP (Wireless Application Protocol) browser which allows you to access the Internet. This section explains how to access the WAP services of your service provider and navigate the WAP browser.

Accessing the WAP Browser

► In Idle mode, touch  and select any one of the following menu options:


- **MEdia Mall** → **Ringtones / Games / Cool Tools/Apps / Color Graphics / Answer Tones / Multimedia Store / MEdia Net Home** (For more information, refer to “MEdia Mall” on page 126.)
- **AT&T Music** → **Music Player / Shop Music / MusicID / XM Radio / Music Videos / Pandora / Community / Music Applications** (For more information, refer to “AT&T Music” on page 129.)
- **MEdia Net** → **MEdia Net Home** (For more information, refer to “Accessing the MEdia Net Homepage” on page 160.)

Tip: You can also access the WAP browser from the **My Stuff** menu by selecting any of the “Shop” options in any of the My Stuff sub-menus.

Navigation Using the WAP Browser

Navigation within web pages is all driven via touch points on the screen.

Browser Window Overview



Note: The default view for the browser is to display as much of the web page without the Web Toolbar.



Back: returns you to the previous web page.



Reload: reloads the current page with updated information.



Magnify: launches the magnification slider that allows you to zoom a web page either in or out.



Add to Favorites: bookmarks the current page and marks it as a favorite site.



Favorites: accesses and displays the bookmarks assigned as favorite web pages.



Home: returns you to the currently assigned homepage.




Fullscreen View: indicates the page is being displayed in a fullscreen view either in a Portrait or Landscape orientation. No toolbars are visible.



Toolbar View: toggles the state of the onscreen Web Toolbar so these onscreen buttons become visible.

Changing the Orientation of the Web page

The A867 comes equipped with an orientation detector that can tell if the phone is being held in an upright (Portrait) or sideways (Landscape) orientation. This is useful when entering text. If the phone is sideways, an onscreen keyboard is displayed. When upright, only the alphanumeric keypad is shown.




- ▶ From within any active web page, change the orientation:
 - Turn the phone on its side to see a Landscape/Widescreen view of the current page.
 - Turn the phone upright to see a Portrait view of the current screen.

Viewing the Page in Full Screen Mode



By default, only the Navigation Toolbar and Screen View icons are displayed on the screen. The Screen View button can be used to either reveal the Web Toolbar or remove it to reveal more of the current page.

Magnifying the current page

From an active page you can toggle the view by touching the Screen View button.

1. Touch  from the upper-right of the current web page.
2. Touch the magnification slider (at the bottom when in landscape or on the right when in portrait) and drag to one side or another


– or –

Touch  to zoom into the page or  to zoom out. This enlarges or shrinks the size of the displayed page in increments.

Scrolling Within a Web Page

As with other menu items and pages on your phone, scrolling requires that steady directional pressure be applied onscreen via your fingertip.

Scrolling



Moving Around

To scroll up or down a Web page

- ▶ Touch and slide your finger either up or down on the screen.


To move around a Web page:

- ▶ Touch and drag across the screen in any direction.


Note: The page must be magnified enough so there are unseen areas to where you would move to. If the page is already being displayed in its entirety, you will not be able to move around it.

Accessing the Web Toolbar

From an active page you can toggle the view by touching the Screen View button.

1. Touch either  to change the view to Fullscreen without Toolbars. This view maximizes the viewable area of the current page.

– or –

Touch  to launch (make visible) the Web Toolbar.

2. Navigate around the web page.

Selecting Onscreen Items

- ▶ Touch an onscreen item or hyperlink.


Links, which are displayed as underlined and colored text, allow you to jump to other Web pages, select special functions, or even activate an application.

Entering Text Into a Search or Text Field




Touch an onscreen text field (such as the Navigation Toolbar) once to reveal an onscreen keyboard.

Touch a search field **twice** to display the text input screen and the onscreen keyboard. For more information, refer to “*Entering Text*” on page 40.

Returning to the Previous Page

- ▶ Touch  from the left of the Navigation Toolbar’s Address bar.

Returning to the Homepage

1. Touch   (Toolbar View) to launch the Web Toolbar.
2. Touch  to return to the homepage.

Navigating via a URL Address


1. In Idle mode, touch  → **ME** → **Media Net** → **Enter URL**.
2. Use either the onscreen alphanumeric keypad or keyboard, to enter the target Web address, beginning with the **www**. The **http://** prefix is pre-inserted into the text string.
3. Touch  to go to the ENTER URL page where you have the opportunity to also add the new page to your Favorites list and assign a display name for the link.

4. Touch  to launch the new web page.







Using Favorites


While navigating through either the Internet or the MEdia Net pages, you can bookmark a site to quickly and easily access it at a future time. The URLs (web site addresses) of the bookmarked sites are stored in the Favorites folder, where you can use the six preset favorites and store your own favorite URLs.

Accessing a Web Site Using Favorites





1. In Idle mode, touch  → **MEdia Net** → **Favorites**.
2. Touch a bookmark item from the Favorite list. The preset bookmarks consist of:
 - **My Account**
 - **Chat Group**
 - **News**
 - **Sports**
 - **Weather**
 - **MEdia Net (homepage)**

Adding Favorites




1. In Idle mode, touch  → **MEdia Net** → **Favorites** → **Add New**.
2. Touch the **Enter URL Address** field and use the onscreen alphanumeric keypad to input the desired web address. Touch  to continue.
3. Touch the **Title** field to associate a display name for this link.
 - Use the onscreen alphanumeric keypad to input the desired web address. Touch  to continue.
4. Touch  to store the new Favorite entry.
– or –
 1. In Idle mode, touch  → **MEdia Net** → **Enter URL**.
 2. Use the onscreen alphanumeric keypad to input the desired web address. Touch  to continue.
 3. Place a checkmark to add the current entry to the Favorites list by touch the **Add to Favorites** field.
 4. Touch the **Title** field to associate a display name for this link.

5. Touch  to store the entry and launch the web page.

Editing Favorites

1. In Idle mode, touch  → **MEdia Net** → **Favorites**.
 - Only those entries with  can be edited.
2. Touch  adjacent to a favorite entry. Do not touch the name, as this will launch the assigned web site.
3. Touch either the Enter URL Address or Title fields and use the onscreen alphanumeric keypad to input the desired web address.
4. Touch  to store the changes to the entry.



Deleting a Favorite

1. In Idle mode, touch  → **MEdia Net** → **Favorites**.
 - Only those entries with  can be deleted.
2. Touch .
3. Place a checkmark adjacent to those editable entries you wish to choose for deletion.
– or –
Touch **Select All** to place a checkmark alongside all deletable fields.

4. Touch .

Copying a URL to a Message

Copying a selected URL as text into a message requires that the selected URL Address already be saved as a Favorite entry.

1. In Idle mode, touch  → **MEdia Net** → **Favorites** → **More** → **Copy URL to Message**.
2. Touch a Favorite entry and touch .
3. Touch the **Tap to Add Recipient** field to use the onscreen keypad/keyboard to enter the recipients phone number.
4. Continue the creation of the remaining message. For more information, refer to “*Messaging*” on page 117.

Sending a URL

A selected URL can also be sent as a file attachment within a new text message but also transmitted to any paired Bluetooth device that can receive the data.

1. In Idle mode, touch  → **MEdia Net** → **Favorites** → **More** → **Send URL via**.

2. Touch one of the following options and follow the onscreen prompts to complete the process:

- **Message:** attaches a selected Favorite URL Address to a new multimedia message.
- **Bluetooth:** sends selected Favorite URL Address as a data file to a paired Bluetooth device capable of using the file.

3. Touch a Favorite entry and touch .

Browser Settings


To configure the parameters on the onboard browser, use the Browser Settings page.

1. In Idle mode, touch  → **MEdia Net** → **Browser Settings**.
2. Touch any of the following function fields.
 - **Clear Caches:** deletes the information stored in the cache. The cache stores the most recently accessed pages (page 157).
 - **Delete Cookies:** delete cookies. Cookies are pieces of personal information sent to a web server while navigating the web (page 158).
 - **Cookie Options:** sets whether cookies are stored on your phone (**Accept All** or **Reject All**). If you select **Prompt**, the phone will ask you to save the cookies on every page requiring cookies.
 - **Delete History:** deletes the record of any previously visited web sites.

- **Preferences:** changes the settings for the web browser to suit your preference.
- **Browser Profiles:** deletes the current browser profile. For more information, refer to *“Changing the WAP Profiles”* on page 161.
- **About Browser:** displays the access version and copyright information about the browser.

3. Touch **Yes** to activate the feature.

– or –

Touch  to save the new setting.

Clearing Caches

A cache is the phone's temporary memory in which the most recently accessed web pages (and their associated images) are stored. The cache can be cleared at any time from your phone.

1. In Idle mode, touch  → **MEdia Net** → **Browser Settings** → **Clear Caches**.
2. At the **Clear cache?** pop-up, touch **Yes** to continue, or **No** to cancel the operation.

Deleting Cookies

A cookie is a small file that is placed on your phone by a web site during navigation. In addition to containing some site-specific information, it can also store some personal information (such as username and password) which can pose a security risk if not properly managed. Cookies can be deleted at any time from your phone.

1. In Idle mode, touch  → **MEdia Net** → **Browser Settings** → **Delete Cookies**.
2. At the **Delete cookies?** pop-up, touch **Yes** to continue, or **No** to cancel the operation.

Setting Cookie Options

You can define how to manage cookie installation on your phone when a web site is attempting to place them on your phone.

1. In Idle mode, touch  → **MEdia Net** → **Browser Settings** → **Cookie Options**.
2. Touch one of the following options:
 - **Accept All:** allows all cookies to be placed on your phone.
 - **Reject All:** allows no cookies to be placed on your phone.
 - **Prompt:** allows you to be prompted before a cookie can be placed on your phone.


3. Touch  to save the new setting.

Using your History

The History list provides you with a list of the most recently visited web sites. These entries can be used to quickly return to a previously unmarked web pages without the need to retype the entire address.

Accessing your History List

1. In Idle mode, touch  → **MEdia Net Home**.



2. Touch the **Toolbar View** ( ) to launch the Web Toolbar.

3. From the Navigation Toolbar (at the top of the web page) touch the History List drop down arrow to reveal the current stored list of visited web sites.
4. Touch an entry from the list to automatically be taken to the selected web site.

Deleting Your History List


A cache is the phone's temporary memory in which the most recently accessed web pages (and their associated images) are stored. The cache can be cleared at any time from your phone.

1. In Idle mode, touch  → **MEdia Net** → **Browser Settings** → **Delete History**.
2. At the **Delete History?** pop-up, touch **Yes** to continue, or **No** to cancel the operation.

Setting Browser Preferences

The **Preferences** option allows you to set your browser's ability to run JavaScript, display images, and play sounds.

1. In Idle mode, touch  → **MEdia Net** → **Browser Settings** → **Preferences**.


2. Activate any of the following by touch an option:
 - **Run JavaScript**
 - **Display Images**
 - **Play Sound**
3. Touch either **On** (to activate the feature) or **Off** (to deactivate the feature).
4. Touch  to save the new setting.

About Browser

The **About Browser** option gives the browser software version information.

1. In Idle mode, touch  → **MEdia Net Home** → **Browser Settings** → **About Browser**.
2. Once finished, press  to return to the previous page.

Accessing the MEdia Net Homepage

1. In Idle mode, touch  → MEdia Net → MEdia Net Home.

The content of the start-up homepage contains the following selections:

- **Search field:** allows you enter a text string into the field and then search the MEdia Net database for matches. For more information, refer to “*Entering Text Into a Search or Text Field*” on page 154.
- **My Links:** provides you with quick access to your those sites which you have setup in this category. Touch an entry to launch the site.
- **Categories:** provides you with a list of MEdia Net web pages containing links to a variety of special interest sites. Touch an entry to launch the site. These categories can be edited from within Customize MEdia Net.

Note: Prior to using these services, you must complete the MEdia Net registration process located at: att.com/wireless, or you must agree to the terms of the service agreement and setup the service on your handset.

- **My Account:** provides you with access to a listing of your most recent purchases and available product (services). From the My Account screen, touch **My Purchases** to begin.

- **Customize MEdia Net:** provides you with a list of MEdia Net setup and service options which allow you to configure different aspects of the MEdia Net experience. Touch an entry to launch the option.
 - **Edit My Links:** provides you with a list of available Internet links which you can choose to add to your **My Links** section of the main Media Net homepage. To add a link, navigate to the **Add to My Links** section and touch an entry. To remove a link, navigate to the **Move/Delete Links** section and touch an entry. From the Edit My Links page, touch **Remove**.
 - **Edit Categories:** allows you to edit those category entries which appear on the MEdia Net homepage. Although the first four entries (WHAT'S HOT, Tones, Games, Pics, and CV) can not be removed, the remaining entries can be toggled on or off. Touch a category entry to toggle it on (appear on the page) or off (remove it from the homepage).
 - **Parental Controls:** provides you with settings which can be configured to restrict certain media content from being downloaded on the phone. (For more information, refer to “*Parental Controls*” on page 78.)
 - **Username & Password:** allows you to setup a username and password prior to gaining access to the MEdia Net homepage and related services.

Note: Prior to using this service you must agree to the terms of the service agreement and setup the service on your handset.


- **MEDIA Net Mail:** allows you to access and edit the entries found within the MEDIA Net messaging center. Although most of the entries can not be removed, the remaining entries can be toggled on or off by navigation to the top of the page, touch **Edit**. From the Mail & Messaging page, touch an entry to toggle it on (appears on the Mail & Messaging page) or off (remove it from the Mail & Messaging page).
- **MEDIA Net Tour:** allows you to take a quick guided tour through the main features of the MEDIA Net pages (homepage, navigation, teams, etc.).
- **Privacy Policy:** provides the web address for Cellular's Privacy Policy.
- **Help:** provides you with list of some of the most frequently asked questions regarding MEDIA Net functionality. Touch a question to launch an on screen description

2. To exit the browser at any time, simply press .

Accessing the MEDIA Net Site

The **MEDIA Net Home** menu option allows you to access your MEDIA Net homepage using the built-in browser. This page gives you quick access to information such as local weather, sports scores, horoscope information and quick links to the previously mentioned shopping sites. To access this menu option, use the following steps:

There are several ways to access a web site:

- In Idle mode, touch  → **MEDIA Net** → **MEDIA Net Home**.
- Selecting a link on the browser.
- Selecting an item in the Favorites menu.
- Entering a URL address manually, using the **Go to URL / Enter URL** browser option.

Changing the WAP Profiles

To configure the settings for text message, multimedia messages, Voice mail, and Push messages.

- ▶ From Idle mode, touch  → **Settings** → **Applications**
Settings → **Browser**.

Connection can be made via either one of three available connection profiles: MEDIA Net, AT&T MMS (MultiMedia Server), or AT&T IMS. Use this menu to create and customize the profiles containing the settings for connecting your phone to the network. You need these settings to use the WAP browser or to send MMS messages or Email messages.


Note: Although the active connection can be changed by the user, it is recommended that this choice be made with the assistance of either the retailer or customer service representative.

1. In Idle mode, touch  → **MEdia Net** → **Browser Settings** → **Browser Profiles**.

2. Touch one of the following profiles:

- **MEdia Net**
- **AT&T MMS**
- **AT&T IMS**

Caution! The WAPs are pre-configured and can not be altered using this screen. The MMS connection option can be edited, renamed, or deleted using this screen. Your phone is set up by default for connecting to the network. If you change the settings without first checking with your service provider, the web browser, MMS, and e-mail features may not work properly.

3. To create a new connection profile, touch  and follow the onscreen prompts.

– or –

To edit an existing profile, touch a profile from list, scroll to the desired field, and use the onscreen keypad/keyboard to edit the parameter you want to edit:

- **Set Name:** enter a profile name.
- **Access Name:** edit the access point name.

- **Auth Type:** select the type of authentication used for this WAP connection: None, Normal, or Secure.
- **User ID:** enter the User ID required to connect to the network.
- **Password:** enter the user password required to connect to the network.
- **Protocol:** set the connection protocol used by the WAP browser: WAP or HTTP.
- **Home URL:** enter the URL address of the page to be used as your homepage.
- **Gateway Address:** (WAP only) enter the gateway address of the proxy server.
- **Proxy Address:** (HTTP only) set the proxy server address and port.
- **Secure Connection:** (WAP only).
- **Linger Time (sec.):** set a time period (in seconds) after which the network is disconnected if there has been no new data traffic in that time.
- **Advanced Settings:** (touch ) allows you to configure some of the IP-specific information: Static IP, Static DNS, Server information, and Traffic Class.
 - **Static IP:** specify if you want to manually enter an IP address. If you want the IP address to be automatically assigned by the server, remove the check mark.
 - **Local Phone IP:** enter the IP address obtained from the network operator, if you checked the Static IP option.

- **Static DNS:** specify if you want to manually enter the Domain Name Server (DNS) address. If you want the address to be automatically assigned by the server, remove the check mark.
- **Server 1/Server 2:** enter the Domain Name Server (DNS) addresses.
- **Traffic Class:** select the traffic class.

4. Touch  to save these settings

The WAP settings may vary depending on the service provider.

Section 18: Accessibility

*TTY Settings**

TTY (also known as a TDD or Text Telephone) is a telecommunications device that allows people who are deaf or hard of hearing, or who have speech or language disabilities, to communicate via a telephone. This phone comes TTY-ready and only requires the insertion of the TTY device to enable this feature.

Use the following steps to access the TTY settings:

- ▶ Inserting a TTY connector into the Headset/Adapter jack (on the left side of the phone) enables this function.

For additional technical support you may access the following website or call 1-888-987-4357.

http://www.samsungtelecom.com/contact_us/accessibility.asp

Section 19: Health and Safety Information

This section outlines the safety precautions associated with using your phone. These safety precautions should be followed to safely use your phone.

Health and Safety Information

Exposure to Radio Frequency (RF) Signals

Certification Information (SAR)

Your wireless phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the exposure limits for radio frequency (RF) energy set by the Federal Communications Commission (FCC) of the U.S. government.

These FCC exposure limits are derived from the recommendations of two expert organizations, the National Council on Radiation Protection and Measurement (NCRP) and the Institute of Electrical and Electronics Engineers (IEEE).

In both cases, the recommendations were developed by scientific and engineering experts drawn from industry, government, and academia after extensive reviews of the scientific literature related to the biological effects of RF energy.

The exposure limit set by the FCC for wireless mobile phones employs a unit of measurement known as the Specific Absorption Rate (SAR). The SAR is a measure of the rate of

absorption of RF energy by the human body expressed in units of watts per kilogram (W/kg). The FCC requires wireless phones to comply with a safety limit of 1.6 watts per kilogram (1.6 W/kg).

The FCC exposure limit incorporates a substantial margin of safety to give additional protection to the public and to account for any variations in measurements.

SAR tests are conducted using standard operating positions accepted by the FCC with the phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR level of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output.

Before a new model phone is available for sale to the public, it must be tested and certified to the FCC that it does not exceed the exposure limit established by the FCC. Tests for each model phone are performed in positions and locations (e.g. at the ear and worn on the body) as required by the FCC.

For body worn operation, this phone has been tested and meets FCC RF exposure guidelines when used with an accessory that contains no metal and that positions the handset a minimum of 1.5 cm from the body.

Use of other accessories may not ensure compliance with FCC RF exposure guidelines.

The FCC has granted an Equipment Authorization for this mobile phone with all reported SAR levels evaluated as in compliance with the FCC RF exposure guidelines. The maximum SAR values for this model phone as reported to the FCC are:

GMS 850

- Head: 0.168 W/Kg.
- Body-worn: 1.080 W/Kg.

PCS

- Head: 0.194 W/Kg.
- Body-worn: 0.420 W/Kg.

WCDMA 2

- Head: 0.815 W/Kg.
- Body-worn: 0.584 W/Kg.

WCDMA 5

- Head: 0.108 W/Kg.
- Body-worn: 0.292 W/Kg.

SAR information on this and other model phones can be viewed online at <http://www.fcc.gov/oet/ea>. To find information that pertains to a particular model phone, this site uses the phone FCC ID number which is usually printed somewhere on the case of the phone.

Sometimes it may be necessary to remove the battery pack to find the number. Once you have the FCC ID number for a particular phone, follow the instructions on the website and it should provide values for typical or maximum SAR for a particular phone. Additional product specific SAR information can also be obtained at www.fcc.gov/cgb/sar.

Samsung Mobile Products and Recycling

Samsung cares for the environment and encourages its customers to recycle Samsung mobile phones and genuine Samsung accessories.

Go to: <https://fun.samsungmobileusa.com/recycling/index.jsp> for more information.

UL Certified Travel Adapter

The Travel Adapter for this phone has met applicable UL safety requirements. Please adhere to the following safety instructions per UL guidelines.

FAILURE TO FOLLOW THE INSTRUCTIONS OUTLINED MAY LEAD TO SERIOUS PERSONAL INJURY AND POSSIBLE PROPERTY DAMAGE.

IMPORTANT SAFETY INSTRUCTIONS - SAVE THESE INSTRUCTIONS.

DANGER - TO REDUCE THE RISK OF FIRE OR ELECTRIC SHOCK, CAREFULLY FOLLOW THESE INSTRUCTIONS.

FOR CONNECTION TO A SUPPLY NOT IN NORTH AMERICA, USE AN ATTACHMENT PLUG ADAPTOR OF THE PROPER CONFIGURATION FOR THE POWER OUTLET. THIS POWER UNIT IS INTENDED TO BE CORRECTLY ORIENTATED IN A VERTICAL OR HORIZONTAL OR FLOOR MOUNT POSITION.

Consumer Information on Wireless Phones

The U.S. Food and Drug Administration (FDA) has published a series of Questions and Answers for consumers relating to radio frequency (RF) exposure from wireless phones. The FDA publication includes the following information:

What kinds of phones are the subject of this update?

The term wireless phone refers here to hand-held wireless phones with built-in antennas, often called "cell," "mobile," or "PCS" phones. These types of wireless phones can expose the user to measurable radio frequency energy (RF) because of the short distance between the phone and the user's head. These RF exposures are limited by Federal Communications Commission safety guidelines that were developed with the advice of FDA and other federal health and safety agencies.

When the phone is located at greater distances from the user, the exposure to RF is drastically lower because a person's RF exposure decreases rapidly with increasing distance from the source. The so-called "cordless phones," which have a base unit connected to the telephone wiring in a house, typically operate at far lower power levels, and thus produce RF exposures well within the FCC's compliance limits.

Do wireless phones pose a health hazard?

The available scientific evidence does not show that any health problems are associated with using wireless phones. There is no proof, however, that wireless phones are absolutely safe. Wireless phones emit low levels of radio frequency energy (RF) in the microwave range while being used. They also emit very low levels of RF when in the stand-by mode. Whereas high levels of RF can produce health effects (by heating tissue), exposure to

low level RF that does not produce heating effects causes no known adverse health effects. Many studies of low level RF exposures have not found any biological effects. Some studies have suggested that some biological effects may occur, but such findings have not been confirmed by additional research. In some cases, other researchers have had difficulty in reproducing those studies, or in determining the reasons for inconsistent results.

What is FDA's role concerning the safety of wireless phones?

Under the law, FDA does not review the safety of radiation-emitting consumer products such as wireless phones before they can be sold, as it does with new drugs or medical devices. However, the agency has authority to take action if wireless phones are shown to emit radio frequency energy (RF) at a level that is hazardous to the user. In such a case, FDA could require the manufacturers of wireless phones to notify users of the health hazard and to repair, replace or recall the phones so that the hazard no longer exists.

Although the existing scientific data do not justify FDA regulatory actions, FDA has urged the wireless phone industry to take a number of steps, including the following:

- Support needed research into possible biological effects of RF of the type emitted by wireless phones;

- Design wireless phones in a way that minimizes any RF exposure to the user that is not necessary for device function; and
- Cooperate in providing users of wireless phones with the best possible information on possible effects of wireless phone use on human health.

FDA belongs to an interagency working group of the federal agencies that have responsibility for different aspects of RF safety to ensure coordinated efforts at the federal level. The following agencies belong to this working group:

- National Institute for Occupational Safety and Health
- Environmental Protection Agency
- Federal Communications Commission
- Occupational Safety and Health Administration
- National Telecommunications and Information Administration

The National Institutes of Health participates in some interagency working group activities, as well.

FDA shares regulatory responsibilities for wireless phones with the Federal Communications Commission (FCC). All phones that are sold in the United States must comply with FCC safety guidelines that limit RF exposure. FCC relies on FDA and other health agencies for safety questions about wireless phones.

FCC also regulates the base stations that the wireless phone networks rely upon. While these base stations operate at higher power than do the wireless phones themselves, the RF exposures that people get from these base stations are typically thousands of times lower than those they can get from wireless phones.

Base stations are thus not the primary subject of the safety questions discussed in this document.

What are the results of the research done already?

The research done thus far has produced conflicting results, and many studies have suffered from flaws in their research methods. Animal experiments investigating the effects of radio frequency energy (RF) exposures characteristic of wireless phones have yielded conflicting results that often cannot be repeated in other laboratories. A few animal studies, however, have suggested that low levels of RF could accelerate the development of cancer in laboratory animals. However, many of the studies that showed increased tumor development used animals that had been genetically engineered or treated with cancer-causing chemicals so as to be pre-disposed to develop cancer in absence of RF exposure. Other studies exposed the animals to RF for up to 22 hours per day. These conditions are not similar to the conditions under which people use wireless

phones, so we don't know with certainty what the results of such studies mean for human health.

Three large epidemiology studies have been published since December 2000. Between them, the studies investigated any possible association between the use of wireless phones and primary brain cancer, glioma, meningioma, or acoustic neuroma, tumors of the brain or salivary gland, leukemia, or other cancers. None of the studies demonstrated the existence of any harmful health effects from wireless phones RF exposures.

However, none of the studies can answer questions about long-term exposures, since the average period of phone use in these studies was around three years.

What research is needed to decide whether RF exposure from wireless phones poses a health risk?

A combination of laboratory studies and epidemiological studies of people actually using wireless phones would provide some of the data that are needed. Lifetime animal exposure studies could be completed in a few years. However, very large numbers of animals would be needed to provide reliable proof of a cancer promoting effect if one exists. Epidemiological studies can provide data that is directly applicable to human populations, but ten or more years' follow-up may be needed to provide answers about some health effects, such as cancer.

This is because the interval between the time of exposure to a cancer-causing agent and the time tumors develop - if they do - may be many, many years. The interpretation of epidemiological studies is hampered by difficulties in measuring actual RF exposure during day-to-day use of wireless phones. Many factors affect this measurement, such as the angle at which the phone is held, or which model of phone is used.

What is FDA doing to find out more about the possible health effects of wireless phone RF?

FDA is working with the U.S. National Toxicology Program and with groups of investigators around the world to ensure that high priority animal studies are conducted to address important questions about the effects of exposure to radio frequency energy (RF).

FDA has been a leading participant in the World Health Organization international Electromagnetic Fields (EMF) Project since its inception in 1996. An influential result of this work has been the development of a detailed agenda of research needs that has driven the establishment of new research programs around the world. The Project has also helped develop a series of public information documents on EMF issues.

FDA and Cellular Telecommunications & Internet Association (CTIA) have a formal Cooperative Research and Development Agreement (CRADA) to do research on wireless phone safety.

FDA provides the scientific oversight, obtaining input from experts in government, industry, and academic organizations.

CTIA-funded research is conducted through contracts to independent investigators. The initial research will include both laboratory studies and studies of wireless phone users. The CRADA will also include a broad assessment of additional research needs in the context of the latest research developments around the world.

What steps can I take to reduce my exposure to radio frequency energy from my wireless phone?

If there is a risk from these products - and at this point we do not know that there is - it is probably very small. But if you are concerned about avoiding even potential risks, you can take a few simple steps to minimize your exposure to radio frequency energy (RF). Since time is a key factor in how much exposure a person receives, reducing the amount of time spent using a wireless phone will reduce RF exposure.

- If you must conduct extended conversations by wireless phone every day, you could place more distance between your body and the source of the RF, since the exposure level drops off dramatically with distance. For example, you could use a headset and carry the wireless phone away from your body or use a wireless phone connected to a remote antenna.

Again, the scientific data do not demonstrate that wireless phones are harmful. But if you are concerned about the RF exposure from these products, you can use measures like those described above to reduce your RF exposure from wireless phone use.

What about children using wireless phones?

The scientific evidence does not show a danger to users of wireless phones, including children and teenagers. If you want to take steps to lower exposure to radio frequency energy (RF), the measures described above would apply to children and teenagers using wireless phones. Reducing the time of wireless phone use and increasing the distance between the user and the RF source will reduce RF exposure.

Some groups sponsored by other national governments have advised that children be discouraged from using wireless phones at all. For example, the government in the United Kingdom distributed leaflets containing such a recommendation in December 2000.

They noted that no evidence exists that using a wireless phone causes brain tumors or other ill effects. Their recommendation to limit wireless phone use by children was strictly precautionary; it was not based on scientific evidence that any health hazard exists.

Do hands-free kits for wireless phones reduce risks from exposure to RF emissions?

Since there are no known risks from exposure to RF emissions from wireless phones, there is no reason to believe that hands-free kits reduce risks. Hands-free kits can be used with wireless phones for convenience and comfort. These systems reduce the absorption of RF energy in the head because the phone, which is the source of the RF emissions, will not be placed against the head. On the other hand, if the phone is mounted against the waist or other part of the body during use, then that part of the body will absorb more RF energy. Wireless phones marketed in the U.S. are required to meet safety requirements regardless of whether they are used against the head or against the body. Either configuration should result in compliance with the safety limit.

Do wireless phone accessories that claim to shield the head from RF radiation work?

Since there are no known risks from exposure to RF emissions from wireless phones, there is no reason to believe that accessories that claim to shield the head from those emissions reduce risks. Some products that claim to shield the user from RF absorption use special phone cases, while others involve nothing more than a metallic accessory attached to the phone. Studies have shown that these products generally do not work as

advertised. Unlike "hand-free" kits, these so-called "shields" may interfere with proper operation of the phone. The phone may be forced to boost its power to compensate, leading to an increase in RF absorption. In February 2002, the Federal Trade Commission (FTC) charged two companies that sold devices that claimed to protect wireless phone users from radiation with making false and unsubstantiated claims.

According to FTC, these defendants lacked a reasonable basis to substantiate their claim.

What about wireless phone interference with medical equipment?

Radio frequency energy (RF) from wireless phones can interact with some electronic devices. For this reason, FDA helped develop a detailed test method to measure electromagnetic interference (EMI) of implanted cardiac pacemakers and defibrillators from wireless telephones. This test method is now part of a standard sponsored by the Association for the Advancement of Medical Instrumentation (AAMI). The final draft, a joint effort by FDA, medical device manufacturers, and many other groups, was completed in late 2000. This standard will allow manufacturers to ensure that cardiac pacemakers and defibrillators are safe from wireless phone EMI. FDA has tested wireless phones and helped develop a voluntary standard sponsored by the Institute of Electrical and Electronic Engineers

(IEEE). This standard specifies test methods and performance requirements for hearing aids and wireless phones so that no interference occurs when a person uses a compatible phone and a compatible hearing aid at the same time. This standard was approved by the IEEE in 2000.

FDA continues to monitor the use of wireless phones for possible interactions with other medical devices. Should harmful interference be found to occur, FDA will conduct testing to assess the interference and work to resolve the problem.

Additional information on the safety of RF exposures from various sources can be obtained from the following organizations (Updated 12/1/2006):

- FCC RF Safety Program:
<http://www.fcc.gov/oet/rfsafety/>
- Environmental Protection Agency (EPA):
<http://www.epa.gov/radiation/>
- Occupational Safety and Health Administration's (OSHA):
<http://www.osha.gov/SLTC/radiofrequencyradiation/index.html>
- National Institute for Occupational Safety and Health (NIOSH):
<http://www.cdc.gov/niosh/homepage.html>
- World Health Organization (WHO):
<http://www.who.int/peh-emf/>
- International Commission on Non-Ionizing Radiation Protection:
<http://www.icnirp.de>

- National Radiation Protection Board (UK):
<http://www.hpa.org.uk/radiation>
- US Food and Drug Administration:
<http://www.fda.gov/cellphones>

Road Safety

Your wireless phone gives you the powerful ability to communicate by voice, almost anywhere, anytime. But an important responsibility accompanies the benefits of wireless phones, one that every user must uphold.

When driving a car, driving is your first responsibility. When using your wireless phone behind the wheel of a car, practice good common sense and remember the following tips:

1. Get to know your wireless phone and its features, such as speed dial and redial. If available, these features help you to place your call without taking your attention off the road.
2. When available, use a hands-free device. If possible, add an additional layer of convenience and safety to your wireless phone with one of the many hands free accessories available today.
3. Position your wireless phone within easy reach. Be able to access your wireless phone without removing your eyes from the road. If you get an incoming call at an inconvenient time, let your voice mail answer it for you.
4. Let the person you are speaking with know you are driving; if necessary, suspend the call in heavy traffic or hazardous weather conditions. Rain, sleet, snow, ice and even heavy traffic can be hazardous.
5. Do not take notes or look up phone numbers while driving. Jotting down a "to do" list or flipping through your address book takes attention away from your primary responsibility, driving safely.
6. Dial sensibly and assess the traffic; if possible, place calls when you are not moving or before pulling into traffic. Try to plan calls when your car will be stationary. If you need to make a call while moving, dial only a few numbers, check the road and your mirrors, then continue.

7. Do not engage in stressful or emotional conversations that may be distracting. Make people you are talking with aware you are driving and suspend conversations that have the potential to divert your attention from the road.
8. Use your wireless phone to call for help. Dial 9-1-1 or other local emergency number in the case of fire, traffic accident or medical emergencies.
9. Use your wireless phone to help others in emergencies. If you see an auto accident, crime in progress or other serious emergency where lives are in danger, call 9-1-1 or other local emergency number, as you would want others to do for you.
10. Call roadside assistance or a special non-emergency wireless assistance number when necessary. If you see a broken-down vehicle posing no serious hazard, a broken traffic signal, a minor traffic accident where no one appears injured, or a vehicle you know to be stolen, call roadside assistance or other special non-emergency number.

"The wireless industry reminds you to use your phone safely when driving."

For more information, please call 1-888-901-SAFE, or visit our web-site www.ctia.org.

Important!: If you are using a handset other than a standard numeric keypad, please call 1-888-901-7233.

Provided by the Cellular Telecommunications & Internet Association.

Responsible Listening

Caution!: Avoid potential hearing loss.

Damage to hearing occurs when a person is exposed to loud sounds over time. The risk of hearing loss increases as sound is played louder and for longer durations. Prolonged exposure to loud sounds (including music) is the most common cause of preventable hearing loss. Some scientific research suggests that using portable audio devices, such as portable music players and cellular telephones, at high volume settings for long durations may lead to permanent noise-induced hearing loss. This includes the use of headphones (including headsets, earbuds, and Bluetooth or other wireless devices). Exposure to very loud sound has also been associated in some studies with tinnitus (a ringing in the ear), hypersensitivity to sound and distorted hearing.

Individual susceptibility to noise-induced hearing loss and potential hearing problem varies. Additionally, the amount of sound produced by a portable audio device varies depending on the nature of the sound, the device settings, and the headphones that are used. As a result, there is no single volume setting that is appropriate for everyone or for every combination of sound, settings and equipment.

You should follow some commonsense recommendations when using any portable audio device:

- Set the volume in a quiet environment and select the lowest volume at which you can hear adequately.
- When using headphones, turn the volume down if you cannot hear the people speaking near you or if the person sitting next to you can hear what you are listening to.
- Do not turn the volume up to block out noisy surroundings. If you choose to listen to your portable device in a noisy environment, you noise-cancelling headphones to block out background environmental noise. By blocking background environment noise, noise cancelling headphones should allow you to hear the music at lower volumes than when using earbuds.
- Limit the amount of time you listen. As the volume increases, less time is required before you hearing could be affected.

- Avoid using headphones after exposure to extremely loud noises, such as rock concerts, that might cause temporary hearing loss. Temporary hearing loss might cause unsafe volumes to sound normal.
- Do not listen at any volume that causes you discomfort. If you experience ringing in your ears, hear muffled speech or experience any temporary hearing difficulty after listening to your portable audio device, discontinue use and consult your doctor.

You can obtain additional information on this subject from the following sources:

American Academy of Audiology

11730 Plaza American Drive, Suite 300

Reston, VA 20190

Voice: (800) 222-2336

Email: info@audiology.org

Internet: <http://www.audiology.org>

National Institute on Deafness and Other Communication Disorders

National Institutes of Health

31 Center Drive, MSC 2320

Bethesda, MD 20892-2320

Voice: (301) 496-7243

Email: nidcdinfo@nih.gov

Internet: <http://www.cdc.gov/niosh/topics/noise/default.html>

National Institute for Occupational Safety and Health

Hubert H. Humphrey Bldg.

200 Independence Ave., SW

Washington, DC 20201

Voice: 1-800-35-NIOSH (1-800-356-4647)

Internet: <http://www.cdc.gov/niosh/topics/noise/default.html>

Operating Environment

Remember to follow any special regulations in force in any area and always switch your phone off whenever it is forbidden to use it, or when it may cause interference or danger.

When connecting the phone or any accessory to another device, read its user's guide for detailed safety instructions. Do not connect incompatible products.

As with other mobile radio transmitting equipment, users are advised that for the satisfactory operation of the equipment and for the safety of personnel, it is recommended that the equipment should only be used in the normal operating position (held to your ear with the antenna pointing over your shoulder if you are using an external antenna).

Using Your Phone Near Other Electronic Devices

Most modern electronic equipment is shielded from radio frequency (RF) signals. However, certain electronic equipment may not be shielded against the RF signals from your wireless phone. Consult the manufacturer to discuss alternatives.

Implantable Medical Devices

A minimum separation of six (6) inches should be maintained between a handheld wireless phone and an implantable medical device, such as a pacemaker or implantable cardioverter defibrillator, to avoid potential interference with the device.

Persons who have such devices:

- Should ALWAYS keep the phone more than six (6) inches from their implantable medical device when the phone is turned ON;
- Should not carry the phone in a breast pocket;
- Should use the ear opposite the implantable medical device to minimize the potential for interference;

- Should turn the phone OFF immediately if there is any reason to suspect that interference is taking place;
- Should read and follow the directions from the manufacturer of your implantable medical device. If you have any questions about using your wireless phone with such a device, consult your health care provider.

For more information see:

<http://www.fcc.gov/oet/rfsafety/rf-faqs.html>

FCC Hearing-Aid Compatibility (HAC) Regulations for Wireless Devices

On July 10, 2003, the U.S. Federal Communications Commission (FCC) Report and Order in WT Docket 01-309 modified the exception of wireless phones under the Hearing Aid Compatibility Act of 1988 (HAC Act) to require digital wireless phones be compatible with hearing-aids.

The intent of the HAC Act is to ensure reasonable access to telecommunications services for persons with hearing disabilities.

While some wireless phones are used near some hearing devices (hearing aids and cochlear implants), users may detect a buzzing, humming, or whining noise. Some hearing devices are more immune than others to this interference noise, and phones also vary in the amount of interference they generate.

The wireless telephone industry has developed a rating system for wireless phones, to assist hearing device users find phones that may be compatible with their hearing devices. Not all phones have been rated. Phones that are rated have the rating on their box or a label located on the box.


The ratings are not guarantees. Results will vary depending on the user's hearing device and hearing loss. If your hearing device happens to be vulnerable to interference, you may not be able to use a rated phone successfully. Trying out the phone with your hearing device is the best way to evaluate it for your personal needs.

M-Ratings: Phones rated M3 or M4 meet FCC requirements and are likely to generate less interference to hearing devices than phones that are not labeled. M4 is the better/higher of the two ratings.

T-Ratings: Phones rated T3 or T4 meet FCC requirements and are likely to generate less interference to hearing devices than phones that are not labeled. T4 is the better/higher of the two ratings.

Hearing devices may also be rated. Your hearing device manufacturer or hearing health professional may help you find this rating. Higher ratings mean that the hearing device is relatively immune to interference noise. The hearing aid and wireless phone rating values are then added together. A sum of 5

is considered acceptable for normal use. A sum of 6 is considered for best use.



In the above example, if a hearing aid meets the M2 level rating and the wireless phone meets the M3 level rating, the sum of the two values equal M5. This is synonymous for T ratings. This should provide the hearing aid user with "normal usage" while using their hearing aid with the particular wireless phone. "Normal usage" in this context is defined as a signal quality that is acceptable for normal operation.

The M mark is intended to be synonymous with the U mark. The T mark is intended to be synonymous with the UT mark. The M and T marks are recommended by the Alliance for Telecommunications Industries Solutions (ATIS). The U and UT marks are referenced in Section 20.19 of the FCC Rules.

The HAC rating and measurement procedure are described in the American National Standards Institute (ANSI) C63.19 standard.

Other Medical Devices

If you use any other personal medical devices, consult the manufacturer of your device to determine if it is adequately shielded from external RF energy. Your physician may be able to assist you in obtaining this information. Switch your phone off in health care facilities when any regulations posted in these areas instruct you to do so. Hospitals or health care facilities may be using equipment that could be sensitive to external RF energy.

Vehicles

RF signals may affect improperly installed or inadequately shielded electronic systems in motor vehicles. Check with the manufacturer or its representative regarding your vehicle. You should also consult the manufacturer of any equipment that has been added to your vehicle.

Posted Facilities

Switch your phone off in any facility where posted notices require you to do so.

Potentially Explosive Environments

Switch your phone off when in any area with a potentially explosive atmosphere and obey all signs and instructions. Sparks in such areas could cause an explosion or fire resulting in bodily injury or even death.

Users are advised to switch the phone off while at a refueling point (service station). Users are reminded of the need to observe restrictions on the use of radio equipment in fuel depots (fuel storage and distribution areas), chemical plants or where blasting operations are in progress.


Areas with a potentially explosive atmosphere are often but not always clearly marked. They include below deck on boats, chemical transfer or storage facilities, vehicles using liquefied petroleum gas (such as propane or butane), areas where the air contains chemicals or particles, such as grain, dust or metal powders, and any other area where you would normally be advised to turn off your vehicle engine.

Emergency Calls

This phone, like any wireless phone, operates using radio signals, wireless and landline networks as well as user-programmed functions, which cannot guarantee connection in all conditions. Therefore, you should never rely solely on any wireless phone for essential communications (medical emergencies, for example).

Remember, to make or receive any calls the phone must be switched on and in a service area with adequate signal strength. Emergency calls may not be possible on all wireless phone networks or when certain network services and/or phone features are in use. Check with local service providers.

To make an emergency call:

1. If the phone is not on, switch it on.
2. Key in the emergency number for your present location (for example, 911 or other official emergency number).
Emergency numbers vary by location.
3. Press the  key.

If certain features are in use (call barring, for example), you may first need to deactivate those features before you can make an emergency call. Consult this document and your local cellular service provider.

When making an emergency call, remember to give all the necessary information as accurately as possible. Remember that your phone may be the only means of communication at the scene of an accident; do not cut off the call until given permission to do so.

Restricting Children's access to your Phone

Your phone is not a toy. Children should not be allowed to play with it because they could hurt themselves and others, damage the phone or make calls that increase your phone bill.

FCC Notice and Cautions

FCC Notice

The phone may cause TV or radio interference if used in close proximity to receiving equipment. The FCC can require you to stop using the phone if such interference cannot be eliminated.

Vehicles using liquefied petroleum gas (such as propane or butane) must comply with the National Fire Protection Standard (NFPA-58). For a copy of this standard, contact the National Fire Protection Association, One Batterymarch Park, Quincy, MA 02269, Attn: Publication Sales Division.

Cautions

Any changes or modifications to your phone not expressly approved in this document could void your warranty for this equipment, and void your authority to operate this equipment. Only use approved batteries, antennas and chargers. The use of any unauthorized accessories may be dangerous and void the phone warranty if said accessories cause damage or a defect to the phone.

Although your phone is quite sturdy, it is a complex piece of equipment and can be broken. Avoid dropping, hitting, bending or sitting on it.

Other Important Safety Information

- Only qualified personnel should service the phone or install the phone in a vehicle. Faulty installation or service may be dangerous and may invalidate any warranty applicable to the device.
- Check regularly that all wireless phone equipment in your vehicle is mounted and operating properly.
- Do not store or carry flammable liquids, gases or explosive materials in the same compartment as the phone, its parts or accessories.
- For vehicles equipped with an air bag, remember that an air bag inflates with great force. Do not place objects, including both installed or portable wireless equipment in the area over the air bag or in the air bag deployment area. If wireless equipment is improperly installed and the air bag inflates, serious injury could result.
- Switch your phone off before boarding an aircraft. The use of wireless phone in aircraft is illegal and may be dangerous to the aircraft's operation.
- Failure to observe these instructions may lead to the suspension or denial of telephone services to the offender, or legal action, or both.

Product Performance

Getting the Most Out of Your Signal Reception

The quality of each call you make or receive depends on the signal strength in your area. Your phone informs you of the current signal strength by displaying a number of bars next to the signal strength icon. The more bars displayed, the stronger the signal.

If you're inside a building, being near a window may give you better reception.

Understanding the Power Save Feature

If your phone is unable to find a signal after searching, a Power Save feature is automatically activated. If your phone is active, it periodically rechecks service availability or you can check it yourself by pressing any key.

Anytime the Power Save feature is activated, a message displays on the screen. When a signal is found, your phone returns to standby mode.

Understanding How Your Phone Operates

Your phone is basically a radio transmitter and receiver. When it's turned on, it receives and transmits radio frequency (RF) signals. When you use your phone, the system handling your call controls the power level. This power can range from 0.006 watts to 0.2 watts in digital mode.

Maintaining Your Phone's Peak Performance

For the best care of your phone, only authorized personnel should service your phone and accessories. Faulty service may void the warranty.

There are several simple guidelines to operating your phone properly and maintaining safe, satisfactory service.

- To ensure that the Hearing Aid Compatibility rating for your phone is maintained, secondary transmitters such as Bluetooth and WLAN components must be disabled during a call.
- If your phone is equipped with an external antenna, hold the phone with the antenna raised, fully-extended and over your shoulder.
- Do not hold, bend or twist the phone's antenna, if applicable.
- Do not use the phone if the antenna is damaged.
- If your phone is equipped with an internal antenna, obstructing the internal antenna could inhibit call performance.
- Speak directly into the phone's receiver.
- Avoid exposing your phone and accessories to rain or liquid spills. If your phone does get wet, immediately turn the power off and remove the battery. If it is inoperable, call Customer Care for service.

Availability of Various Features/Ring Tones

Many services and features are network dependent and may require additional subscription and/or usage charges. Not all features are available for purchase or use in all areas.

Downloadable Ring Tones may be available at an additional cost. Other conditions and restrictions may apply. See your service provider for additional information.

Battery Standby and Talk Time

Standby and talk times will vary depending on phone usage patterns and conditions. Battery power consumption depends on factors such as network configuration, signal strength, operating temperature, features selected, frequency of calls, and voice, data, and other application usage patterns.

Battery Precautions

- Avoid dropping the cell phone. Dropping it, especially on a hard surface, can potentially cause damage to the phone and battery. If you suspect damage to the phone or battery, take it to a service center for inspection.
- Never use any charger or battery that is damaged in any way.
- Do not modify or remanufacture the battery as this could result in serious safety hazards.

- If you use the phone near the network's base station, it uses less power; talk and standby time are greatly affected by the signal strength on the cellular network and the parameters set by the network operator.
- Follow battery usage, storage and charging guidelines found in the user's guide.
- Battery charging time depends on the remaining battery charge and the type of battery and charger used. The battery can be charged and discharged hundreds of times, but it will gradually wear out. When the operation time (talk time and standby time) is noticeably shorter than normal, it is time to buy a new battery.
- If left unused, a fully charged battery will discharge itself over time.
- Use only Samsung-approved batteries and recharge your battery only with Samsung-approved chargers. When a charger is not in use, disconnect it from the power source. Do not leave the battery connected to a charger for more than a week, since overcharging may shorten its life.
- Do not use incompatible cell phone batteries and chargers. Some Web sites and second-hand dealers, not associated with reputable manufacturers and carriers, might be selling incompatible or even counterfeit batteries and chargers. Consumers should purchase manufacturer or carrier recommended products and accessories. If unsure about whether a replacement battery or charger is compatible, contact the manufacturer of the battery or charger.

- Misuse or use of incompatible phones, batteries, and charging devices could result in damage to the equipment and a possible risk of fire, explosion, leakage, or other serious hazard.
- Extreme temperatures will affect the charging capacity of your battery: it may require cooling or warming first.
- Do not leave the battery in hot or cold places, such as in a car in summer or winter conditions, as you will reduce the capacity and lifetime of the battery. Always try to keep the battery at room temperature. A phone with a hot or cold battery may temporarily not work, even when the battery is fully charged. Li-ion batteries are particularly affected by temperatures below 0 °C (32 °F).
- Do not place the phone in areas that may get very hot, such as on or near a cooking surface, cooking appliance, iron, or radiator.
- Do not get your phone or battery wet. Even though they will dry and appear to operate normally, the circuitry could slowly corrode and pose a safety hazard.
- Do not short-circuit the battery. Accidental short-circuiting can occur when a metallic object (coin, clip or pen) causes a direct connection between the + and - terminals of the battery (metal strips on the battery), for example when you carry a spare battery in a pocket or bag. Short-circuiting the terminals may damage the battery or the object causing the short-circuiting.
- Do not permit a battery out of the phone to come in contact with metal objects, such as coins, keys or jewelry.

- Do not crush, puncture or put a high degree of pressure on the battery as this can cause an internal short-circuit, resulting in overheating.
- Dispose of used batteries in accordance with local regulations. In some areas, the disposal of batteries in household or business trash may be prohibited. For safe disposal options for Li-Ion batteries, contact your nearest Samsung authorized service center. Always recycle. Do not dispose of batteries in a fire.

Care and Maintenance

Your phone is a product of superior design and craftsmanship and should be treated with care. The suggestions below will help you fulfill any warranty obligations and allow you to enjoy this product for many years.

- Keep the phone and all its parts and accessories out of the reach of small children.
- Keep the phone dry. Precipitation, humidity and liquids contain minerals that will corrode electronic circuits.
- Do not use the phone with a wet hand. Doing so may cause an electric shock to you or damage to the phone.
- Do not use or store the phone in dusty, dirty areas, as its moving parts may be damaged.
- Do not store the phone in hot areas. High temperatures can shorten the life of electronic devices, damage batteries, and warp or melt certain plastics.

- Do not store the phone in cold areas. When the phone warms up to its normal operating temperature, moisture can form inside the phone, which may damage the phone's electronic circuit boards.
- Do not drop, knock or shake the phone. Rough handling can break internal circuit boards.
- Do not use harsh chemicals, cleaning solvents or strong detergents to clean the phone. Wipe it with a soft cloth slightly dampened in a mild soap-and-water solution.
- Do not paint the phone. Paint can clog the device's moving parts and prevent proper operation.
- Do not put the phone in or on heating devices, such as a microwave oven, a stove or a radiator. The phone may explode when overheated.
- If your phone is equipped with an external antenna, use only the supplied or an approved replacement antenna. Unauthorized antennas or modified accessories may damage the phone and violate regulations governing radio devices.
- If the phone, battery, charger or any accessory is not working properly, take it to your nearest qualified service facility. The personnel there will assist you, and if necessary, arrange for service.

Section 20: Warranty Information

Standard Limited Warranty

What is Covered and For How Long?

SAMSUNG TELECOMMUNICATIONS AMERICA, LLC ("SAMSUNG") warrants to the original purchaser ("Purchaser") that SAMSUNG's Phones and accessories ("Products") are free from defects in material and workmanship under normal use and service for the period commencing upon the date of purchase and continuing for the following specified period of time after that date:

Phone	1 Year
Batteries	1 Year
Leather Case	90 Days
Holster	90 Days
Other Phone Accessories	1 Year

What is Not Covered? This Limited Warranty is conditioned upon proper use of Product by Purchaser. This Limited Warranty does not cover: (a) defects or damage resulting from accident, misuse, abuse, neglect, unusual physical, electrical or electromechanical stress, or modification of any part of Product, including antenna, or cosmetic damage; (b) equipment that has the serial number

removed or made illegible; (c) any plastic surfaces or other externally exposed parts that are scratched or damaged due to normal use; (d) malfunctions resulting from the use of Product in conjunction with accessories, products, or ancillary/peripheral equipment not furnished or approved by SAMSUNG; (e) defects or damage from improper testing, operation, maintenance, installation, or adjustment; (f) installation, maintenance, and service of Product, or (g) Product used or purchased outside the United States or Canada.

This Limited Warranty covers batteries only if battery capacity falls below 80% of rated capacity or the battery leaks, and this Limited Warranty does not cover any battery if (i) the battery has been charged by a battery charger not specified or approved by SAMSUNG for charging the battery, (ii) any of the seals on the battery are broken or show evidence of tampering, or (iii) the battery has been used in equipment other than the SAMSUNG phone for which it is specified.

What are SAMSUNG's Obligations? During the applicable warranty period, SAMSUNG will repair or replace, at SAMSUNG's sole option, without charge to Purchaser, any defective component part of Product. To obtain service under this Limited Warranty, Purchaser must return Product to an authorized phone service

facility in an adequate container for shipping, accompanied by Purchaser's sales receipt or comparable substitute proof of sale showing the date of purchase, the serial number of Product and the sellers' name and address. To obtain assistance on where to deliver the Product, call Samsung Customer Care at 1-888-987-4357. Upon receipt, SAMSUNG will promptly repair or replace the defective Product. SAMSUNG may, at SAMSUNG's sole option, use rebuilt, reconditioned, or new parts or components when repairing any Product or replace Product with a rebuilt, reconditioned or new Product. Repaired/replaced leather cases, pouches and holsters will be warranted for a period of ninety (90) days. All other repaired/replaced Product will be warranted for a period equal to the remainder of the original Limited Warranty on the original Product or for 90 days, whichever is longer. All replaced parts, components, boards and equipment shall become the property of SAMSUNG.

If SAMSUNG determines that any Product is not covered by this Limited Warranty, Purchaser must pay all parts, shipping, and labor charges for the repair or return of such Product.

WHAT ARE THE LIMITS ON SAMSUNG'S WARRANTY/LIABILITY?

EXCEPT AS SET FORTH IN THE EXPRESS WARRANTY CONTAINED HEREIN, PURCHASER TAKES THE PRODUCT "AS IS," AND SAMSUNG MAKES NO WARRANTY OR REPRESENTATION AND THERE ARE NO CONDITIONS, EXPRESS OR IMPLIED, STATUTORY

OR OTHERWISE, OF ANY KIND WHATSOEVER WITH RESPECT TO THE PRODUCT, INCLUDING BUT NOT LIMITED TO:

- THE MERCHANTABILITY OF THE PRODUCT OR ITS FITNESS FOR ANY PARTICULAR PURPOSE OR USE;
- WARRANTIES OF TITLE OR NON-INFRINGEMENT;
- DESIGN, CONDITION, QUALITY, OR PERFORMANCE OF THE PRODUCT;
- THE WORKMANSHIP OF THE PRODUCT OR THE COMPONENTS CONTAINED THEREIN; OR
- COMPLIANCE OF THE PRODUCT WITH THE REQUIREMENTS OF ANY LAW, RULE, SPECIFICATION OR CONTRACT PERTAINING THERETO.

NOTHING CONTAINED IN THE INSTRUCTION MANUAL SHALL BE CONSTRUED TO CREATE AN EXPRESS WARRANTY OF ANY KIND WHATSOEVER WITH RESPECT TO THE PRODUCT. ALL IMPLIED WARRANTIES AND CONDITIONS THAT MAY ARISE BY OPERATION OF LAW, INCLUDING IF APPLICABLE THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, ARE HEREBY LIMITED TO THE SAME DURATION OF TIME AS THE EXPRESS WRITTEN WARRANTY STATED HEREIN. SOME STATES/PROVINCES DO NOT ALLOW LIMITATIONS ON HOW LONG AN IMPLIED WARRANTY LASTS, SO THE ABOVE LIMITATION MAY NOT APPLY TO YOU. IN ADDITION, SAMSUNG SHALL NOT BE LIABLE FOR ANY DAMAGES OF ANY KIND RESULTING FROM THE PURCHASE, USE, OR MISUSE OF, OR INABILITY TO USE THE PRODUCT OR ARISING DIRECTLY OR INDIRECTLY FROM THE USE

OR LOSS OF USE OF THE PRODUCT OR FROM THE BREACH OF THE EXPRESS WARRANTY, INCLUDING INCIDENTAL, SPECIAL, CONSEQUENTIAL OR SIMILAR DAMAGES, OR LOSS OF ANTICIPATED PROFITS OR BENEFITS, OR FOR DAMAGES ARISING FROM ANY TORT (INCLUDING NEGLIGENCE OR GROSS NEGLIGENCE) OR FAULT COMMITTED BY SAMSUNG, ITS AGENTS OR EMPLOYEES, OR FOR ANY BREACH OF CONTRACT OR FOR ANY CLAIM BROUGHT AGAINST PURCHASER BY ANY OTHER PARTY. SOME STATES/PROVINCES DO NOT ALLOW THE EXCLUSION OR LIMITATION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE LIMITATION OR EXCLUSION MAY NOT APPLY TO YOU. THIS WARRANTY GIVES YOU SPECIFIC LEGAL RIGHTS, AND YOU MAY ALSO HAVE OTHER RIGHTS, WHICH VARY FROM STATE TO STATE/PROVINCE TO PROVINCE. THIS LIMITED WARRANTY SHALL NOT EXTEND TO ANYONE OTHER THAN THE ORIGINAL PURCHASER OF THIS PRODUCT AND STATES PURCHASER'S EXCLUSIVE REMEDY. IF ANY PORTION OF THIS LIMITED WARRANTY IS HELD ILLEGAL OR UNENFORCEABLE BY REASON OF ANY LAW, SUCH PARTIAL ILLEGALITY OR UNENFORCEABILITY SHALL NOT AFFECT THE ENFORCEABILITY FOR THE REMAINDER OF THIS LIMITED WARRANTY WHICH PURCHASER ACKNOWLEDGES IS AND WILL ALWAYS BE CONSTRUED TO BE LIMITED BY ITS TERMS OR AS LIMITED AS THE LAW PERMITS. THE PARTIES UNDERSTAND THAT THE PURCHASER MAY USE THIRD-PARTY SOFTWARE OR EQUIPMENT

IN CONJUNCTION WITH THE PRODUCT. SAMSUNG MAKES NO WARRANTIES OR REPRESENTATIONS AND THERE ARE NO CONDITIONS, EXPRESS OR IMPLIED, STATUTORY OR OTHERWISE, AS TO THE QUALITY, CAPABILITIES, OPERATIONS, PERFORMANCE OR SUITABILITY OF ANY THIRDPARTY SOFTWARE OR EQUIPMENT, WHETHER SUCH THIRD-PARTY SOFTWARE OR EQUIPMENT IS INCLUDED WITH THE PRODUCT DISTRIBUTED BY SAMSUNG OR OTHERWISE, INCLUDING THE ABILITY TO INTEGRATE ANY SUCH SOFTWARE OR EQUIPMENT WITH THE PRODUCT. THE QUALITY, CAPABILITIES, OPERATIONS, PERFORMANCE AND SUITABILITY OF ANY SUCH THIRD-PARTY SOFTWARE OR EQUIPMENT LIE SOLELY WITH THE PURCHASER AND THE DIRECT VENDOR, OWNER OR SUPPLIER OF SUCH THIRD-PARTY SOFTWARE OR EQUIPMENT, AS THE CASE MAY BE.

This Limited Warranty allocates risk of Product failure between Purchaser and SAMSUNG, and SAMSUNG's Product pricing reflects this allocation of risk and the limitations of liability contained in this Limited Warranty. The agents, employees, distributors, and dealers of SAMSUNG are not authorized to make modifications to this Limited Warranty, or make additional warranties binding on SAMSUNG. Accordingly, additional statements such as dealer advertising or presentation, whether oral or written, do not constitute warranties by SAMSUNG and should not be relied upon.

Precautions for Transfer and Disposal

If data stored on this device is deleted or reformatted using the standard methods, the data only appears to be removed on a superficial level, and it may be possible for someone to retrieve and reuse the data by means of special software.

To avoid unintended information leaks and other problems of this sort, it is recommended that the device be returned to Samsung's Customer Care Center for an Extended File System (EFS) Clear which will eliminate all user memory and return all settings to default settings. Please contact the **Samsung Customer Care Center** for details.

Important! Please provide warranty information (proof of purchase) to Samsung's Customer Care Center in order to provide this service at no charge. If the warranty has expired on the device, charges may apply.

Customer Care Center:

1000 Klein Rd.

Plano, TX 75074

Toll Free Tel: 1.888.987.HELP (4357)

Samsung Telecommunications America, LLC:

1301 East Lookout Drive

Richardson, Texas 75082

Phone: 1-800-SAMSUNG (726-7864)

Important! If you are using a handset other than a standard numeric keypad, dial the numbers listed in brackets.

Phone: 1-888-987-HELP (4357)

©2008 Samsung Telecommunications America. All rights reserved.

No reproduction in whole or in part allowed without prior written approval. Specifications and availability subject to change without notice.

A

Accessing AT&T Music 129

Adding a New Contact

Adding More Fields 89

Deleting Fields 89

During a Call 90

Idle Screen 87

Address Book

Adding a New Contact 87

Address Book Entry Options 92

Checking the Used Space 97

Copying an entry to the Phone 96

Copying Entry to Phone 96

Copying Entry to SIM Card 95

Deleting all of the Address Book

Entries 96

Dialing a Number 91

FDN (Fixed Dialing Number) Mode

93

Finding an Address Book Entry 91

Group Settings 94

Managing Address Book Entries 95

Own Phone Number 93

Service Dialing Numbers 97

Using Contacts List 91

Address Book Settings 87

AIM 121

Alarms 104, 145

Answer Tones 100, 127

AOL 121

Application Settings

Record Audio 73

Video Share 72

Applications

Alarms 145

Calculator 148

Calendar 146

Converter 149

Memo 148

Music Player 129

Record Audio 144

Stopwatch 150

Tasks 148

Timer 150

Tools 144

Using the Camcorder 114

Using the Camera 104, 108

World Clock 149

AT&T GPS

Navigator 140

AT&T Mobile TV 80

Full-Screen Mode 83

Getting Started 80

Overview 80

Parental Controls 85

PIN 85

Player 82

Program Guide 83

Refresh Subscription 86

Subscribing 81

Subscription manager 84

Updates 86

AT&T Music

Adding Music to your Handset 130

Community 139

Music Apps 139

Music Player 129

Music Videos 78, 139

MusicID 136

- Pandora 139
- Playing Music Through a Stereo Bluetooth Device 132
- Playing Music while Using the Phone 132
- Playlists 133
- Shop Music 131
- Transferring Music From the Digital Music Stores 131
- Transferring Music Windows Media Player 134
- XM Radio 138

AT&T Yahoo! 121

Audio 99

Audio Folder 119, 145

B

Backlight

settings 59

Battery

charging 7

Installing 6

Low Battery Indicator 8

BellSouth 121

Birthday Widget 27

Block Caller 32

Bluetooth Device

Stereo 132

Brightness 59

Browser

Preferences 159

Settings 161

C

Calculator 105

Calendar 146

Deleting an Event 147

Viewing an Event 147

Call Functions 28

3-Way Calling (Multi-Party Calling)
39

Address Book 29

Adjusting the Call Volume 36

Answering a Call 30

Call Back Missed Call 33

Call Time 35

Call Waiting 39

Correcting the Number 28

Data Counter 35

Deleting Missed Call 34

Dialing a Recent Number 29

Ending a Call 28

International Call 28

Making a Call 28

Missed Call Details 33

Options During a Call 36

Putting a Call on Hold 37

Recent Calls 32

Saving the Missed Call Number to
Address Book 34

Searching for a Number in Address
Book 38

Send Message to Missed Call 34

Using the Speakerphone 38

Viewing All Calls 32

Viewing Missed Calls 33

Camcorder 114

Accessing the Video Folder 116

Camcorder Options 115

Shooting Video 114

Camcorder Options

Camcorder Options after a Video is
Taken 115

Camera 104

- Accessing the Pictures Folder 112
- Camera Options 109
- Picture Folder 112
- Taking Pictures 104, 108

Camera Options

- Settings 110
- Shooting mode 109
- Timer 111
- White Balance 111

Cellular Video (CV) 76

- Adding a Video Alert 77
- Customizing 77
- My Purchases 77
- Parental Controls 78
- Updating Favorites 77
- Video Categories 77

Change Phone Password 64

Changing Your Settings 50

Charging battery 7

Check PIN code 63

Clear Phone Memory 74

Converter 106

Cookies

- Deleting 158
- Options 158

Copying a URL 156

D

Digital Music Stores 131

Display

- icons 15

E

Entering Text 40

- Changing the Text Entry Mode 41, 45, 48
- Using Multitap Mode 42
- Using Numeric 43
- Using Symbols 43
- Using T9 Mode 41

Event Widget 27

F

FDN

- Changing the State 93
- Creating New Numbers 93

Fixed Dialing Mode 64

Full Screen Mode 153

G

Games 127

Games & Apps 101

Getting Started 5

- Setting Up Your Phone 5
- Voice mail 10

GPS Applications 127, 142

- Shopping For 127, 142

Graphics 127

Group

- Adding an Entry 94
- Creating New Group 94
- Editing 95
- Removing an Entry 95

Group Settings

- Editing a Caller Group 95

H

HAC 177

Handwriting 44

- Changing Text Input 45
- Entering Characters 46
- Entering Numbers 46
- Entering Symbols 47

Health and Safety Information 165

I

Icons, description 15

Illumination 59

IMS Settings 71

In-Call Options 30

International Call 28

J

Join 39

K

Keyboard

 Changing Text Input 48

Keyboard 40, 48

L

Landscape 48

Lock Applications 63

M

MEdia Mall

 Answer Tones 127

 Games 127

 Multimedia Store 128

 Options 128

 Ringtones 126

 Tools & Apps 127

MEdia Net and WAP

 Accessing the MEdia Net Homepage
 160

 Accessing the MEdia Net Site 161

 Changing WAP Profiles 161

 Downloading Multimedia Files 126

 Navigating with the WAP Browser
 151

 Using Favorites 155

Memory

 Used Space 125

Memory Card Installation 6

Memory Management 74

 Used Space 74

Menu Navigation 19

Messaging

 Creating and Sending Text
 Messages 117

 Settings 122

 Signing into Your Mobile Email 121

 Types of Messages 117

 Using Message Options 120

microSD card

 Installing 6

Mobile Banking 102

Mobile Email

 AIM 121

 AOL 121

 AT&T Yahoo! 121

 BellSouth 121

 Windows Live Mail 121

M-Ratings 177

Multitap Keys 43

Multitap Mode 40

Multitasking 132

 Functions 17

 Menu 17

Music 100

Music File Extensions

 3GP 129

 AAC 129

 AAC+ 129

 eAAC+ 129

 M4A 129

 MP3 129

 MP4 129

 MPEG 129

 WMA 129

Music Player 129

Music Videos

Music Video Options 79

Viewing a Video Clip 79

MusicID

Exit 138

Help me out 138

ID song! 137

Manage IDs 137

Mute 36, 38

My Stuff

Alarms 104

Answer Tones 100

Audio 99

Calculator 105

Calendar 105

Camera 104

Converter 106

Games & Apps 101

Memo 105

Mobile Banking 102

Music 100

Other Files 106

Pictures 102

Recent Calls 105

Recorded Audio 100

Shop Applications 101

Shop Games 101

Stopwatch 106

Tasks 105

Timer 106

Tones 99

Used Space 107

Videos 104

World Clock 106

N

Network Profile

Configuration 70

Network Selection 70

Number mode 40

P

Pandora 139

Paragraph

Inserting a Return 46

Parental Controls

Configuring Filters 78

Setup 78

Password

Changing 64

Phone

Front View 11

icons 15

Rear View 14

Side View 13

Switching On/Off 9

Phone Information 75

Phone Lock 63

Phone Safety 176

Phone Settings 61

Playlists

Adding songs to a Playlist 133

Creating a Playlist 133

Importing a Playlist from Windows

Media Player 136

Removing songs from a Playlist 133

Power Search tab 22

Powering

Off 9

On 9

Q

QWERTY Keyboard 48

R

Recent Calls 32, 105, 148

Record Audio

Audio Folder 119, 145

Recorded Audio 100

Creating 100

S

SAR values 165

Security 62

Sending a URL 156

Service Dialing Numbers 97

Settings

Address Book 87

Applications 72

Call Settings 66

Display and Light 57

Phone 61

Phone Information 75

Reset 73

Security 62

Software Update 75

Sound 50

Time & Date 60

SIM card

installation 5

Installing 5

Speakerphone Key 38

Standard Limited Warranty

185

Stopwatch 106

Swap 37

Symbol mode 40

T

T9 mode 40

Tasks 105

Text Input Mode

Changing within Handwriting 45

Changing within Keypad 41

Timer 106

Tones 99

Tools

Alarms 145

Calculator 148

Calendar 146

Camera 108

Converter 149

Memo 148

Recent Calls 148

Record Audio 144

Stopwatch 150

Tasks 148

Timer 150

World Clock 149

Touch Screen 9

Lock/Unlock 9

Transition Effect 59

T-Ratings 177

Travel Adapter 7

Using 7

TTY Settings 164

U

UL Certification 167

Understanding Your Phone 11

Features of Your Phone 11

Front View 11

Rear View 14

Side Views 13

Unmute 36

URL

Copying to Message 156

Entering Manually 154

Sending 156

Used Space 97, 107, 125

Using Favorites

Accessing a Web Site Using

Favorites 155

Adding Favorites 155

Deleting a Favorite 156

Editing Favorites 156

V

Video Categories

Viewing a Video Clip 76

Video Features 76

Video Share 30

IMS Settings 71

In-Call 32

Initiating and Receiving a Video

Share Session 30

Play a Recording 32

Settings 72

Videos 104

Voice Mail

Accessing 10

From Another Phone 10

Setup 10

W

Warranty Information 185

Widget

Activation 27

Event 27

Widgets 23

Accessing 26

Adding to the Widget bar 23

Deleting from the Widget bar 23

Rearranging 26

Undocking 26

Windows Live Hotmail 121

World Clock 149

Deleting an Entry 150

Y

Yellowpages 150